

\$87.75



2016 NATIONAL ELECTRICAL ESTIMATOR

By Mark C. Tyler

Includes inside the back cover:



Inside the back cover of this book you'll find a software download certificate. To access the download, follow the instructions printed there. The download includes the National Estimator, an easy to-use estimating program with all the cost estimates in this book. The software will run on PCs using Windows XP, Vista, 7, 8, or 10 operating systems.

Quarterly price updates on the Web are free and automatic all during 2016. You'll be prompted when it's time to collect the next update. A connection to the Web is required.

Download all of Craftsman's most popular costbooks for one low price with the Craftsman Site License. <http://CraftsmanSiteLicense.com>



- Turn your estimate into a bid.
- Turn your bid into a contract.
- ConstructionContractWriter.com



Craftsman Book Company
6058 Corte del Cedro, Carlsbad, CA 92011

Acknowledgments

The author wishes to thank the following individuals and companies for providing materials and information used in this book.

George H. Booth, Vice President Sales — Graybar Electric Company, Inc.

Steve Koundouriotis — P-W Western, Inc.

Don Geibel — Walker Division of Butler Manufacturing Company.

The tables on pages 439 and 440 are reprinted with permission from NFPA 70®-2014, the *National Electrical Code*®, Copyright 2013, National Fire Protection Association, Quincy, MA 02169. This reprinted material is not the complete and official position of the National Fire Protection Association on the referenced subject, which is represented only by the standard in its entirety.

National Electrical Code® and *NEC*® are registered trademarks of the National Fire Protection Association, Inc. Quincy, MA 02169.

Looking for Other Construction Reference Manuals?

Craftsman has the books to fill your needs. **Call toll-free 1-800-829-8123**
or write to Craftsman Book Company, 6058 Corte del Cedro, Carlsbad, CA 92011
for a **FREE CATALOG** of over 100 books, including how-to manuals,
annual cost books, and estimating software.
Visit our Web site: <http://www.craftsman-book.com>

Cover design: *Jennifer Johnson*

©2015 Craftsman Book Company
ISBN 978-1-57218-317-9
Published November 2015 for the year 2016.

Contents

| | | | |
|--|-----------|---|------------|
| How to Use This Book | 5 | Section 2: Wire and Cable | 88 |
| Improving Estimating Accuracy and Profits | 7 | Copper Building Wire..... | 93 |
| Section 1: Conduit and Fittings | 10 | Flexible Cords..... | 96 |
| EMT Conduit..... | 17 | Non-Metallic Cable | 100 |
| EMT Fittings | 18 | Armored Cable | 103 |
| Flexible Conduit..... | 28 | Power Cable..... | 104 |
| Flex Connectors | 29 | Aluminum Wire | 105 |
| Flex Couplings..... | 32 | Steel Messenger Strand..... | 114 |
| Liquid-Tight Flex Conduit..... | 33 | Wire Connectors..... | 115 |
| Liquid-Tight Flex Connectors..... | 34 | Connector Lugs | 118 |
| PVC Conduit..... | 37 | Section 3: Outlet Boxes | 119 |
| PVC Fittings..... | 38 | Handy Boxes and Covers, Switch Boxes | 123 |
| P&C Duct..... | 45 | Octagon and Square Boxes | 125 |
| P&C Fittings..... | 46 | 4" Square Switch Rings and Bar Hangers..... | 129 |
| Plastic Spacers..... | 47 | Gang Boxes..... | 132 |
| ENT Conduit and Fittings | 48 | Fiberglass Boxes..... | 133 |
| Galvanized Rigid Steel Conduit and Elbows | 49 | Plastic Boxes | 140 |
| GRS Elbows and Couplings | 51 | Cast Aluminum Boxes | 143 |
| GRS Terminations, IMC and Elbows..... | 52 | Sheet Metal Pull Boxes | 146 |
| IMC Elbows, Couplings and Running Thread..... | 53 | Floor Boxes, Covers, and Accessories..... | 153 |
| GRS Locknuts and Bushings..... | 54 | Section 4: Lighting Fixtures | 157 |
| GRS Nipples..... | 55 | Incandescent Light Fixtures..... | 161 |
| Aluminum Rigid Conduit Elbows & Nipples | 58 | Recessed Light Fixtures | 166 |
| ARC Nipples | 59 | Track Lighting..... | 168 |
| Metal Entrance Elbows and Conduit Bodies | 63 | Exit Fixtures..... | 171 |
| Conduit Body Covers..... | 64 | Fluorescent Fixtures | 174 |
| Conduit Body Gaskets and Bodies..... | 65 | HID Fixtures..... | 181 |
| Galvanized Capped Elbows | 65 | Light Poles..... | 195 |
| Galvanized Cast Boxes and Covers..... | 66 | LED Lamps..... | 199 |
| Expansion Fittings | 68 | Compact Fluorescent Lamps..... | 201 |
| Reducing Bushings..... | 69 | Incandescent Halogen, Quartz, LED Lamps | 202 |
| Reducing Washers | 70 | HID Lamps..... | 204 |
| Bushed Nipples | 71 | Sodium Lamps..... | 208 |
| Couplings and Offset Nipples | 72 | Fluorescent Lamps | 210 |
| Couplings and Connectors | 73 | Ceiling Fans..... | 217 |
| Connectors and Straps..... | 75 | Section 5: Wiring Devices | 218 |
| Conduit Clamps and Entrance Caps | 77 | Switches | 223 |
| PVC Coated Conduit and Fittings..... | 78 | Single and Duplex Receptacles..... | 237 |
| Hanger Fittings | 86 | Ground & Arc Fault Circuit Interrupters | 246 |
| Steel Channel and Fittings | 87 | Power Cord Receptacles and Plugs..... | 248 |
| | | Locking Receptacles | 253 |
| | | Plastic Locking Connectors and Plugs | 255 |
| | | Photo Controls..... | 259 |
| | | Wiring Device Plates | 260 |

Section 6: Service Entrance Equipment 269

| | |
|--------------------------------------|-----|
| Safety Switches | 275 |
| Plug Fuses..... | 283 |
| Cartridge Fuses | 285 |
| Circuit Breakers | 306 |
| Circuit Breaker Enclosures | 315 |
| Meter Sockets and Meter Centers..... | 317 |
| Loadcenters and Panelboards..... | 322 |
| Signal Cabinets | 327 |
| Wireway and Wireway Fittings | 328 |
| Transformers | 332 |

Section 7: Underfloor Raceway 335

| | |
|--|-----|
| Junction Boxes and Duct Supports | 339 |
| Underfloor Raceway Fittings | 341 |
| Service Fittings | 342 |

Section 8: Bus Duct 343

| | |
|-----------------------------|-----|
| Aluminum | 346 |
| Copper..... | 350 |
| Bus Duct Fittings | 354 |
| Bus Duct Plug-in Units..... | 356 |

Section 9: Cable Tray 358

| | |
|--|-----|
| Louvered Tray and Fittings..... | 361 |
| Aluminum Ladder Tray and Fittings..... | 363 |

Section 10: Signal Systems 365

| | |
|--------------------------------|-----|
| Bells, Buzzers and Sirens..... | 367 |
| Beacons and Chimes | 369 |
| Signal Systems..... | 370 |
| Detectors | 371 |
| Entry Control..... | 372 |

Section 11: Precast Concrete Access Boxes 373

| | |
|---|-----|
| Handholes, Pull Boxes and Manholes..... | 375 |
| Manhole Necking and Transformer Slabs | 376 |

Section 12: Equipment Hookup 377

| | |
|--|-----|
| Motor Hookup and Mechanical Hookup | 379 |
| Kitchen Hookup | 380 |
| Standby Generator Hookup..... | 381 |

Section 13: Motor Control Equipment 382

| | |
|-----------------------------|-----|
| Manual Motor Starters | 384 |
| Magnetic Contactors..... | 390 |
| Magnetic Starters | 398 |
| Combination Starters..... | 404 |
| Control Stations | 418 |

Section 14: Trenching and Excavation 420

| | |
|--------------------------------|-----|
| Trenching and Excavation | 422 |
|--------------------------------|-----|

Section 15: Surface Raceways 423

| | |
|---|-----|
| Steel Raceway, Fittings and Assemblies..... | 426 |
| Overhead Distribution Systems | 432 |
| Telephone-Power Poles | 436 |

Section 16: Grounding 438

| | |
|-------------------------------|-----|
| Copper Wire and Bushings..... | 442 |
| Lugs and Clamps..... | 443 |
| Ground Rods | 444 |
| Exothermic Connections..... | 445 |

Section 17: Assemblies 446

| | |
|-------------------------------|-----|
| EMT Conduit..... | 447 |
| Aluminum Flex Conduit | 451 |
| Steel Flex Conduit | 455 |
| PVC Conduit..... | 459 |
| Galvanized Rigid Conduit..... | 463 |
| Handy Box Switches..... | 467 |
| Sectional Box Switches | 471 |
| Switches, 1 and 2 Gang | 487 |
| Boxes and Receptacles..... | 508 |
| Troffer Fluorescent | 518 |

Section 18: Communications 519

| | |
|--|-----|
| Communications Cable | 521 |
| Contacts, Pins, Plugs, Receptacles..... | 528 |
| Subminiature D Connectors | 529 |
| Data Connectors..... | 532 |
| Baluns..... | 533 |
| Modular Couplers, Jacks, Connectors..... | 534 |

Wire Conversion Table 537

Section 19: Undercarpet Wiring Systems 538

| | |
|---|-----|
| Wiring, Cables, Connectors, Accessories | 539 |
|---|-----|

Index 542

How to Use This Book

This manual is a guide to the cost of installing electrical work in buildings. It lists costs to the electrical subcontractor for a wide variety of electrical work.

Before using any estimate in this book, you should understand one important point about estimating electrical construction costs. Estimating is an art, not a science. There's no estimate that fits all work. The manhour estimates in this book will be accurate for many jobs, but remember that no two jobs are identical. And no two crews complete all tasks in exactly the same amount of time. That's why electrical cost estimating requires exercising good judgment. Every estimate has to be custom-made for the specific job, crew and contractor. No estimating reference, computerized cost estimating system or estimating service can take into consideration all the variables that make each job unique.

This book isn't meant to replace well-informed decisions. But when supplemented with an estimator's professional evaluation, the figures in this manual will be a good aid in developing a reliable cost of electrical systems.



Inside the back cover of this book you'll find a software download certificate. To access the download, follow the instructions printed there. The download includes the National Estimator, an easy-to-use estimating program with all the cost estimates in this book. The software will run on PCs using Windows XP, Vista, 7, 8, or 10 operating systems. When the National Estimator program has been installed, click Help on the menu bar to see a list of topics that will get you up and running. Or, go online to www.costbook.com and click the ShowMe tutorial link to view an interactive tutorial for National Estimator.

Labor Costs

The labor costs listed in this manual will apply to most jobs where the hourly wage in effect is the same or similar to the following rates:

Journeyman Electrician

| | |
|---|-----------------|
| Base Wage..... | \$30.20 per hr. |
| Taxable Fringe Benefits at 5.46%..... | \$1.65 per hr. |
| Taxes & Insurance at 19.84%..... | \$6.32 per hr. |
| Non-taxable Fringe Benefits at 4.82%... | \$1.46 per hr. |
| Total Labor Cost..... | \$39.63 per hr. |

The total hourly cost includes the basic wage, taxable fringe benefits (vacation pay), workers' compensation insurance, liability insurance, taxes (state and federal unemployment, Social Security and

Medicare), and typical nontaxable fringe benefits such as medical insurance.

If your hourly labor cost is much lower or higher, costs of installation can be expected to be proportionately lower or higher than the installation costs listed in this book. If your total hourly labor cost is 25 percent less, for example, reduce the labor figures in the cost tables by 25 percent to find your local cost.

The Craft@Hrs column shows the recommended crew and manhours per unit for installation. For example, L2 in the Craft@Hrs column means that we recommend a crew of two electricians. L1 means that a crew of one electrician is recommended. Costs in the Labor Cost column are the result of multiplying the manhours per unit by the rate of \$39.63 per hour.

For example, if the Craft@Hrs column shows L2@.250, the Labor Cost column will show \$9.91. That's .250 manhours multiplied by \$39.63 per man-hour and rounded to the nearest penny.

Divide the manhours per unit into 8 to find the number of units one electrician can install in one 8-hour day: 8 divided by .250 equals 32 units per day. Multiply that amount by the number of crew members to find the number of units the crew is likely to install in an 8-hour day. For example, if the crew is two electricians, multiply 32 by 2 to find that the crew can be expected to install 64 units in an 8-hour day.

Some tasks require less labor under certain conditions. For example, when conduit is run in groups, less labor is required for each 100 linear feet. It's the estimator's responsibility to identify conditions likely to require more or less labor than the standard for the type of work being estimated.

This book lists both the labor cost per installed unit and the manhours required for installation. Manhours are listed in hundredths of an hour rather than minutes, making it easier to calculate units.

Material Costs

Material prices in this book are based on actual costs in late 2015, with projections to mid-2016 based on the author's judgment. Prices are neither "retail" nor "wholesale" costs. Instead, they're intended to reflect typical costs to electrical contractors who buy at electrical supply houses in mid-2016. Volume purchases may cost less because many dealers offer quantity discounts to good customers. Expect prices to vary with location, terms demanded, services offered, and competitive conditions.

Prices in this manual are not representative of shelf prices for electrical materials at big box building

material retailers – and for good reason. Most electrical contractors don't buy from big box retailers. They buy from specialized electrical material dealers who offer the selection, service and terms that electrical contractors expect. Big box retailers stock limited quantities, no more than a few hundred electrical SKUs, specialize in commodity-grade merchandise and are generally not set up to meet the needs of professional electrical contractors.

Material costs in this book include normal waste. If waste of materials or breakage is expected to exceed 3 to 5 percent of the materials used on the job, include a separate allowance for excessive waste.

Material delivery cost to the job site isn't included in this book. When delivery cost is significant and can be identified, add that cost to these figures.

Please note that the cost of some electrical materials is highly volatile. For example, copper wire prices have been known to fluctuate 10 percent or more in one month. There's no reliable way to forecast price movements like this. If you're bidding on a project that has a quantity of copper products, you may want to add a qualification to your bid proposal which would allow you to pass on a pricing increase (or decrease), based upon the actual materials pricing at the time of purchase. This way, you can use the current price quoted at the time of your bid, but still leave the door open to any major pricing fluctuations.

Add Sales Tax

No state or local sales tax is included in material prices listed here. Sales tax varies from area to area and may not be applicable on purchases for some types of projects. Add at the appropriate rate when sales tax is charged on materials bought for the job.

Add Overhead and Profit

To complete the estimate, add your overhead and expected profit. Many contractors add an additional 10 to 15 percent for profit to yield an acceptable return on the money invested in the business. But no profit percentage fits all jobs and all contractors. Profit should be based on the current market in each user's local area.

For some electrical contractors, overhead may add as little as 10 percent to the labor and material cost. But routinely adding 10 percent for overhead is poor estimating practice. Overhead should be based on each user's built-in costs. It's the estimator's responsibility to identify all overhead costs and include them in the estimate, either as a lump sum or as a percentage of the total labor and material cost.

Other Costs to Add

A few other costs are excluded from the figures in this manual: electrical building permits, special hoist-

ing costs, freight costs not absorbed by the supplier, utility company charges for installation and service, special insurance and bonds, power equipment other than small tools, mobilization to remote sites, demobilization, nonproductive labor, and nonworking supervisors. If these costs are significant and can be determined, add them to your estimate. If not, you should exclude them and specify clearly that they're not a part of your bid.

All Tables Assume "Good" Conditions

This means that there are few or no unusual conditions to delay production. Conditions are good when work is performed during usual working hours in relatively clean surroundings and in readily accessible areas not over 12 feet above the finish floor. The temperature is between 50 and 85 degrees F. Electricians are working no more than 8 hours a day, 5 days a week.

Good conditions require that all tools and materials be available on the job site when needed. Tools, including power tools, are assumed to be in good working order. Where power tools are appropriate, it's assumed that temporary power is provided. Add the cost of temporary power when it's furnished at your expense.

Proper supervision makes a big difference in labor productivity. The tables assume there is adequate supervision but make no allowance for nonproductive labor — supervisors who direct but do no installation. If you plan to have nonproductive supervision on the job, add that cost to the figures in this manual.

Conditions are seldom "good" when the work area is confined, or when a short construction schedule makes it necessary for many trades to work at the same time. The usual result will be stacks of material obstructing the work space and several tradesmen competing for access at the point of installation.

If the conditions on the job you're estimating aren't expected to be "good," adjust the labor figures in this book as appropriate. Occasionally, larger jobs can be done faster because specialized equipment or crews can be used to good advantage. This will usually reduce the installation cost. More often, conditions are less than "good." In that case, labor costs will be higher.

There's no accepted way to decide how much "bad" conditions will increase the labor hours needed. But it's accepted estimating practice to assign a cost multiplier of more than 1.0 to a job that can be expected to require more than the usual amount of labor per unit installed. For example, if conditions are less than "good" only in minor respects, you might multiply labor costs by 1.10. If conditions are very poor, a multiplier of 1.50 or more may be appropriate.

Other Factors That Affect Productivity

This book's tables assume that the crew used for the job is the smallest crew appropriate for the work at hand. Usually this means that the crew is one journeyman electrician.

Most experts on the productivity of construction trades agree that the smallest crew that can do the job is usually the most efficient. For example, it's foolish to have two men working together setting duplex receptacles — one handing tools and material to the other as needed. Only one of them would be working at any given time. It's more productive to use two one-man crews, each working independently.

Of course, there are exceptions. Sometimes a crew of one takes twice as long as a crew of two. When pulling feeder cable or setting floor-standing switchboards or motor control centers, more help usually cuts the labor cost per installed unit. Some jobs simply can't be done by a crew of one.

When work is done on a scaffold, someone should be on the ground to chase parts and equipment and prepare lighting fixtures for hanging. It wastes manpower to have an electrician leave the scaffold and return when parts or tools are needed. Scaffold

installers should install one fixture while the "grunt" below prepares the next. Conduit should be prefabricated on the ground from measurements taken by the electricians on the scaffold. The assistant should bend the conduit and hand it up to the installer.

These labor savings are obvious to anyone who's done this type of work, and are assumed in this book's labor tables.

The Electrician

This book's labor hours are typical of what a trained and motivated journeyman electrician with 5 years of experience will do on most jobs. It's assumed that the installer can read and follow plans and specifications and has the ability to lay out the work to code.

It shouldn't make any difference whether the work is in a hospital, a grocery store, a wood mill or a small convenience store. An experienced journeyman electrician should be able to handle the work at the rates shown here even though the materials and code requirements differ. But you'll have to make allowances if your installers are only familiar with residential work, and the job at hand is something else.

Improving Estimating Accuracy & Profits

It's been said that electrical estimators learn by making mistakes. The best estimators are the ones who've made the most mistakes. Once you've made every mistake possible, you're a real expert.

I can't subscribe 100 percent to that theory, but I know that there are plenty of pitfalls for unsuspecting electrical estimators. This section is intended to suggest ways to spot potential problems before they become major losses. It'll also recommend steps you can take to increase the profit on most jobs.

Labor Productivity

Improving output even slightly can result in major cost savings. Cutting only a minute or two off the installation time for each duplex receptacle or handy box can reduce the labor cost by several hundred to a thousand dollars a job. Getting better productivity from your electricians should be a primary concern for every electrical contractor.

Assuming your electricians are experienced, well-trained, and have all the tools and materials they need to complete the work, the most significant increase in productivity will probably be through motivation.

The best form of motivation for most electricians is to encourage pride in the work they do. Every alert supervisor knows the value of recognizing a job well done. Acknowledging good work builds confidence and encourages extra effort in the future.

Labor Availability

Labor in each locale may not always be readily available. Prior to bidding any project, make an evaluation of the available work force. You may need to make staffing or salary adjustments for the duration of that project. Your work force evaluation will help you prepare for adding another workman, or adjusting a current employee's salary and benefits to compete with rates in your area.

Handling Inspections

The on-site supervisor or foreman should be responsible for dealing with all inspectors. Don't let others circumvent the supervisor's or foreman's authority.

An inspector's only job is to see that the installation complies with the code. They aren't supervisors and don't direct the work. They can and do interpret the code and sometimes make mistakes. Encourage the foreman or supervisor to take issue promptly with a questionable interpretation. Ask the inspector to cite a specific code as his reference. If the inspector insists that his interpretation is correct, and if you believe it's wrong, call the building official to initiate an appeal. Your trade association or the National Electrical Contractors' Association may also be able to persuasively argue in your favor.

Some inspectors have a reputation for being impossible to deal with. Aggressive enforcement of questionable code interpretations can severely hurt project productivity. Following the code carefully will keep you out of most compliance arguments. Every electrician and electrical supervisor must know the code. Code classes are taught at continuation schools in many communities. You can take code classes to both understand how the code is applied and to remain current on code changes.

Mobilization and Demobilization

Many electrical subcontractors have job shacks and lockup boxes that can be moved onto the job for storing tools and materials. Some larger firms have trailers that can be moved from job to job. No matter what type of on-site storage you use, setting up takes time. The bigger the job, the more time will probably be needed.

Usually the first step is getting permission to set up your storage area on the site. Sometimes storage space is at a premium. Some city projects literally have no storage space until parts of the building are completed and can then be used. Occasionally tools and equipment will have to be stored off site. This can require daily mobilization and demobilization, which increases your labor cost substantially. Be sure your estimate includes these costs.

Demobilization usually takes less time and costs less than mobilization. Removing the surplus material, tools and equipment can be done by helpers or material handlers rather than electricians.

One important item in mobilization is temporary electrical service. Be sure you know who pays for installation of temporary power and who pays for power used on site during construction. It's common for the electrical contractor to cover the cost of electrical distribution and service. Installation is usually done by your electricians and will have to pass inspection.

Most communities require temporary electrical permits prior to starting work. Before applying for the permit, contact the electric utility provider and request a meeting with whoever coordinates extensions of service — usually the planner. Before your meeting, determine what size service you need. The planner will tell you what voltage is available and where the point of connection will be. Don't end this meeting with the planner until you've covered every requirement and procedure imposed by the electric utility.

Job Cleanup

Trash and debris that obstructs access to (and on) the job site can make good production next to impossible. That alone should be encouragement to regularly dispose of accumulated waste. Most specifications require that subcontractors remove unused materials, cartons, wrappers and discarded equip-

ment. On many jobs, the general contractor has the right to backcharge subs for removal of their discards if they don't clean the site themselves.

Encourage your crews to do their cleanup while installation is in progress. For example, each time a fixture is removed from a carton, the tradesman should collapse the carton and throw it on the discard pile. It takes slightly more time to dispose of trash this way, but cleanup is less likely to be forgotten.

Some contractors and subcontractors have a reputation for running a dirty job. You've probably seen sites that are so cluttered that you can't understand how anyone could work efficiently. Of course, as the electrical contractor, you can't dictate to the general contractor or the other subcontractors. But the work habits of others affect your productivity, and consequently, your profit.

I believe that if accumulated debris is slowing progress on the job, it's within your rights to discuss it with the general and the other subs. Request a meeting, right in the middle of the clutter. That alone may do the trick.

If you don't insist on a clean site, the fire department probably will. A clean job is more efficient and safer. A cluttered job costs everyone time and money.

Production

No matter how simple and quick you anticipate them to be, most jobs will have some production problems. Every job is unique. Every job brings together skilled tradesmen with varying preferences and habits. Some have never worked together before. Yet each must coordinate the work he does with those who precede him and those who follow. It's normal to expect that some adjustments will be needed before cooperation becomes routine.

Of course, the general contractor is the key to cooperation among the trades. A general who schedules trades properly will have fewer problems and will help all subcontractors earn the profit they're hoping for. This isn't automatic. And some general contractors never learn how to schedule properly. From an estimating perspective, it's more expensive to work for a contractor who has scheduling problems than it is to work for a contractor who's efficient at job coordination. If you anticipate production problems like this on a job, your estimate should reflect it.

Good supervision helps avoid most production problems. Try to schedule material deliveries in a timely manner. Have the right tools on hand when needed. Keep crews as small as possible. Don't work your crews more than 40 hours a week unless absolutely necessary. Too many bodies and too many hours will erode production.

If you're using a larger crew, don't have everyone work at the same time. Instead, break the crew into two units and encourage friendly competition between the two. Offer a reward for the winning crew.

Corrections

This book's tables assume that little or no time is spent making corrections after the work is done. Electrical contractors should have very few callbacks.

If you're called back often to replace faulty materials or correct defective workmanship, one of four things is happening. First, you could be working for some very particular contractors or owners, or handling some very sensitive work. In that case, callbacks could be part of the job and should be included in each estimate. Second, you could be installing substandard materials. Third, your electricians could be doing haphazard work. Finally, your installation procedure could be omitting fixture and circuit tests that could locate problems before the owner finds them.

When qualified electricians install quality materials, the risk of a callback is small. Occasionally a ballast will fail after 10 or 20 hours in use. And sometimes an owner's negligence will damage a circuit or switch. When this happens, accept the service work as routine. Complete it promptly at no extra charge. Consider it cheap advertising — a chance to establish your reputation with the owner. You could turn the service call into some extra work later.

Your Type of Work

Most electrical contractors prefer to handle specific types of work. Only a few have the capital, equipment and skills needed to handle the largest jobs. Most will do residential wiring because that's the most plentiful work available. Some prefer private work with as little government interference as possible. Others bid only government jobs.

The most profitable electrical contractors specialize in one type of work or customer. The electrical construction field is too broad to do everything well. Select an area that you feel comfortable with, and concentrate on doing it as well or better than anyone else. Of course, some of the older and larger electrical shops will do almost any type of work. But nearly every electrical contractor prefers some class of job over all others — and would take only that work if there was enough available to stay busy.

Observe the electrical contractors in your area. Notice the companies that seem to be busiest and most profitable. See what class of customers they service or what type of work they do most. It's probably easier to follow the success of another contractor who's found a winning formula than it is to invent a new formula yourself.

Specialization lets you hire electricians who are specialists, too. That tends to improve productivity, keep costs down, and improve profits — as long as you're handling work that's within your specialty.

Coordination is easier and the profits will usually be higher if you work for a limited number of general contractors. Some contractors seem to be masters at putting a project together. These same contractors probably pay promptly and treat their subs fairly. That makes your job easier and tends to fatten your bottom line. If you've found several contractors who make life more pleasant for you, keep them supplied with competitive bids that'll bring more work into both your shop and theirs.

Most electrical contractors don't bid government work. It's a specialty that requires specific knowledge: complying with detailed general conditions, observing regulations, anticipating inspection criteria and following administrative procedures. And every branch of federal, state and local government has its own requirements. Those who've mastered the procedures usually do quite well when work is plentiful. But government work is a tide that rises and falls just like that of general construction.

Bid Shopping

Many contractors prefer projects that require subcontractor listings. The general contractor must list the subcontractors he plans to use, and has to use the subs he lists. When listing of subs isn't required, in some cases the general contractor shops for lower subcontract bids right up to the time work begins. Even if the general has to list his subs in the contract with the owner, he'll still usually have a month or two to shop bids after the contract is awarded.

When a general contractor uses your bid to land a job, it's normal to expect that your company will get the contract. Giving all your competition a second look at the job is in no one's interest but the general contractor's. It's a waste of time to bid for general contractors who shop their sub bids. Nor is it good practice to undercut another electrical contractor whose estimate was used by the winning general contractor. Support the effort of reputable subcontractors who promote subcontractor listing at bid time.

Need More Help?

This book is concerned primarily with labor and material costs for electrical construction. You'll find only limited information here on how to compile an estimate. If you need a detailed explanation on how to make a material take-off and complete the bid, another book by this publisher may be helpful. You can read about and purchase *Estimating Electrical Construction Revised* using the order form bound into the back of this book.

Section 1: Conduit and Fittings

Every electrical estimator should be familiar with the *National Electrical Code*®. Nearly all inspection authorities follow *NEC*® recommendations on what is and what is not good electrical construction practice. Most inspection authorities accept electrical materials that comply with *NEC* standards. But some cities and counties have special requirements that supplement the current *NEC*. Others are still following an older edition of the *NEC*. The *NEC* is revised every three years to incorporate changes deemed necessary to keep the code up-to-date.

Be aware of the version of the *NEC* that applies at each job you're estimating, and stay current on special requirements that the inspection authority may impose.

Job specifications usually state that all work must comply with the *NEC*. But on many jobs the *NEC* sets only the minimum standard. Job specifications may prohibit what the *NEC* permits. For example, job specs might require specific installation methods or mandate specification grade fixtures.

The *National Electrical Code* classifies all enclosed channels intended to carry electrical conductors as "raceway." This includes conduit, busway and wireway. The most common raceway is electrical conduit. The code identifies the size and number of conductors that can be run through each size of conduit.

Conduit is intended to serve two purposes. First, it's a protective shield for the conductor it carries. It reduces the chance of accidental damage to the wire or insulation. Second, it protects people and property from accidental contact with the conductors. A ground or short is both a safety and a fire hazard.

Conduit is generally required in commercial and industrial buildings, hospitals, hotels, office buildings, stores and underground facilities. It's not generally used in wiring homes and apartments.

Several types of electrical conduit have been approved for electrical construction. Each is designed for a specific purpose or use. All conduit used in electrical construction as a raceway for conductors must bear a label issued by the Underwriter's Laboratories. The UL label indicates that the product has been approved for use under the *National Electrical Code*.

The *NEC* permits a maximum of four bends totaling 360 degrees between terminations in a run

of conduit. Exposed conduit should be installed horizontal or vertical and should run parallel to building members. Concealed conduit should be run in the shortest direct line to reduce the length of run. Long runs waste materials, require excessive labor and, if long enough, can reduce the voltage available at the load end.

Electrical Metallic Tubing

EMT is also known as **thin wall** or **steel tube**. EMT conduit is nonferrous steel tubing sold in 10-foot lengths. Unlike water pipe, the ends aren't threaded. The conduit has a corrosion-resistant coating inside and outside. This coating may be hot-dipped galvanizing, electroplating, or some other material. The conduit sizes are ½", ¾", 1", 1¼", 1½", 2", 2½", 3", 3½" and 4".

Many types of EMT fittings are available. There are elbows, compression, set screw, indent and drive-on fittings which may be made of steel or die cast. Couplings and connectors are sold separately and not included in the price of the conduit. Various types of connectors may be purchased with or without insulated throats. The locknuts for the connectors are included in the cost of the connector.

Couplings are available for joining EMT to rigid metal conduit and to flexible conduit. These couplings are available in compression, set screw and drive-on type and are made of steel or die cast.

EMT conduit is sold without couplings. You have to figure the number of couplings needed and price them separately. To figure the number needed, allow one coupling for each 10 feet of conduit. Then add one coupling for each factory-made elbow.

EMT should be bent with a special conduit bender. The bender has a shoe that fits over and around about half of the conduit to keep the conduit from collapsing as it bends. With a bender it's easy to produce smooth, consistent bends up to 90 degrees. Hand benders are used on sizes from ½" to 1¼". EMT bending machines are available for all sizes of conduit. There are manual, hydraulic and electrically driven machines.

Offsets are made to take EMT conduit around obstructions, and when needed, to align the conduit at a box or cabinet. You can make offsets with a hand bender on sizes up to 1¼". Offsets in EMT conduit over 1¼" should be made with a machine.

In smaller sizes, conduit can be cut with a tubing cutter. Cut larger diameters with a hacksaw or by machine. Cut ends must be reamed to remove the burrs made while cutting. Burrs can damage insulation when wire is pulled through the conduit. Ream with a pocket knife or pliers on smaller sizes and with a metal file or pipe reamer on larger sizes.

EMT must be supported so it doesn't deflect on longer runs. Straps and nailers are the most common way of supporting EMT. Straps usually have one or two holes for securing to the building. Most inspection authorities won't let you support EMT on plumber's perforated metal tape. Straps come in thin steel, heavy duty steel or malleable types. There are special straps made of spring steel for supporting small sizes of EMT to hanger rods or drop ceiling wires.

EMT conduit should be supported at least every 10 feet with a strap or hanger and within 18 inches of every junction box or cabinet.

Other supports include beam clamps for attaching conduit to structural steel members and straps for mounting EMT on steel channel strut. These two-piece straps or clamps are inserted into the strut and bolted together to hold the conduit in place.

EMT can be installed inside or outside, in concrete or masonry, exposed or concealed in walls, floors or ceilings. But be sure to use the correct fittings in wet locations. EMT is not approved for most types of hazardous locations. Some specs limit the use of EMT to dry areas and don't allow placement in masonry or concrete. Conduit placed in concrete floor slab is generally placed below the reinforcing bar curtain or between curtains when two curtains are used. Tie the conduit to the rebar to prevent shifting as the concrete is placed.

Where conduit is turned up above the surface of the concrete, the radius of the turn must be concealed. Part of it can be concealed in a wall, but none should be visible after the building finish has been installed.

As with all types of conduit, EMT should be installed with a minimum of damage to the structure. Keep it clear of heating, ventilating and air conditioning ducts, fire sprinkler systems, plumbing lines, access doors, etc. When necessary, the installer will have to make offsets and bends so the conduit fits into devices, electrical boxes and cabinets.

Flexible Metal Conduit

There are several types of flex conduit: standard wall steel flex, reduced wall steel flex, and aluminum flex. It comes in diameters from 3/8" to 4" and is coiled in rolls of 100 feet in the small sizes and 25 feet in the larger sizes. Flex is usually used

in concealed locations but never underground or in concrete. It's cut with a special flex cutter, a hand hacksaw, or with a power cutter such as a portable band saw. The inside cut edge must be reamed to remove cutting burrs which would damage insulation when wire is pulled through conduit.

Flex connectors are available with set screw, screw-in, clamp type, straight, or angled connectors. They're made of steel or die cast. Insulated connectors are also available. Die cast flex couplings are available for joining flex to flex, flex to EMT, or flex to threaded conduit. Support flex with conduit straps or nailers.

Most inspection authorities require that a bonding conductor be installed when electrical wiring is run in flex. Bonding ensures that there's electrical continuity in the flex from one end to the other.

Some specifications restrict the use of flex to short connections to equipment that is subject to vibration (such as motors and machinery) and for built-ins, recessed lighting, and lay-in lighting fixtures.

Flex conduit is popular in remodeling work where wiring in raceway has to be run through an existing cavity wall or in a ceiling cavity. With a little effort, your installer can fish the flex from point to point without opening the wall or ceiling.

Polyvinyl Chloride Conduit

PVC conduit is approved by the *NEC* for many types of applications. But there are some situations where it cannot replace metallic conduit. It's not approved for hazardous locations or in return air plenums. Check with the inspection authority for other restrictions. The standard length is 10 feet and sizes range from 1/2" to 6". Schedule 40 PVC is the standard weight. Schedule 80 has a heavier wall. PVC can be installed directly underground, concrete encased underground, exposed, in concrete walls, and in unit masonry.

One coupling is furnished with each length of conduit and is usually attached to the conduit. PVC must be bent with a special hot box which heats the conduit until it becomes pliable. Once heated to the right temperature, the tube is bent and then allowed to cool. PVC fittings fit both Schedule 40 and 80 conduit. Couplings, terminal adapters, female adapters, expansion fittings, end bells, caps, conduit bodies, pull boxes, outlet boxes and elbows require a special cement. The glue is air-drying and comes in half-pints, pints, quarts, and gallon containers. The smaller containers have a brush attached to the cap for applying the cement to the conduit or fittings. PVC conduit can join other types of conduit if you use the right fittings to tie the two types together.

PVC is nonconductive. That makes a bonding conductor necessary to ensure electrical continuity

from the device to the service panel. You probably won't need a bonding conductor when PVC is used as communications conduit or in some application that doesn't include electrical wiring. When installed exposed, PVC requires extra support to keep it from sagging.

Some job specs restrict use of PVC to specific locations. One common restriction is to limit PVC to underground installations encased in a concrete envelope. Many specifications restrict its use to certain applications.

PVC conduit can be cut with a hand hacksaw, a wood crosscut saw, or with a power cutting machine. The inside cut edge should be reamed to remove the cutting burr. Use a pocket knife or a file.

Power and communications duct is usually called **P&C duct**. It's made of PVC in 25-foot lengths and in diameters from 1" to 6". There are two types of P&C duct. One is called **EB** for encased burial. The other is **DB** for direct burial. Fittings for P&C duct include couplings (one is furnished with each length), end bells, caps and plugs, terminal adapters, female adapters, elbows, and expansion fittings. The elbows are available in various shapes and with either long or short radii. Fittings can be used either on type EB or DB. Use a special cement to weld the fittings to the conduit.

Bend P&C duct with a hot box. It can be cut with the same tools as PVC conduit. The inside cut edge must be reamed to remove the cutting burr.

P&C duct is used for underground systems only, never above ground.

ABS underground duct is used and installed the same as PVC P&C duct. It requires a special ABS cement to weld the fittings to the conduit. The job specifications or the utility company may require either P&C, ABS or PVC duct, depending on the specific use.

Galvanized Rigid Conduit

GRS or RSC (for rigid steel conduit) is made with nonferrous metal and has a corrosion-resistant coating on the inside. The outer coating is either hot-dipped galvanizing or electroplate. It comes in diameters from ½" to 6" and in 10-foot lengths with a thread on each end. A coupling is furnished on one end of each length. GRS can be cut with a hand hacksaw, a pipe cutter, or with a cutting machine. The inner cut edge must be reamed to remove the burr. Use a pipe reamer or a file.

After the pipe has been cut and reamed, it can be threaded. Use a hand die for threading on a small job. Where there's more cutting and threading to be done, use a threading machine. Several types are available. Small portable electric threading tools cut sizes up to 2". Larger threading machines can cut, ream and thread conduit diame-

ters up to 6". Another good choice for GRS up to 6" is a threading set that uses a tripod vise stand and a threading head that clamps to the pipe in the vise stand. The threading head is turned with a universal joint connected to a power vise. Another set uses a tripod vise stand to hold the conduit. The threading head clamped on the conduit is turned with a reduction gear assembly powered by an electric drill. This rig works well on diameters over 2".

Use enough cutting oil to keep the die cool and lubricated during thread cutting. Cutting oil comes in clear or dark and in small cans, gallons and barrels. Use an oil can to keep a film of oil ahead of the dies. Commercial oiling units hold about a gallon of cutting oil and recirculate oil back to the cutting teeth as oil drips into the catch basin. Most threading machines have automatic oilers that filter the oil as it's reused.

Elbows are available for all sizes of GRS. Long radius bends are available for the larger sizes. Some specifications require concentric bends for all exposed conduit installed parallel on a common hanging assembly or trapeze.

GRS fittings include couplings, locknuts, bushings, one-hole straps, two-hole straps, heavy duty two-hole straps, expansion fittings, threadless compression couplings, threadless set-screw couplings, threadless compression connectors, threadless set-screw connectors, three-piece union-type couplings, strut clamps, beam clamps, hanger clamps, condulets, split couplings, caps, and plugs.

Galvanized rigid conduit is bent about the same way as EMT except that the bender is made for bending rigid conduit. Hand benders are used on conduit up to 1". There are hand benders for 1¼" and 1½" rigid steel conduit, but it takes a lot of effort to make the bend. Power benders can be used on all sizes of conduit, even the ½".

There are three common types of rigid steel benders: one-shot benders create a single standard radius arc. Segment benders must be moved along the conduit as each few degrees of bend are made. The electric sidewinder bender has up to three bending shoes in place ready to bend any of three sizes of conduit. The sidewinder saves labor on larger rigid conduit jobs.

Supports for rigid conduit must be no more than 10 feet apart from support to support and within 18 inches of junction boxes or cabinets.

Trapeze hangers are often used to carry multiple runs of GRS conduit. Trapeze hangers can be made from strut, angle iron, or channel iron. The trapeze is supported from the structural frame of the building with threaded rod — usually either ¾" or ½" diameter. The upper part of the rod is attached to beam clamps or concrete anchors. The lower portion of the rod is run through the trapeze and is secured with double nuts and flat washers.

Like other hangers, trapezes have to be placed within 10 feet of each other and should be sized to support the total weight of the conduit and all cable. Trapeze hangers can be stacked one over the other with conduit clamped on each one.

IMC Conduit

Intermediate metal conduit (IMC) has a thinner wall than GRS. It comes in the same sizes and uses the same fittings as GRS. The same tools can be used for cutting, threading, and bending. It's made about the same way as GRS, comes in 10-foot lengths and is galvanized for corrosion resistance. The difference is that IMC is lighter and easier to install than GRS. Some specifications restrict its use to specific applications.

PVC Coated Conduit

Both GRS and IMC conduit come with a PVC coating for use in highly corrosive locations. Aluminum tubing also comes with a PVC coating, but applications are restricted to specific uses. The PVC coating is either 10, 20 or 40 mils thick, and is bonded directly to the conduit wall. Most fittings made for use with GRS are available with a PVC coating.

To thread PVC coated conduit, the PVC coating must be cut back away from the end to be threaded. When PVC coated conduit is put in a vise, be sure the coating is protected from the vise jaws. Also be careful when you're bending PVC coated conduit not to damage the coating. If the coating is damaged, patching material is available to restore the surface. The material comes in a spray can. Apply several thin layers to repair worn spots.

Conduit Take-Off

Here's how to calculate conduit quantities. First, scan the specs that cover conduit and conduit installation. Absorb all the information that relates to conduit. Then review the drawings for anything about conduit. The symbol list may include the engineer's design notations. Notes on the drawings or in the specs may set specific minimum conduit sizes. It's common for an engineer to require a minimum size conduit in the home run to the panel or cabinets or to specify a minimum size of $\frac{3}{4}$ " throughout the job. It's also common practice to limit the maximum size of EMT to 2". Ignoring a note like that can be expensive.

For your quantity take-off, use any ruled $8\frac{1}{2}$ " by 11" tablet. Draw a pencil line down the left side of the sheet about an inch from the edge. Begin by looking for the smallest diameter of EMT. Write "EMT" at the top left of your take-off sheet. On the next line down, to the left of the vertical line, list the smallest EMT size found in the project — probably $\frac{1}{2}$ ". To the right of the vertical line and on the

same horizontal line as the size, you're going to list lengths of EMT of that diameter. Then you'll go to the next larger diameter, listing quantities until all EMT on the plans has been covered.

Check the plan scale before you start measuring conduit. If the plan has been reduced photographically to save paper, the scale will be inaccurate. Once you're sure of the correct scale, select the appropriate map measure or rule to compute conduit lengths.

Measure the length of each run of $\frac{1}{2}$ " EMT. Add enough conduit to include the run down to the wall switch, receptacle or panel. Write down the calculated length. As each run is listed on your take-off sheet, put a check mark on the plan over the line you just measured. Use an erasable color pencil and let each color stand for a particular conduit type. For example, red might be for GRS conduit. Follow the same color code on all estimates to avoid mistakes.

If there are more than two or three plan sheets, it's good practice to calculate the length of $\frac{1}{2}$ " EMT on each plan sheet and list that number separately on your take-off form. When you've finished taking off $\frac{1}{2}$ " EMT on the first plan sheet, list that quantity, and at the top of the column write in the plan sheet number. Then draw a vertical line to the right of that column and start accumulating lengths from the next plan sheet. As each plan page is taken off, enter the total and write the plan sheet number at the top of the column. Figure 1-1 shows what your take-off might look like if conduit and fittings are found on plan sheets E3 to E11.

When all of the smallest-diameter EMT has been listed, go on to the next larger size. Follow the same procedure.

After listing all EMT, begin with the fittings. Below the last horizontal line used for conduit, and to the left of the vertical line, write the word "Connectors." Below that, list all sizes of connectors needed for the job, again working from the smallest size to the largest. Don't bother to list the couplings. They'll be figured later from the total conduit length — one for each 10 feet and one for each elbow.

Count each connector needed for each conduit run on each plan sheet. Enter the total on your take-off form. When all connectors are counted, count EMT elbows from $1\frac{1}{4}$ " to the largest size needed.

Follow this system for all estimates and for each item on every estimate. Keep it simple and uniform to avoid mistakes and omissions. When finished, your conduit and fitting take-off form might look like Figure 1-1. The right column is the sum of the columns to the left.

| Work Sheet | | | | | | Estimate No.: <u>M351</u> | | | | |
|--------------------|-----|-----|-----|-----|-----|---------------------------|-----|-----|-----|-------|
| Conduit / Fittings | | | | | | | | | | |
| | E3 | E4 | E5 | E6 | E7 | E8 | E9 | E10 | E11 | Total |
| ½" EMT | 550 | 420 | 200 | 90 | 290 | 130 | 190 | 320 | | 2190 |
| ¾" | 20 | | 30 | 20 | 80 | | | | | 150 |
| 1" | | | 3 | | 5 | | 50 | | | 58 |
| 1¼" | | | 30 | | | | | | | 30 |
| 1½" | | | | | | | | | 90 | 90 |
| 2" | | | | | 4 | | | | 16 | 20 |
| ½" Conn | 76 | 52 | 124 | 47 | 48 | 16 | 14 | 18 | | 395 |
| ¾" | 4 | | 26 | 4 | 19 | 2 | | | | 55 |
| 1" | | | 4 | | 5 | 2 | 2 | | | 13 |
| 1¼" | | | 2 | | | | | | | 2 |
| 1½" | | | | | | | | | 4 | 4 |
| 2" | | | | | 2 | | | | 4 | 6 |
| 1¼" Elb | | | 2 | | | | | | | 2 |
| 1½" | | | | | | | | | 3 | 3 |
| 2" | | | | | | | | | 3 | 3 |
| ½" PVC | | | 310 | 380 | 50 | | | | | 740 |
| ¾" | | | 120 | 100 | 220 | 50 | | | | 490 |
| 1" | | | 40 | | 320 | 40 | | | | 400 |
| 1¼" | | | | | | 180 | | | | 180 |
| 1½" | | | | 60 | | | | | 75 | 135 |
| 2" | | | | 10 | 25 | | | 70 | 75 | 180 |
| 4" | | | | | | | | 150 | | 150 |
| ½" FA | | | 45 | 30 | 4 | | | | | 79 |
| ¾" | | | 4 | 4 | 12 | 2 | | | | 22 |
| 1" | | | 2 | | 17 | 2 | | | | 21 |
| 1¼" | | | | | | | | | | 0 |
| 1½" | | | | 4 | | | | | 2 | 6 |
| 2" | | | | 2 | 2 | | | | 2 | 6 |
| ½" TA | | | 5 | | | | | | | 5 |
| ¾" | | | | | 4 | | | | | 4 |
| 1" | | | | | 1 | | | | | 1 |
| ½" Elb | | | 50 | 30 | 4 | | | | | 84 |
| ¾" | | | 2 | 2 | 16 | 2 | | | | 22 |

Figure 1-1

Many jobs limit the use of EMT to dry locations. So your EMT take-off will probably start with the lighting plans or the lighting portion of the plan.

Taking Off the Wire

Next, compute the quantity of wire needed. Head up another take-off form with the word "Wire" at the top. Put a vertical line down the left side of the page about an inch from the left edge. In this margin, list wire sizes from the smallest to the largest. To the right of the vertical line you'll list lengths for each wire gauge, on each plan sheet.

Start by measuring the length of ½" EMT with two #12 wires. Multiply by 2 to find the wire length. Then measure the length of ½" EMT with three #12 wires and multiply by 3. Keep following this proce-

cedure until the wire needed in all EMT has been computed. But watch for changes in the wire size on long runs. Sometimes the engineer will decide that a larger wire size is needed in the first portion of a run to reduce the voltage drop at the end of the line. This is common where the last device or fixture on a circuit is a long way from the panel.

Follow the same procedure for all conduit and wire. Record all of the measurements on the work sheets. Don't worry about waste of conduit or wire at this point. We'll include an allowance for waste after the totals are added and before figures are transferred to the pricing sheets.

Sometimes the specifications or a note on the plans will allow the use of aluminum feeder wire over a certain size, providing the ampacity of the

wire is maintained and the conduit size is increased to accommodate the larger wire size. Be sure to observe these restrictions.

Taking Off Other Conduit

Some specifications permit the use of aluminum conduit in certain locations. The aluminum conduit is made in the same sizes as GRS. The fittings are identical except that they're made of aluminum instead of steel. Most specs prohibit the use of dissimilar metals in a conduit run and don't allow placing of aluminum conduit in concrete. Aluminum conduit saves time because it's lighter and easier to handle. But large wire sizes may be a little more difficult to pull in aluminum conduit. The insulation of the wire, the length of the conduit run, and the pulling lubricant used have an effect on pulling resistance.

When taking off the underground conduit, start a separate work sheet for trenching, surface cutting, breaking, and patching. List all excavation for underground pull boxes, handholes, manholes, poles, and light pole bases. Be sure the trenches are big enough for the number of duct they have to carry. If the specifications require concrete or sand encasement around underground duct, calculate the amount of concrete or sand as you compute measurements for each trench.

Be systematic. Follow the same procedure consistently on every take-off. If there are other estimators in your office, be sure they are using the same procedures. Being consistent reduces errors, minimizes omissions, and makes the work easier for others to check.

We've covered all common conduit. But some other types are used occasionally for special purposes:

Fiber duct is a paper and creosote duct. Type 1 is intended for concrete encasement and Type 2 is used for direct burial. Sizes range from 2" to 5". Lengths can be 5, 8 or 10 feet. End fittings are tapered. Ends that have been cut must be tapered with a duct lathe.

Transite duct is cement asbestos duct. Type 1 is for concrete encasement and Type 2 is for direct burial. Sizes range from 2" to 6". It's made in 5, 8 and 10-foot lengths. Transite is harder to cut and must have tapered ends for fittings.

Soapstone duct is made from a soapstone-like material in sizes from 2" to 4".

Wrought iron pipe comes in sizes from 2" to 4". It's used only for certain types of underground communications lines and has to be threaded on each end to accept fittings.

Clay conduit comes in sizes from 2" to 4". It's used for underground communication runs only.

These types of conduit are seldom specified today. You'll see them used only when an old duct line has to be extended. It may be hard to find a fitting that will join an existing duct system made with one type of duct to a new run of duct made from some other material. Sometimes an oversize plastic coupling can be used. In some cases an inside plastic coupling can be inserted into the old conduit. Then new conduit can be joined to start the new run.

Before extending an old underground duct system, check the old conduit with a mandrel to be sure the line is clean and clear. Old fiber duct that's been under water for a long time will swell, making the inside diameter too small to pull new cable.

Silicon-bronze conduit comes in sizes from ½" to 4". It's threaded like GRS and uses similar fittings, except that fittings are silicon-bronze also. It's used in extremely corrosive locations. This type of conduit will be available from your dealer on special request only. It's harder to bend, but can be bent with standard rigid bending tools. It threads very well with the standard threading tools and cutting oil.

Liquid-tight flexible metal conduit comes in sizes from ½" to 4". It's used to extend conduit to electrical equipment in damp or wet locations. Special fittings are available for connecting electrical systems and devices with this conduit. Your dealer probably stocks a limited supply of liquid-tight flex and will quote prices on request. The conduit can be cut with a hacksaw. Be sure to remove the cutting burr. Special connectors with grips are available to support the conduit and prevent any pulling strain.

Liquid-tight flexible non-metallic conduit comes in sizes from ½" to 1½". It's used in place of flexible metal conduit in concealed locations. Special fittings are available for making connections. Your dealer may have a limited supply in stock.

Flexible metallic tubing is available only in sizes from 3/8" to 3/4". Special fittings are available for making connections. The tubing can be bent by hand and is cut with a hacksaw. The cutting burr must be removed before connectors are installed.

Other UL-approved raceways for electrical systems are covered in other sections of this book. See the sections on surface metal raceway, under-floor ducts, header ducts, cable tray, and wireway.

Using the Conduit Tables

The labor tables that follow are for conduit runs that average 50 feet. You'll note that there is no modification in the tables for shorter runs or longer runs of conduit. I agree that it takes more time per linear foot to install a 5-foot run of conduit than it does to install a 95-foot run of conduit. But I don't

recommend that you tally shorter runs and longer runs separately and then compute labor separately for each. There's an easier way.

On most jobs the conduit runs average 50 feet. There will usually be about as many runs under 50 feet as there are runs over 50 feet. It's safe then, to use a 50-foot run as our benchmark. As long as the conduit runs on a job average close to 50 feet, there's no need to modify the figures in these tables. If conduit runs average well over 50 feet, consider reducing the cost per linear foot slightly. Increase the cost slightly if conduit runs average less than 50 feet.

The labor costs that follow include the labor needed to bore holes in wood stud walls. Where holes have to be cut through concrete or unit masonry, add these costs separately.

Typical conduit bending is included in the tables that follow. Usually you will have a bend or offset about every 20 feet. Labor needed to make bends and offsets is minor when installing the smaller sizes of conduit.

Concealed conduit is installed where it will be inaccessible once the structure or finish of the building is completed. **Exposed conduit** is attached to the surface where access is possible even after the building is completed. It's usually faster to run concealed conduit through wall and ceiling cavities that will be covered later by finish materials. Installing conduit on surfaces that won't be covered later usually takes more time.

If only a small percentage of the conduit is to be installed exposed, the cost difference will be minor and probably can be ignored. But if most of the job is exposed, add about 20 percent to the labor cost.

The conduit tables that follow assume that electricians are working from ladders and lifts up to 12 feet above the floor. Add to the labor cost for heights beyond 12 feet. If a large quantity of conduit has to be installed at 18 feet above the floor, for example, add 15 percent to the labor cost.

If there are conduit runs over 20 feet above the floor, check your labor contract for a **high time clause**. Some agreements require that electricians be paid time and one-half for heights from 20 to 50 feet and double time for heights beyond 50 feet. If high time must be paid, be sure the extra cost is covered in your bid.

Job Size Modifiers

It's seldom necessary to estimate lower productivity just because the job is small. If you're figuring a very small job with only four or five conduit runs, each with only a strap or two, you might want to use a higher hourly labor rate. On any other job

that takes from two days to several years, you can use the labor units in the tables that follow. Of course, you'll still have to modify the figures for other than "good" conditions. And if you have long runs of feeder conduit with parallel runs on a common trapeze, you can reduce those labor units by as much as 40 percent.

Pitfalls

The most common error when estimating conduit is failing to read the plans and specs. Read carefully! Your profit depends on it. It's easy to miss a little note where the designer sets the minimum size for conduit at $\frac{3}{4}$ " and 1" for all home runs to the panel. Look for a note on the plans that requires stub ups to ceiling cavities from power and lighting panels. The designer may require one $\frac{3}{4}$ " conduit run for each three spare circuit breakers in a panel.

It's common for rigid conduit to be installed in a concrete floor slab. Where GRS is stubbed up out of the concrete for a wall switch, it's easier and cheaper to use EMT for the wall extension. The NEC permits making that extension in EMT. But some specs don't! Others require that a junction box be used to separate the two types of conduit. Failing to catch that note can be an expensive mistake.

You'll find all sorts of restrictions in specs and notes on the plans. That's why it's so important to read the plans and specs carefully. It's elementary, but it's so often overlooked.

Waste of Material

There will always be some waste on a job. Rounding off the conduit and wire needed to the next even 100 feet will usually allow enough extra material to cover all waste. But there are some cases where you can anticipate a waste problem. For example, suppose there will be 2 feet of waste for every 20 feet of conduit installed because of an unusual lighting pattern. Or suppose a row of junction boxes is spaced at 9 feet. Then a 10 percent waste allowance may be called for. That's almost certainly true if your job is installing the lighting only. There may be no chance to use waste materials on another part of the job.

Allowances

Be sure to make allowances for the vertical portion of every conduit run that stubs up or down in a wall. The floor plan doesn't show the 4 or 5 feet needed to run from the slab to the wall switch or panel. Even worse, if the job is a warehouse, the stub up to a switch or panel may be 15 to 20 feet. That's a wide miss! Watch for stub up.

Electrical Metallic Tubing

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

EMT conduit in floor slab or multiple runs on a trapeze

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 1/2" | L1@3.25 | CLF | 59.80 | 129.00 | 188.80 |
| 3/4" | L1@3.50 | CLF | 113.00 | 139.00 | 252.00 |
| 1" | L1@4.00 | CLF | 190.00 | 159.00 | 349.00 |
| 1-1/4" | L1@4.50 | CLF | 288.00 | 178.00 | 466.00 |
| 1-1/2" | L1@5.50 | CLF | 355.00 | 218.00 | 573.00 |
| 2" | L1@7.00 | CLF | 434.00 | 277.00 | 711.00 |
| 2-1/2" | L1@9.00 | CLF | 707.00 | 357.00 | 1,064.00 |
| 3" | L1@10.0 | CLF | 867.00 | 396.00 | 1,263.00 |
| 3-1/2" | L1@11.0 | CLF | 1,260.00 | 436.00 | 1,696.00 |
| 4" | L1@12.0 | CLF | 1,280.00 | 476.00 | 1,756.00 |



EMT conduit in concealed areas, walls and closed ceilings

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 1/2" | L1@3.50 | CLF | 59.80 | 139.00 | 198.80 |
| 3/4" | L1@3.75 | CLF | 113.00 | 149.00 | 262.00 |
| 1" | L1@4.25 | CLF | 190.00 | 168.00 | 358.00 |
| 1-1/4" | L1@5.00 | CLF | 288.00 | 198.00 | 486.00 |
| 1-1/2" | L1@6.00 | CLF | 355.00 | 238.00 | 593.00 |
| 2" | L1@8.00 | CLF | 434.00 | 317.00 | 751.00 |
| 2-1/2" | L1@10.0 | CLF | 707.00 | 396.00 | 1,103.00 |
| 3" | L1@12.0 | CLF | 867.00 | 476.00 | 1,343.00 |
| 3-1/2" | L1@14.0 | CLF | 1,260.00 | 555.00 | 1,815.00 |
| 4" | L1@16.0 | CLF | 1,280.00 | 634.00 | 1,914.00 |



EMT conduit installed in exposed areas

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 1/2" | L1@3.75 | CLF | 59.80 | 149.00 | 208.80 |
| 3/4" | L1@4.00 | CLF | 113.00 | 159.00 | 272.00 |
| 1" | L1@4.50 | CLF | 190.00 | 178.00 | 368.00 |
| 1-1/4" | L1@6.00 | CLF | 288.00 | 238.00 | 526.00 |
| 1-1/2" | L1@8.00 | CLF | 355.00 | 317.00 | 672.00 |
| 2" | L1@10.0 | CLF | 434.00 | 396.00 | 830.00 |
| 2-1/2" | L1@12.0 | CLF | 707.00 | 476.00 | 1,183.00 |
| 3" | L1@14.0 | CLF | 867.00 | 555.00 | 1,422.00 |
| 3-1/2" | L1@16.0 | CLF | 1,260.00 | 634.00 | 1,894.00 |
| 4" | L1@18.0 | CLF | 1,280.00 | 713.00 | 1,993.00 |



Use these figures to estimate the cost of EMT conduit installed in a building under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include typical bending, boring out wood studs and joists (in concealed locations only), layout, material handling, and normal waste. Add for connectors, couplings, straps, boxes, wire, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Conduit runs are assumed to be 50' long. Shorter runs will take more labor and longer runs will take less labor per linear foot.

EMT Hand Benders are on page 27.

EMT Fittings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|-----------------------------|-----------|------|---------------|------------|----------------|
| EMT 45 degree elbows | | | | | |
| 1" | L1@0.06 | Ea | 8.67 | 2.38 | 11.05 |
| 1-1/4" | L1@0.08 | Ea | 10.90 | 3.17 | 14.07 |
| 1-1/2" | L1@0.08 | Ea | 18.40 | 3.17 | 21.57 |
| 2" | L1@0.10 | Ea | 23.40 | 3.96 | 27.36 |
| 2-1/2" | L1@0.15 | Ea | 57.00 | 5.94 | 62.94 |
| 3" | L1@0.20 | Ea | 85.10 | 7.93 | 93.03 |
| 3-1/2" | L1@0.20 | Ea | 113.00 | 7.93 | 120.93 |
| 4" | L1@0.25 | Ea | 134.00 | 9.91 | 143.91 |

EMT 90 degree elbows

| | | | | | |
|--------|---------|----|--------|------|--------|
| 1" | L1@0.08 | Ea | 11.10 | 3.17 | 14.27 |
| 1-1/4" | L1@0.10 | Ea | 13.80 | 3.96 | 17.76 |
| 1-1/2" | L1@0.10 | Ea | 15.90 | 3.96 | 19.86 |
| 2" | L1@0.15 | Ea | 23.40 | 5.94 | 29.34 |
| 2-1/2" | L1@0.15 | Ea | 57.00 | 5.94 | 62.94 |
| 3" | L1@0.20 | Ea | 85.10 | 7.93 | 93.03 |
| 3-1/2" | L1@0.20 | Ea | 113.00 | 7.93 | 120.93 |
| 4" | L1@0.25 | Ea | 134.00 | 9.91 | 143.91 |

Use these figures to estimate the cost of EMT elbows installed on EMT conduit in a building under the conditions described on pages 5 and 6. Costs listed are for each elbow installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs are for factory-made elbows and include layout, material handling, and normal waste. Add for field bending, couplings and connectors at the end of the run, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

Conduit weight per 100 feet (in pounds)


| Diameter | EMT steel | ENT plastic | PVC 40 | Rigid steel | Intermediate rigid steel | Rigid aluminum |
|----------|-----------|-------------|--------|-------------|--------------------------|----------------|
| 1/2" | 30 | 11 | 18 | 79 | 57 | 30 |
| 3/4" | 46 | 14 | 23 | 105 | 78 | 40 |
| 1" | 66 | 20 | 35 | 153 | 112 | 59 |
| 1-1/4" | 96 | — | 48 | 201 | 114 | 80 |
| 1-1/2" | 112 | — | 57 | 249 | 176 | 96 |
| 2" | 142 | — | 76 | 334 | 230 | 129 |
| 2-1/2" | 230 | — | 125 | 527 | 393 | 205 |
| 3" | 270 | — | 164 | 690 | 483 | 268 |
| 3-1/2" | 350 | — | 198 | 831 | 561 | 321 |
| 4" | 400 | — | 234 | 982 | 625 | 382 |
| 5" | — | — | 317 | 1344 | — | 522 |
| 6" | — | — | 412 | 1770 | — | 678 |

EMT Connectors

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Indent EMT connectors

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.05 | Ea | .73 | 1.98 | 2.71 |
| 3/4" | L1@0.06 | Ea | 1.34 | 2.38 | 3.72 |




Die cast set screw EMT connectors

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .45 | 1.98 | 2.43 |
| 3/4" | L1@0.06 | Ea | .73 | 2.38 | 3.11 |
| 1" | L1@0.08 | Ea | 1.41 | 3.17 | 4.58 |
| 1-1/4" | L1@0.10 | Ea | 2.48 | 3.96 | 6.44 |
| 1-1/2" | L1@0.10 | Ea | 3.37 | 3.96 | 7.33 |
| 2" | L1@0.15 | Ea | 4.50 | 5.94 | 10.44 |
| 2-1/2" | L1@0.15 | Ea | 10.20 | 5.94 | 16.14 |
| 3" | L1@0.20 | Ea | 12.40 | 7.93 | 20.33 |
| 3-1/2" | L1@0.20 | Ea | 14.70 | 7.93 | 22.63 |
| 4" | L1@0.25 | Ea | 18.50 | 9.91 | 28.41 |




Insulated die cast set screw EMT connectors

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .74 | 1.98 | 2.72 |
| 3/4" | L1@0.06 | Ea | 1.14 | 2.38 | 3.52 |
| 1" | L1@0.08 | Ea | 2.06 | 3.17 | 5.23 |
| 1-1/4" | L1@0.10 | Ea | 4.11 | 3.96 | 8.07 |
| 1-1/2" | L1@0.10 | Ea | 5.02 | 3.96 | 8.98 |
| 2" | L1@0.15 | Ea | 6.74 | 5.94 | 12.68 |
| 2-1/2" | L1@0.15 | Ea | 18.30 | 5.94 | 24.24 |
| 3" | L1@0.20 | Ea | 21.30 | 7.93 | 29.23 |
| 3-1/2" | L1@0.20 | Ea | 27.10 | 7.93 | 35.03 |
| 4" | L1@0.25 | Ea | 30.00 | 9.91 | 39.91 |



Steel set screw EMT connectors

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | 1.12 | 1.98 | 3.10 |
| 3/4" | L1@0.06 | Ea | 1.83 | 2.38 | 4.21 |
| 1" | L1@0.08 | Ea | 3.20 | 3.17 | 6.37 |
| 1-1/4" | L1@0.10 | Ea | 6.68 | 3.96 | 10.64 |
| 1-1/2" | L1@0.10 | Ea | 9.72 | 3.96 | 13.68 |
| 2" | L1@0.15 | Ea | 13.80 | 5.94 | 19.74 |
| 2-1/2" | L1@0.15 | Ea | 45.40 | 5.94 | 51.34 |
| 3" | L1@0.20 | Ea | 53.30 | 7.93 | 61.23 |
| 3-1/2" | L1@0.20 | Ea | 70.00 | 7.93 | 77.93 |
| 4" | L1@0.25 | Ea | 80.40 | 9.91 | 90.31 |




Use these figures to estimate the cost of EMT connectors installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each connector or expanded elbow installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the connector locknut, removing the knockout, layout, material handling, and normal waste. Add for insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

Indenter tools are on page 22.

EMT Connectors


| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Insulated steel set screw EMT connectors




| | | | | | |
|--------|---------|----|--------|------|--------|
| 1/2" | L1@0.05 | Ea | 1.50 | 1.98 | 3.48 |
| 3/4" | L1@0.06 | Ea | 2.42 | 2.38 | 4.80 |
| 1" | L1@0.08 | Ea | 4.01 | 3.17 | 7.18 |
| 1-1/4" | L1@0.10 | Ea | 8.04 | 3.96 | 12.00 |
| 1-1/2" | L1@0.10 | Ea | 11.80 | 3.96 | 15.76 |
| 2" | L1@0.15 | Ea | 17.10 | 5.94 | 23.04 |
| 2-1/2" | L1@0.15 | Ea | 76.50 | 5.94 | 82.44 |
| 3" | L1@0.20 | Ea | 95.40 | 7.93 | 103.33 |
| 3-1/2" | L1@0.20 | Ea | 128.00 | 7.93 | 135.93 |
| 4" | L1@0.25 | Ea | 140.00 | 9.91 | 149.91 |

Die cast compression EMT connectors, raintight



| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .73 | 1.98 | 2.71 |
| 3/4" | L1@0.06 | Ea | 1.31 | 2.38 | 3.69 |
| 1" | L1@0.08 | Ea | 2.15 | 3.17 | 5.32 |
| 1-1/4" | L1@0.10 | Ea | 3.56 | 3.96 | 7.52 |
| 1-1/2" | L1@0.10 | Ea | 4.65 | 3.96 | 8.61 |
| 2" | L1@0.15 | Ea | 7.39 | 5.94 | 13.33 |
| 2-1/2" | L1@0.15 | Ea | 15.80 | 5.94 | 21.74 |
| 3" | L1@0.20 | Ea | 19.20 | 7.93 | 27.13 |
| 3-1/2" | L1@0.20 | Ea | 25.40 | 7.93 | 33.33 |
| 4" | L1@0.25 | Ea | 29.70 | 9.91 | 39.61 |

Insulated die cast compression EMT connectors, raintight



| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .97 | 1.98 | 2.95 |
| 3/4" | L1@0.06 | Ea | 1.72 | 2.38 | 4.10 |
| 1" | L1@0.08 | Ea | 2.67 | 3.17 | 5.84 |
| 1-1/4" | L1@0.10 | Ea | 4.99 | 3.96 | 8.95 |
| 1-1/2" | L1@0.10 | Ea | 6.17 | 3.96 | 10.13 |
| 2" | L1@0.15 | Ea | 9.09 | 5.94 | 15.03 |
| 2-1/2" | L1@0.15 | Ea | 26.80 | 5.94 | 32.74 |
| 3" | L1@0.20 | Ea | 31.50 | 7.93 | 39.43 |
| 3-1/2" | L1@0.20 | Ea | 39.40 | 7.93 | 47.33 |
| 4" | L1@0.25 | Ea | 45.90 | 9.91 | 55.81 |


Use these figures to estimate the cost of EMT connectors installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the connector locknut, removing the knockout, layout, material handling, and normal waste. Add for insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

EMT Connectors

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Steel compression EMT connectors, raintight

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .14 | 1.98 | 2.12 |
| 3/4" | L1@0.06 | Ea | .21 | 2.38 | 2.59 |
| 1" | L1@0.08 | Ea | .29 | 3.17 | 3.46 |
| 1-1/4" | L1@0.10 | Ea | .65 | 3.96 | 4.61 |
| 1-1/2" | L1@0.10 | Ea | .94 | 3.96 | 4.90 |
| 2" | L1@0.15 | Ea | 1.34 | 5.94 | 7.28 |
| 2-1/2" | L1@0.15 | Ea | 6.48 | 5.94 | 12.42 |
| 3" | L1@0.20 | Ea | 8.99 | 7.93 | 16.92 |
| 3-1/2" | L1@0.20 | Ea | 13.60 | 7.93 | 21.53 |
| 4" | L1@0.25 | Ea | 13.90 | 9.91 | 23.81 |




Insulated steel compression EMT connectors, raintight

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .15 | 1.98 | 2.13 |
| 3/4" | L1@0.06 | Ea | .23 | 2.38 | 2.61 |
| 1" | L1@0.08 | Ea | .40 | 3.17 | 3.57 |
| 1-1/4" | L1@0.10 | Ea | .83 | 3.96 | 4.79 |
| 1-1/2" | L1@0.10 | Ea | 1.21 | 3.96 | 5.17 |
| 2" | L1@0.15 | Ea | 1.75 | 5.94 | 7.69 |
| 2-1/2" | L1@0.15 | Ea | 10.90 | 5.94 | 16.84 |
| 3" | L1@0.20 | Ea | 14.10 | 7.93 | 22.03 |
| 3-1/2" | L1@0.20 | Ea | 20.60 | 7.93 | 28.53 |
| 4" | L1@0.25 | Ea | 21.20 | 9.91 | 31.11 |



Die cast indent offset EMT connectors

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.10 | Ea | 2.31 | 3.96 | 6.27 |
| 3/4" | L1@0.10 | Ea | 3.17 | 3.96 | 7.13 |



Die cast set screw offset EMT connectors


| | | | | | |
|------|---------|----|------|------|-------|
| 1/2" | L1@0.10 | Ea | 2.89 | 3.96 | 6.85 |
| 3/4" | L1@0.10 | Ea | 4.20 | 3.96 | 8.16 |
| 1" | L1@0.15 | Ea | 6.06 | 5.94 | 12.00 |



Use these figures to estimate the cost of EMT connectors installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the connector locknut, removing the knockout, layout, material handling, and normal waste. Add for insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

Indenter tools are on page 22.

EMT Connectors and Couplings




| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|-----------|------|---------------|------------|----------------|
| Steel compression offset EMT connectors, raintight | | | | | |
| 1/2" | L1@0.10 | Ea | 4.43 | 3.96 | 8.39 |
| 3/4" | L1@0.10 | Ea | 6.42 | 3.96 | 10.38 |
| 1" | L1@0.15 | Ea | 7.13 | 5.94 | 13.07 |

Indent EMT couplings

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.05 | Ea | .77 | 1.98 | 2.75 |
| 3/4" | L1@0.06 | Ea | 1.50 | 2.38 | 3.88 |

Die cast set screw EMT couplings



| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .50 | 1.98 | 2.48 |
| 3/4" | L1@0.06 | Ea | .77 | 2.38 | 3.15 |
| 1" | L1@0.08 | Ea | 1.31 | 3.17 | 4.48 |
| 1-1/4" | L1@0.10 | Ea | 2.29 | 3.96 | 6.25 |
| 1-1/2" | L1@0.10 | Ea | 3.49 | 3.96 | 7.45 |
| 2" | L1@0.15 | Ea | 4.66 | 5.94 | 10.60 |
| 2-1/2" | L1@0.15 | Ea | 8.91 | 5.94 | 14.85 |
| 3" | L1@0.20 | Ea | 10.20 | 7.93 | 18.13 |
| 3-1/2" | L1@0.20 | Ea | 11.80 | 7.93 | 19.73 |
| 4" | L1@0.25 | Ea | 14.40 | 9.91 | 24.31 |

Indenter tools




| | | | | | |
|------------------------------|---|----|-------|---|-------|
| With jaws for 1/2" EMT | — | Ea | 47.00 | — | 47.00 |
| With jaws for 3/4" EMT | — | Ea | 65.40 | — | 65.40 |
| Replacement points, 1/2" EMT | — | Ea | 3.55 | — | 3.55 |
| Replacement points, 3/4" EMT | — | Ea | 3.70 | — | 3.70 |

Use these figures to estimate the cost of EMT connectors and couplings installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each coupling or connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the connector or coupling, layout, material handling, and normal waste. Add for conduit, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Drive-on EMT fittings are rated as raintight and are also concrete tight. They are threaded with a standard electrical pipe thread and can be adapted easily to rigid conduit or other threaded fittings. Material costs assume purchase of full box quantities.


EMT Couplings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|--------------------------------------|-----------|------|---------------|------------|----------------|
| Set screw steel EMT couplings | | | | | |
| 1/2" | L1@0.05 | Ea | .27 | 1.98 | 2.25 |
| 3/4" | L1@0.06 | Ea | .35 | 2.38 | 2.73 |
| 1" | L1@0.08 | Ea | .56 | 3.17 | 3.73 |
| 1-1/4" | L1@0.10 | Ea | 1.13 | 3.96 | 5.09 |
| 1-1/2" | L1@0.10 | Ea | 1.71 | 3.96 | 5.67 |
| 2" | L1@0.15 | Ea | 2.25 | 5.94 | 8.19 |
| 2-1/2" | L1@0.15 | Ea | 4.91 | 5.94 | 10.85 |
| 3" | L1@0.20 | Ea | 5.49 | 7.93 | 13.42 |
| 3-1/2" | L1@0.20 | Ea | 6.74 | 7.93 | 14.67 |
| 4" | L1@0.25 | Ea | 7.33 | 9.91 | 17.24 |




Die cast compression EMT couplings, raintight

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .41 | 1.98 | 2.39 |
| 3/4" | L1@0.06 | Ea | .53 | 2.38 | 2.91 |
| 1" | L1@0.08 | Ea | .86 | 3.17 | 4.03 |
| 1-1/4" | L1@0.10 | Ea | 1.60 | 3.96 | 5.56 |
| 1-1/2" | L1@0.10 | Ea | 2.48 | 3.96 | 6.44 |
| 2" | L1@0.15 | Ea | 3.03 | 5.94 | 8.97 |
| 2-1/2" | L1@0.15 | Ea | 11.80 | 5.94 | 17.74 |
| 3" | L1@0.20 | Ea | 12.60 | 7.93 | 20.53 |
| 3-1/2" | L1@0.20 | Ea | 15.40 | 7.93 | 23.33 |
| 4" | L1@0.25 | Ea | 16.10 | 9.91 | 26.01 |




Steel compression EMT couplings, raintight

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .41 | 1.98 | 2.39 |
| 3/4" | L1@0.06 | Ea | .59 | 2.38 | 2.97 |
| 1" | L1@0.08 | Ea | .90 | 3.17 | 4.07 |
| 1-1/4" | L1@0.10 | Ea | 1.64 | 3.96 | 5.60 |
| 1-1/2" | L1@0.10 | Ea | 2.38 | 3.96 | 6.34 |
| 2" | L1@0.15 | Ea | 3.25 | 5.94 | 9.19 |
| 2-1/2" | L1@0.15 | Ea | 13.40 | 5.94 | 19.34 |
| 3" | L1@0.20 | Ea | 17.10 | 7.93 | 25.03 |
| 3-1/2" | L1@0.20 | Ea | 24.50 | 7.93 | 32.43 |
| 4" | L1@0.25 | Ea | 25.10 | 9.91 | 35.01 |




Use these figures to estimate the cost of EMT couplings installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each coupling installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the coupling, layout, material handling, and normal waste. Add for conduit, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Compression fittings are raintight and can be used in concrete. Material costs assume purchase of full box quantities.

EMT Couplings and Straps



| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---------------------------------------|-----------|------|---------------|------------|----------------|
| Die cast EMT to flex couplings | | | | | |
| 1/2" | L1@0.05 | Ea | 2.13 | 1.98 | 4.11 |
| 3/4" | L1@0.05 | Ea | 2.86 | 1.98 | 4.84 |
| 1" | L1@0.06 | Ea | 3.99 | 2.38 | 6.37 |



| | | | | | |
|--|---------|----|-------|------|-------|
| Steel EMT to GRS compression couplings, raintight | | | | | |
| 1/2" | L1@0.05 | Ea | 3.27 | 1.98 | 5.25 |
| 3/4" | L1@0.06 | Ea | 4.65 | 2.38 | 7.03 |
| 1" | L1@0.08 | Ea | 7.07 | 3.17 | 10.24 |
| 1-1/4" | L1@0.10 | Ea | 12.30 | 3.96 | 16.26 |
| 1-1/2" | L1@0.10 | Ea | 15.10 | 3.96 | 19.06 |
| 2" | L1@0.15 | Ea | 30.00 | 5.94 | 35.94 |



| | | | | | |
|------------------------------|---------|----|-----|------|------|
| Steel EMT nail straps | | | | | |
| 1/2" | L1@0.02 | Ea | .13 | .79 | .92 |
| 3/4" | L1@0.03 | Ea | .14 | 1.19 | 1.33 |
| 1" | L1@0.05 | Ea | .18 | 1.98 | 2.16 |



| | | | | | |
|----------------------------------|---------|----|------|------|-------|
| Steel one hole EMT straps | | | | | |
| 1/2" | L1@0.03 | Ea | .05 | 1.19 | 1.24 |
| 3/4" | L1@0.04 | Ea | .10 | 1.59 | 1.69 |
| 1" | L1@0.05 | Ea | .16 | 1.98 | 2.14 |
| 1-1/4" | L1@0.06 | Ea | .25 | 2.38 | 2.63 |
| 1-1/2" | L1@0.06 | Ea | .40 | 2.38 | 2.78 |
| 2" | L1@0.10 | Ea | .48 | 3.96 | 4.44 |
| 2-1/2" | L1@0.10 | Ea | 1.81 | 3.96 | 5.77 |
| 3" | L1@0.15 | Ea | 2.22 | 5.94 | 8.16 |
| 3-1/2" | L1@0.15 | Ea | 3.45 | 5.94 | 9.39 |
| 4" | L1@0.15 | Ea | 4.37 | 5.94 | 10.31 |

Use these figures to estimate the cost of EMT couplings and EMT straps installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each coupling and strap installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include cutting the EMT conduit, layout, material handling, and normal waste. Add the cost of conduit, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

EMT Straps

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

One hole heavy duty steel EMT straps

| | | | | | |
|--------|---------|----|------|------|------|
| 1/2" | L1@0.03 | Ea | .23 | 1.19 | 1.42 |
| 3/4" | L1@0.04 | Ea | .30 | 1.59 | 1.89 |
| 1" | L1@0.05 | Ea | .54 | 1.98 | 2.52 |
| 1-1/4" | L1@0.06 | Ea | .72 | 2.38 | 3.10 |
| 1-1/2" | L1@0.06 | Ea | 1.09 | 2.38 | 3.47 |
| 2" | L1@0.10 | Ea | 1.66 | 3.96 | 5.62 |



One hole malleable EMT straps

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.03 | Ea | .34 | 1.19 | 1.53 |
| 3/4" | L1@0.04 | Ea | .49 | 1.59 | 2.08 |
| 1" | L1@0.05 | Ea | .69 | 1.98 | 2.67 |
| 1-1/4" | L1@0.06 | Ea | 1.40 | 2.38 | 3.78 |
| 1-1/2" | L1@0.06 | Ea | 1.60 | 2.38 | 3.98 |
| 2" | L1@0.10 | Ea | 3.15 | 3.96 | 7.11 |
| 2-1/2" | L1@0.10 | Ea | 6.80 | 3.96 | 10.76 |
| 3" | L1@0.15 | Ea | 8.59 | 5.94 | 14.53 |
| 3-1/2" | L1@0.15 | Ea | 11.20 | 5.94 | 17.14 |
| 4" | L1@0.15 | Ea | 24.80 | 5.94 | 30.74 |



Two hole steel EMT straps

| | | | | | |
|--------|---------|----|------|------|------|
| 1/2" | L1@0.03 | Ea | .21 | 1.19 | 1.40 |
| 3/4" | L1@0.04 | Ea | .29 | 1.59 | 1.88 |
| 1" | L1@0.05 | Ea | .47 | 1.98 | 2.45 |
| 1-1/4" | L1@0.06 | Ea | .68 | 2.38 | 3.06 |
| 1-1/2" | L1@0.06 | Ea | .81 | 2.38 | 3.19 |
| 2" | L1@0.10 | Ea | 1.38 | 3.96 | 5.34 |
| 2-1/2" | L1@0.10 | Ea | 2.03 | 3.96 | 5.99 |
| 3" | L1@0.15 | Ea | 2.39 | 5.94 | 8.33 |
| 3-1/2" | L1@0.15 | Ea | 2.48 | 5.94 | 8.42 |
| 4" | L1@0.15 | Ea | 2.95 | 5.94 | 8.89 |



Use these figures to estimate the cost of EMT straps installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each strap installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include cutting the EMT conduit, layout, material handling, and normal waste. Add the cost of conduit, screws or nails to hold the straps, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

EMT Straps, Hangers and Clips

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Two hole heavy duty steel EMT straps

| | | | | | |
|--------|---------|----|------|------|------|
| 1" | L1@0.05 | Ea | .22 | 1.98 | 2.20 |
| 1-1/4" | L1@0.06 | Ea | .29 | 2.38 | 2.67 |
| 1-1/2" | L1@0.06 | Ea | .43 | 2.38 | 2.81 |
| 2" | L1@0.10 | Ea | .69 | 3.96 | 4.65 |
| 2-1/2" | L1@0.10 | Ea | .81 | 3.96 | 4.77 |
| 3" | L1@0.10 | Ea | 1.18 | 3.96 | 5.14 |
| 3-1/2" | L1@0.15 | Ea | 1.75 | 5.94 | 7.69 |
| 4" | L1@0.15 | Ea | 2.99 | 5.94 | 8.93 |



Steel EMT conduit hangers with bolt

| | | | | | |
|--------|---------|----|------|------|-------|
| 1/2" | L1@0.03 | Ea | .53 | 1.19 | 1.72 |
| 3/4" | L1@0.04 | Ea | .60 | 1.59 | 2.19 |
| 1" | L1@0.05 | Ea | .70 | 1.98 | 2.68 |
| 1-1/4" | L1@0.06 | Ea | .85 | 2.38 | 3.23 |
| 1-1/2" | L1@0.06 | Ea | 1.05 | 2.38 | 3.43 |
| 2" | L1@0.10 | Ea | 1.31 | 3.96 | 5.27 |
| 2-1/2" | L1@0.10 | Ea | 1.50 | 3.96 | 5.46 |
| 3" | L1@0.15 | Ea | 1.98 | 5.94 | 7.92 |
| 3-1/2" | L1@0.15 | Ea | 2.31 | 5.94 | 8.25 |
| 4" | L1@0.15 | Ea | 6.17 | 5.94 | 12.11 |




Beam clamp EMT conduit hanger assembly

| | | | | | |
|--------|---------|----|------|------|------|
| 1/2" | L1@0.05 | Ea | 1.05 | 1.98 | 3.03 |
| 3/4" | L1@0.06 | Ea | 1.22 | 2.38 | 3.60 |
| 1" | L1@0.08 | Ea | 1.41 | 3.17 | 4.58 |
| 1-1/4" | L1@0.10 | Ea | 1.69 | 3.96 | 5.65 |
| 1-1/2" | L1@0.10 | Ea | 2.12 | 3.96 | 6.08 |
| 2" | L1@0.15 | Ea | 2.61 | 5.94 | 8.55 |



EMT Strut Clamp

| | | | | | |
|--------|---------|----|------|------|------|
| 1/2" | L1@0.06 | Ea | .77 | 2.38 | 3.15 |
| 3/4" | L1@0.08 | Ea | .79 | 3.17 | 3.96 |
| 1" | L1@0.10 | Ea | .91 | 3.96 | 4.87 |
| 1-1/4" | L1@0.10 | Ea | 1.03 | 3.96 | 4.99 |
| 1-1/2" | L1@0.10 | Ea | 1.26 | 3.96 | 5.22 |
| 2" | L1@0.15 | Ea | 1.31 | 5.94 | 7.25 |



Use these figures to estimate the cost of EMT straps, hangers and clips installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each strap, hanger or clip installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include cutting the EMT conduit, layout, material handling, and normal waste. Add the cost of conduit, screws or nails to hold the straps, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

EMT Clips, Adapters, Elbows, Caps and Benders

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

EMT clips for rod, wire, or steel flange

| | | | | | |
|--------|---------|----|-----|------|------|
| 1/2" | L1@0.04 | Ea | .25 | 1.59 | 1.84 |
| 3/4" | L1@0.05 | Ea | .28 | 1.98 | 2.26 |
| 1" | L1@0.06 | Ea | .32 | 2.38 | 2.70 |
| 1-1/4" | L1@0.08 | Ea | .39 | 3.17 | 3.56 |




EMT split adapters

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.08 | Ea | 2.23 | 3.17 | 5.40 |
| 3/4" | L1@0.10 | Ea | 1.99 | 3.96 | 5.95 |
| 1" | L1@0.15 | Ea | 2.75 | 5.94 | 8.69 |


Die cast 90 degree EMT elbows

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.10 | Ea | 4.40 | 3.96 | 8.36 |
| 3/4" | L1@0.10 | Ea | 6.87 | 3.96 | 10.83 |
| 1" | L1@0.15 | Ea | 9.54 | 5.94 | 15.48 |
| 1-1/4" | L1@0.15 | Ea | 47.40 | 5.94 | 53.34 |
| 1-1/2" | L1@0.15 | Ea | 61.70 | 5.94 | 67.64 |




90 degree EMT short elbows

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.10 | Ea | 3.91 | 3.96 | 7.87 |
| 3/4" | L1@0.10 | Ea | 5.47 | 3.96 | 9.43 |
| 1" | L1@0.15 | Ea | 9.63 | 5.94 | 15.57 |
| 1-1/4" | L1@0.15 | Ea | 38.10 | 5.94 | 44.04 |




Slip-fitter EMT entrance caps

| | | | | | |
|--------|---------|----|------|------|-------|
| 1/2" | L1@0.10 | Ea | 6.47 | 3.96 | 10.43 |
| 3/4" | L1@0.10 | Ea | 7.58 | 3.96 | 11.54 |
| 1" | L1@0.15 | Ea | 8.91 | 5.94 | 14.85 |
| 1-1/4" | L1@0.15 | Ea | 9.99 | 5.94 | 15.93 |




EMT hand benders

| | | | | | |
|------|---|----|-------|---|-------|
| 1/2" | — | Ea | 32.60 | — | 32.60 |
| 3/4" | — | Ea | 70.70 | — | 70.70 |
| 1" | — | Ea | 79.00 | — | 79.00 |




Use these figures to estimate the cost of items shown above installed on EMT conduit under the conditions described on pages 5 and 6. Costs listed are for each item installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the connector locknut, removing the knockout when required, layout, material handling, and normal waste. Add for conduit boxes, insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

Flexible Conduit



| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---------------------------|-----------|------|---------------|------------|----------------|
| Flex steel conduit | | | | | |
| 3/8" | L1@2.50 | CLF | 31.90 | 99.10 | 131.00 |
| 1/2" | L1@2.75 | CLF | 28.40 | 109.00 | 137.40 |
| 3/4" | L1@3.00 | CLF | 38.70 | 119.00 | 157.70 |
| 1" | L1@3.25 | CLF | 70.70 | 129.00 | 199.70 |
| 1-1/4" | L1@3.50 | CLF | 90.90 | 139.00 | 229.90 |
| 1-1/2" | L1@3.75 | CLF | 149.00 | 149.00 | 298.00 |
| 2" | L1@4.00 | CLF | 182.00 | 159.00 | 341.00 |
| 2-1/2" | L1@4.25 | CLF | 220.00 | 168.00 | 388.00 |
| 3" | L1@4.50 | CLF | 383.00 | 178.00 | 561.00 |
| 3-1/2" | L1@4.75 | CLF | 545.00 | 188.00 | 733.00 |
| 4" | L1@5.00 | CLF | 493.00 | 198.00 | 691.00 |



| | | | | | |
|------------------------------|---------|-----|--------|--------|--------|
| Flex aluminum conduit | | | | | |
| 3/8" | L1@2.25 | CLF | 34.90 | 89.20 | 124.10 |
| 1/2" | L1@2.50 | CLF | 29.00 | 99.10 | 128.10 |
| 3/4" | L1@2.75 | CLF | 40.00 | 109.00 | 149.00 |
| 1" | L1@3.00 | CLF | 75.20 | 119.00 | 194.20 |
| 1-1/4" | L1@3.25 | CLF | 99.90 | 129.00 | 228.90 |
| 1-1/2" | L1@3.50 | CLF | 180.00 | 139.00 | 319.00 |
| 2" | L1@3.75 | CLF | 191.00 | 149.00 | 340.00 |
| 2-1/2" | L1@4.00 | CLF | 305.00 | 159.00 | 464.00 |
| 3" | L1@4.25 | CLF | 500.00 | 168.00 | 668.00 |
| 3-1/2" | L1@4.50 | CLF | 577.00 | 178.00 | 755.00 |
| 4" | L1@4.75 | CLF | 643.00 | 188.00 | 831.00 |


Use these figures to estimate the cost of flexible conduit installed in a building, and for equipment hookup under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include boring or notching wood studs and joists (in concealed locations), cutting flex conduit, layout, material handling, and normal waste. Add for connectors, couplings, straps, boxes, wire, bonding wire, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Conduit runs are assumed to be 25' long. Labor costs per linear foot will be higher on shorter runs and lower on longer runs.

Flexible Conduit Connectors

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Die cast screw-in flex connectors

| | | | | | |
|--------|---------|----|------|------|------|
| 3/8" | L1@0.03 | Ea | .24 | 1.19 | 1.43 |
| 1/2" | L1@0.03 | Ea | .32 | 1.19 | 1.51 |
| 3/4" | L1@0.05 | Ea | .56 | 1.98 | 2.54 |
| 1" | L1@0.06 | Ea | 1.23 | 2.38 | 3.61 |
| 1-1/4" | L1@0.10 | Ea | 2.37 | 3.96 | 6.33 |
| 1-1/2" | L1@0.10 | Ea | 3.31 | 3.96 | 7.27 |
| 2" | L1@0.15 | Ea | 4.02 | 5.94 | 9.96 |




Insulated die cast screw-in flex connectors

| | | | | | |
|--------|---------|----|------|------|-------|
| 3/8" | L1@0.03 | Ea | .50 | 1.19 | 1.69 |
| 1/2" | L1@0.03 | Ea | .57 | 1.19 | 1.76 |
| 3/4" | L1@0.05 | Ea | .74 | 1.98 | 2.72 |
| 1" | L1@0.06 | Ea | 1.60 | 2.38 | 3.98 |
| 1-1/4" | L1@0.10 | Ea | 3.69 | 3.96 | 7.65 |
| 1-1/2" | L1@0.10 | Ea | 4.38 | 3.96 | 8.34 |
| 2" | L1@0.15 | Ea | 5.05 | 5.94 | 10.99 |




Die cast squeeze flex connectors

| | | | | | |
|--------|---------|----|-------|------|-------|
| 3/8" | L1@0.05 | Ea | .97 | 1.98 | 2.95 |
| 1/2" | L1@0.05 | Ea | 1.12 | 1.98 | 3.10 |
| 3/4" | L1@0.06 | Ea | 1.25 | 2.38 | 3.63 |
| 1" | L1@0.08 | Ea | 2.48 | 3.17 | 5.65 |
| 1-1/4" | L1@0.10 | Ea | 5.39 | 3.96 | 9.35 |
| 1-1/2" | L1@0.10 | Ea | 10.20 | 3.96 | 14.16 |
| 2" | L1@0.15 | Ea | 17.30 | 5.94 | 23.24 |




Use these figures to estimate the cost of flexible conduit connectors installed on flex conduit under the conditions described on pages 5 and 6. Costs listed are for each connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the locknut, removing the knockout, layout, material handling, and normal waste. Add for connectors, couplings, straps, boxes, wire, bonding wire, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full boxes.


Squeeze Flexible Conduit Connectors



| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|-----------|------|---------------|------------|----------------|
| Insulated die cast squeeze flex connectors | | | | | |
| 1/2" | L1@0.05 | Ea | 1.71 | 1.98 | 3.69 |
| 3/4" | L1@0.06 | Ea | 1.74 | 2.38 | 4.12 |
| 1" | L1@0.08 | Ea | 2.12 | 3.17 | 5.29 |
| 1-1/4" | L1@0.10 | Ea | 5.13 | 3.96 | 9.09 |
| 1-1/2" | L1@0.10 | Ea | 8.42 | 3.96 | 12.38 |
| 2" | L1@0.15 | Ea | 12.80 | 5.94 | 18.74 |



| | | | | | |
|--|---------|----|-------|------|-------|
| Malleable squeeze flex connectors | | | | | |
| 3/8" | L1@0.05 | Ea | .95 | 1.98 | 2.93 |
| 1/2" | L1@0.05 | Ea | 1.41 | 1.98 | 3.39 |
| 3/4" | L1@0.06 | Ea | 1.13 | 2.38 | 3.51 |
| 1" | L1@0.08 | Ea | 4.16 | 3.17 | 7.33 |
| 1-1/4" | L1@0.10 | Ea | 6.54 | 3.96 | 10.50 |
| 1-1/2" | L1@0.10 | Ea | 8.91 | 3.96 | 12.87 |
| 2" | L1@0.15 | Ea | 12.50 | 5.94 | 18.44 |
| 2-1/2" | L1@0.15 | Ea | 24.40 | 5.94 | 30.34 |
| 3" | L1@0.20 | Ea | 33.80 | 7.93 | 41.73 |



| | | | | | |
|--|---------|----|--------|------|--------|
| Insulated malleable squeeze flex connectors | | | | | |
| 3/8" | L1@0.05 | Ea | 1.94 | 1.98 | 3.92 |
| 1/2" | L1@0.05 | Ea | 2.06 | 1.98 | 4.04 |
| 3/4" | L1@0.06 | Ea | 2.29 | 2.38 | 4.67 |
| 1" | L1@0.08 | Ea | 4.16 | 3.17 | 7.33 |
| 1-1/4" | L1@0.10 | Ea | 8.91 | 3.96 | 12.87 |
| 1-1/2" | L1@0.10 | Ea | 13.10 | 3.96 | 17.06 |
| 2" | L1@0.15 | Ea | 19.80 | 5.94 | 25.74 |
| 2-1/2" | L1@0.15 | Ea | 38.80 | 5.94 | 44.74 |
| 3" | L1@0.20 | Ea | 50.90 | 7.93 | 58.83 |
| 3-1/2" | L1@0.25 | Ea | 141.00 | 9.91 | 150.91 |
| 4" | L1@0.25 | Ea | 166.00 | 9.91 | 175.91 |


Use these figures to estimate the cost of flexible conduit connectors installed on flex conduit under the conditions described on pages 5 and 6. Costs listed are for each connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the locknut, removing the knockout, layout, material handling, and normal waste. Add for conduit boxes, insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full boxes.

Flexible Conduit Connectors

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


45 degree die cast flex connectors

| | | | | | |
|------|---------|----|------|------|------|
| 3/8" | L1@0.05 | Ea | .42 | 1.98 | 2.40 |
| 1/2" | L1@0.05 | Ea | .54 | 1.98 | 2.52 |
| 3/4" | L1@0.06 | Ea | 1.49 | 2.38 | 3.87 |




45 degree malleable flex connectors

| | | | | | |
|------|---------|----|------|------|------|
| 3/8" | L1@0.05 | Ea | 1.27 | 1.98 | 3.25 |
| 1/2" | L1@0.06 | Ea | 1.38 | 2.38 | 3.76 |




90 degree die cast two screw flex connectors

| | | | | | |
|--------|---------|----|-------|------|-------|
| 3/8" | L1@0.05 | Ea | .37 | 1.98 | 2.35 |
| 1/2" | L1@0.05 | Ea | .51 | 1.98 | 2.49 |
| 3/4" | L1@0.06 | Ea | 1.38 | 2.38 | 3.76 |
| 1" | L1@0.08 | Ea | 2.87 | 3.17 | 6.04 |
| 1-1/4" | L1@0.10 | Ea | 4.36 | 3.96 | 8.32 |
| 1-1/2" | L1@0.15 | Ea | 10.50 | 5.94 | 16.44 |
| 2" | L1@0.20 | Ea | 28.40 | 7.93 | 36.33 |
| 2-1/2" | L1@0.25 | Ea | 35.20 | 9.91 | 45.11 |
| 3" | L1@0.25 | Ea | 47.20 | 9.91 | 57.11 |



Insulated 90 degree die cast two screw flex connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.05 | Ea | .51 | 1.98 | 2.49 |
| 1/2" | L1@0.05 | Ea | .67 | 1.98 | 2.65 |
| 3/4" | L1@0.06 | Ea | 1.60 | 2.38 | 3.98 |
| 1" | L1@0.08 | Ea | 3.25 | 3.17 | 6.42 |
| 1-1/4" | L1@0.10 | Ea | 5.89 | 3.96 | 9.85 |
| 1-1/2" | L1@0.15 | Ea | 11.40 | 5.94 | 17.34 |
| 2" | L1@0.20 | Ea | 29.80 | 7.93 | 37.73 |
| 2-1/2" | L1@0.25 | Ea | 36.50 | 9.91 | 46.41 |
| 3" | L1@0.25 | Ea | 48.20 | 9.91 | 58.11 |
| 3-1/2" | L1@0.30 | Ea | 110.00 | 11.90 | 121.90 |
| 4" | L1@0.30 | Ea | 131.00 | 11.90 | 142.90 |




Use these figures to estimate the cost of flexible conduit connectors installed on flex conduit under the conditions described on pages 5 and 6. Costs listed are for each connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the locknut, removing the knockout, layout, material handling, and normal waste. Add for conduit boxes, insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full boxes.

Flexible Conduit Connectors and Couplings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

90 degree malleable squeeze flex connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.05 | Ea | .86 | 1.98 | 2.84 |
| 1/2" | L1@0.05 | Ea | 1.68 | 1.98 | 3.66 |
| 3/4" | L1@0.06 | Ea | 2.40 | 2.38 | 4.78 |
| 1" | L1@0.08 | Ea | 3.20 | 3.17 | 6.37 |
| 1-1/4" | L1@0.10 | Ea | 7.00 | 3.96 | 10.96 |
| 1-1/2" | L1@0.15 | Ea | 13.60 | 5.94 | 19.54 |
| 2" | L1@0.20 | Ea | 19.90 | 7.93 | 27.83 |
| 2-1/2" | L1@0.25 | Ea | 22.70 | 9.91 | 32.61 |
| 3" | L1@0.25 | Ea | 61.80 | 9.91 | 71.71 |
| 3-1/2" | L1@0.30 | Ea | 93.60 | 11.90 | 105.50 |
| 4" | L1@0.30 | Ea | 228.00 | 11.90 | 239.90 |



Insulated 90 degree malleable squeeze flex connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.05 | Ea | 1.18 | 1.98 | 3.16 |
| 1/2" | L1@0.05 | Ea | 1.95 | 1.98 | 3.93 |
| 3/4" | L1@0.06 | Ea | 2.48 | 2.38 | 4.86 |
| 1" | L1@0.08 | Ea | 3.45 | 3.17 | 6.62 |
| 1-1/4" | L1@0.10 | Ea | 7.97 | 3.96 | 11.93 |
| 1-1/2" | L1@0.15 | Ea | 14.10 | 5.94 | 20.04 |
| 2" | L1@0.20 | Ea | 21.20 | 7.93 | 29.13 |
| 2-1/2" | L1@0.25 | Ea | 24.80 | 9.91 | 34.71 |
| 3" | L1@0.25 | Ea | 62.70 | 9.91 | 72.61 |
| 3-1/2" | L1@0.30 | Ea | 95.40 | 11.90 | 107.30 |
| 4" | L1@0.30 | Ea | 237.00 | 11.90 | 248.90 |



Die cast screw-in flex couplings

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.03 | Ea | 1.55 | 1.19 | 2.74 |
| 3/4" | L1@0.05 | Ea | 2.55 | 1.98 | 4.53 |
| 1" | L1@0.06 | Ea | 4.44 | 2.38 | 6.82 |

Die cast screw-in flex to EMT couplings

| | | | | | |
|------|---------|----|------|------|------|
| 3/8" | L1@0.05 | Ea | 1.68 | 1.98 | 3.66 |
| 1/2" | L1@0.06 | Ea | 2.60 | 2.38 | 4.98 |
| 3/4" | L1@0.08 | Ea | 3.61 | 3.17 | 6.78 |
| 1" | L1@0.10 | Ea | 5.07 | 3.96 | 9.03 |

Die cast set screw flex to rigid couplings

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.05 | Ea | 3.54 | 1.98 | 5.52 |
| 3/4" | L1@0.06 | Ea | 4.51 | 2.38 | 6.89 |


Use these figures to estimate the cost of flexible conduit connectors and couplings installed on flex conduit under the conditions described on pages 5 and 6. Costs listed are for each connector or coupling installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the locknut, removing the knockout, layout, material handling, and normal waste. Add for conduit boxes, insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full boxes.

Liquid-tight Flexible Conduit

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Type EF or Type LT flex steel conduit

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 3/8" | L1@4.00 | CLF | 53.40 | 159.00 | 212.40 |
| 1/2" | L1@4.00 | CLF | 63.50 | 159.00 | 222.50 |
| 3/4" | L1@4.50 | CLF | 84.70 | 178.00 | 262.70 |
| 1" | L1@5.00 | CLF | 129.00 | 198.00 | 327.00 |
| 1-1/4" | L1@6.00 | CLF | 176.00 | 238.00 | 414.00 |
| 1-1/2" | L1@7.00 | CLF | 239.00 | 277.00 | 516.00 |
| 2" | L1@9.00 | CLF | 300.00 | 357.00 | 657.00 |
| 2-1/2" | L1@11.0 | CLF | 774.00 | 436.00 | 1,210.00 |
| 3" | L1@15.0 | CLF | 1,060.00 | 594.00 | 1,654.00 |
| 4" | L1@17.0 | CLF | 1,540.00 | 674.00 | 2,214.00 |




Type UA liquid-tight flex conduit

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 3/8" | L1@4.00 | CLF | 125.00 | 159.00 | 284.00 |
| 1/2" | L1@4.00 | CLF | 147.00 | 159.00 | 306.00 |
| 3/4" | L1@4.50 | CLF | 204.00 | 178.00 | 382.00 |
| 1" | L1@5.00 | CLF | 317.00 | 198.00 | 515.00 |
| 1-1/4" | L1@6.00 | CLF | 452.00 | 238.00 | 690.00 |
| 1-1/2" | L1@7.00 | CLF | 471.00 | 277.00 | 748.00 |
| 2" | L1@9.00 | CLF | 587.00 | 357.00 | 944.00 |
| 2-1/2" | L1@11.0 | CLF | 1,070.00 | 436.00 | 1,506.00 |
| 3" | L1@15.0 | CLF | 1,530.00 | 594.00 | 2,124.00 |
| 4" | L1@17.0 | CLF | 2,450.00 | 674.00 | 3,124.00 |




Type OR liquid-tight flex conduit

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 3/8" | L1@4.00 | CLF | 121.00 | 159.00 | 280.00 |
| 1/2" | L1@4.00 | CLF | 140.00 | 159.00 | 299.00 |
| 3/4" | L1@4.50 | CLF | 213.00 | 178.00 | 391.00 |
| 1" | L1@5.00 | CLF | 292.00 | 198.00 | 490.00 |
| 1-1/4" | L1@6.00 | CLF | 383.00 | 238.00 | 621.00 |
| 1-1/2" | L1@7.00 | CLF | 539.00 | 277.00 | 816.00 |
| 2" | L1@9.00 | CLF | 672.00 | 357.00 | 1,029.00 |
| 2-1/2" | L1@11.0 | CLF | 1,320.00 | 436.00 | 1,756.00 |
| 3" | L1@15.0 | CLF | 1,800.00 | 594.00 | 2,394.00 |
| 4" | L1@17.0 | CLF | 2,540.00 | 674.00 | 3,214.00 |



Construction grade liquid-tight flex conduit

| | | | | | |
|--------|---------|-----|--------|--------|--------|
| 3/8" | L1@4.00 | CLF | 45.40 | 159.00 | 204.40 |
| 1/2" | L1@4.00 | CLF | 73.00 | 159.00 | 232.00 |
| 3/4" | L1@4.50 | CLF | 103.00 | 178.00 | 281.00 |
| 1" | L1@5.00 | CLF | 156.00 | 198.00 | 354.00 |
| 1-1/4" | L1@6.00 | CLF | 222.00 | 238.00 | 460.00 |
| 1-1/2" | L1@7.00 | CLF | 255.00 | 277.00 | 532.00 |
| 2" | L1@9.00 | CLF | 312.00 | 357.00 | 669.00 |




Use these figures to estimate the cost of liquid-tight flex conduit installed as part of equipment hookup under the conditions described on pages 5 and 6. Costs listed are for each linear foot installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include cutting conduit, layout, material handling, and normal waste. Add for connectors, boxes, straps, wire, bonding wire, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Conduit runs are assumed to be 25' long. Labor costs per linear foot will be higher on shorter runs and lower on longer runs.

Liquid-tight Flexible Conduit and Connectors


| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Type HC liquid-tight extra flex conduit




| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 3/8" | L1@4.00 | CLF | 156.00 | 159.00 | 315.00 |
| 1/2" | L1@4.00 | CLF | 164.00 | 159.00 | 323.00 |
| 3/4" | L1@4.50 | CLF | 228.00 | 178.00 | 406.00 |
| 1" | L1@5.00 | CLF | 332.00 | 198.00 | 530.00 |
| 1-1/4" | L1@6.00 | CLF | 451.00 | 238.00 | 689.00 |
| 1-1/2" | L1@7.00 | CLF | 615.00 | 277.00 | 892.00 |
| 2" | L1@9.00 | CLF | 766.00 | 357.00 | 1,123.00 |
| 2-1/2" | L1@11.0 | CLF | 1,420.00 | 436.00 | 1,856.00 |
| 3" | L1@15.0 | CLF | 1,970.00 | 594.00 | 2,564.00 |
| 4" | L1@17.0 | CLF | 2,880.00 | 674.00 | 3,554.00 |

Type CN-P liquid-tight flex non-metallic conduit




| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 3/8" | L1@3.50 | CLF | 185.00 | 139.00 | 324.00 |
| 1/2" | L1@3.75 | CLF | 240.00 | 149.00 | 389.00 |
| 3/4" | L1@4.00 | CLF | 342.00 | 159.00 | 501.00 |
| 1" | L1@4.50 | CLF | 438.00 | 178.00 | 616.00 |
| 1-1/4" | L1@5.00 | CLF | 572.00 | 198.00 | 770.00 |
| 1-1/2" | L1@5.50 | CLF | 950.00 | 218.00 | 1,168.00 |
| 2" | L1@6.00 | CLF | 1,330.00 | 238.00 | 1,568.00 |

Malleable liquid-tight flex connectors



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.10 | Ea | 3.39 | 3.96 | 7.35 |
| 1/2" | L1@0.10 | Ea | 3.39 | 3.96 | 7.35 |
| 3/4" | L1@0.10 | Ea | 4.83 | 3.96 | 8.79 |
| 1" | L1@0.15 | Ea | 7.10 | 5.94 | 13.04 |
| 1-1/4" | L1@0.20 | Ea | 12.20 | 7.93 | 20.13 |
| 1-1/2" | L1@0.20 | Ea | 17.30 | 7.93 | 25.23 |
| 2" | L1@0.25 | Ea | 32.00 | 9.91 | 41.91 |
| 2-1/2" | L1@0.25 | Ea | 146.00 | 9.91 | 155.91 |
| 3" | L1@0.30 | Ea | 166.00 | 11.90 | 177.90 |
| 4" | L1@0.30 | Ea | 215.00 | 11.90 | 226.90 |

Insulated malleable liquid-tight flex connectors



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.10 | Ea | 4.26 | 3.96 | 8.22 |
| 1/2" | L1@0.10 | Ea | 4.26 | 3.96 | 8.22 |
| 3/4" | L1@0.10 | Ea | 6.24 | 3.96 | 10.20 |
| 1" | L1@0.15 | Ea | 9.59 | 5.94 | 15.53 |
| 1-1/4" | L1@0.20 | Ea | 15.50 | 7.93 | 23.43 |
| 1-1/2" | L1@0.20 | Ea | 22.50 | 7.93 | 30.43 |
| 2" | L1@0.25 | Ea | 42.10 | 9.91 | 52.01 |
| 2-1/2" | L1@0.25 | Ea | 230.00 | 9.91 | 239.91 |
| 3" | L1@0.30 | Ea | 258.00 | 11.90 | 269.90 |
| 4" | L1@0.30 | Ea | 308.00 | 11.90 | 319.90 |


Use these figures to estimate the cost of liquid-tight flex conduit (two top tables) and connectors (two bottom tables) installed with equipment hookup under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet of conduit and each connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include cutting conduit, removal of the knockout for the connector, layout, material handling, and normal waste. Add for straps, boxes, wire, bonding wire, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Connector costs assume the purchase of full box quantities.

Liquid-tight Flexible Conduit

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Die cast liquid-tight flex connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.10 | Ea | 3.36 | 3.96 | 7.32 |
| 1/2" | L1@0.10 | Ea | 3.30 | 3.96 | 7.26 |
| 3/4" | L1@0.10 | Ea | 4.70 | 3.96 | 8.66 |
| 1" | L1@0.15 | Ea | 6.96 | 5.94 | 12.90 |
| 1-1/4" | L1@0.20 | Ea | 12.00 | 7.93 | 19.93 |
| 1-1/2" | L1@0.20 | Ea | 16.70 | 7.93 | 24.63 |
| 2" | L1@0.25 | Ea | 30.80 | 9.91 | 40.71 |
| 2-1/2" | L1@0.25 | Ea | 145.00 | 9.91 | 154.91 |
| 3" | L1@0.30 | Ea | 162.00 | 11.90 | 173.90 |
| 4" | L1@0.30 | Ea | 212.00 | 11.90 | 223.90 |




Insulated die cast liquid-tight flex connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.10 | Ea | 3.59 | 3.96 | 7.55 |
| 1/2" | L1@0.10 | Ea | 3.59 | 3.96 | 7.55 |
| 3/4" | L1@0.10 | Ea | 5.28 | 3.96 | 9.24 |
| 1" | L1@0.15 | Ea | 8.12 | 5.94 | 14.06 |
| 1-1/4" | L1@0.20 | Ea | 12.80 | 7.93 | 20.73 |
| 1-1/2" | L1@0.20 | Ea | 18.10 | 7.93 | 26.03 |
| 2" | L1@0.25 | Ea | 33.60 | 9.91 | 43.51 |
| 2-1/2" | L1@0.25 | Ea | 173.00 | 9.91 | 182.91 |
| 3" | L1@0.30 | Ea | 192.00 | 11.90 | 203.90 |
| 4" | L1@0.30 | Ea | 225.00 | 11.90 | 236.90 |




45 degree malleable liquid-tight flex connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.12 | Ea | 2.12 | 4.76 | 6.88 |
| 1/2" | L1@0.12 | Ea | 2.08 | 4.76 | 6.84 |
| 3/4" | L1@0.15 | Ea | 3.20 | 5.94 | 9.14 |
| 1" | L1@0.15 | Ea | 6.27 | 5.94 | 12.21 |
| 1-1/4" | L1@0.20 | Ea | 10.70 | 7.93 | 18.63 |
| 1-1/2" | L1@0.20 | Ea | 14.10 | 7.93 | 22.03 |
| 2" | L1@0.25 | Ea | 18.60 | 9.91 | 28.51 |
| 2-1/2" | L1@0.25 | Ea | 90.60 | 9.91 | 100.51 |
| 3" | L1@0.30 | Ea | 97.30 | 11.90 | 109.20 |
| 4" | L1@0.30 | Ea | 121.00 | 11.90 | 132.90 |



Insulated 45 degree malleable liquid-tight flex connectors

| | | | | | |
|------|---------|----|-------|------|-------|
| 3/8" | L1@0.12 | Ea | 4.26 | 4.76 | 9.02 |
| 1/2" | L1@0.12 | Ea | 6.81 | 4.76 | 11.57 |
| 3/4" | L1@0.15 | Ea | 10.30 | 5.94 | 16.24 |




Use these figures to estimate the cost of liquid-tight flex connectors installed on liquid-tight flex conduit under the conditions described on pages 5 and 6. Costs listed are for each connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include locknuts and removal of the knockout, layout, material handling, and normal waste. Add for conduit, insulating bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

Liquid-tight Flex Connectors and Couplings


| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Insulated 45 degree malleable liquid-tight flex connectors




| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1" | L1@0.15 | Ea | 19.90 | 5.94 | 25.84 |
| 1-1/4" | L1@0.20 | Ea | 30.80 | 7.93 | 38.73 |
| 1-1/2" | L1@0.20 | Ea | 37.50 | 7.93 | 45.43 |
| 2" | L1@0.25 | Ea | 56.20 | 9.91 | 66.11 |
| 2-1/2" | L1@0.25 | Ea | 27.80 | 9.91 | 37.71 |
| 3" | L1@0.30 | Ea | 33.40 | 11.90 | 45.30 |
| 4" | L1@0.30 | Ea | 38.40 | 11.90 | 50.30 |

90 degree malleable liquid-tight flex connectors




| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.15 | Ea | 5.23 | 5.94 | 11.17 |
| 1/2" | L1@0.15 | Ea | 5.12 | 5.94 | 11.06 |
| 3/4" | L1@0.15 | Ea | 7.81 | 5.94 | 13.75 |
| 1" | L1@0.20 | Ea | 16.00 | 7.93 | 23.93 |
| 1-1/4" | L1@0.25 | Ea | 24.00 | 9.91 | 33.91 |
| 1-1/2" | L1@0.25 | Ea | 29.00 | 9.91 | 38.91 |
| 2" | L1@0.30 | Ea | 42.40 | 11.90 | 54.30 |
| 2-1/2" | L1@0.30 | Ea | 192.00 | 11.90 | 203.90 |
| 3" | L1@0.40 | Ea | 233.00 | 15.90 | 248.90 |
| 4" | L1@0.40 | Ea | 344.00 | 15.90 | 359.90 |

Insulated 90 degree malleable liquid-tight flex connectors



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/8" | L1@0.15 | Ea | 6.81 | 5.94 | 12.75 |
| 1/2" | L1@0.15 | Ea | 6.81 | 5.94 | 12.75 |
| 3/4" | L1@0.15 | Ea | 10.30 | 5.94 | 16.24 |
| 1" | L1@0.20 | Ea | 19.60 | 7.93 | 27.53 |
| 1-1/4" | L1@0.25 | Ea | 29.70 | 9.91 | 39.61 |
| 1-1/2" | L1@0.25 | Ea | 36.30 | 9.91 | 46.21 |
| 2" | L1@0.30 | Ea | 54.50 | 11.90 | 66.40 |
| 2-1/2" | L1@0.30 | Ea | 276.00 | 11.90 | 287.90 |
| 3" | L1@0.40 | Ea | 331.00 | 15.90 | 346.90 |
| 4" | L1@0.40 | Ea | 431.00 | 15.90 | 446.90 |

Malleable liquid-tight flex to rigid combination couplings



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.15 | Ea | 4.57 | 5.94 | 10.51 |
| 3/4" | L1@0.15 | Ea | 4.57 | 5.94 | 10.51 |
| 1" | L1@0.20 | Ea | 6.46 | 7.93 | 14.39 |
| 1-1/4" | L1@0.25 | Ea | 21.20 | 9.91 | 31.11 |
| 1-1/2" | L1@0.25 | Ea | 37.80 | 9.91 | 47.71 |
| 2" | L1@0.30 | Ea | 52.00 | 11.90 | 63.90 |
| 2-1/2" | L1@0.30 | Ea | 243.00 | 11.90 | 254.90 |
| 3" | L1@0.40 | Ea | 268.00 | 15.90 | 283.90 |
| 4" | L1@0.40 | Ea | 331.00 | 15.90 | 346.90 |


Use these figures to estimate the cost of liquid-tight flex connectors installed on liquid-tight flex conduit under the conditions described on pages 5 and 6. Costs listed are for each connector installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include locknuts and removal of the knockout, layout, material handling, and normal waste. Add for conduit, insulating bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

PVC Conduit and Elbows

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Schedule 40 PVC conduit, 10' lengths with coupling

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 1/2" | L1@3.10 | CLF | 68.10 | 123.00 | 191.10 |
| 3/4" | L1@3.20 | CLF | 90.30 | 127.00 | 217.30 |
| 1" | L1@3.30 | CLF | 135.00 | 131.00 | 266.00 |
| 1-1/4" | L1@3.40 | CLF | 184.00 | 135.00 | 319.00 |
| 1-1/2" | L1@3.45 | CLF | 221.00 | 137.00 | 358.00 |
| 2" | L1@3.50 | CLF | 290.00 | 139.00 | 429.00 |
| 2-1/2" | L2@3.60 | CLF | 466.00 | 143.00 | 609.00 |
| 3" | L2@3.75 | CLF | 552.00 | 149.00 | 701.00 |
| 4" | L2@4.00 | CLF | 777.00 | 159.00 | 936.00 |
| 5" | L2@4.25 | CLF | 1,120.00 | 168.00 | 1,288.00 |
| 6" | L2@4.50 | CLF | 1,480.00 | 178.00 | 1,658.00 |




Schedule 80 heavy wall PVC conduit, 10' lengths with coupling

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 1/2" | L1@3.20 | CLF | 135.00 | 127.00 | 262.00 |
| 3/4" | L1@3.30 | CLF | 182.00 | 131.00 | 313.00 |
| 1" | L1@3.40 | CLF | 260.00 | 135.00 | 395.00 |
| 1-1/4" | L1@3.50 | CLF | 362.00 | 139.00 | 501.00 |
| 1-1/2" | L1@3.60 | CLF | 434.00 | 143.00 | 577.00 |
| 2" | L1@3.70 | CLF | 597.00 | 147.00 | 744.00 |
| 2-1/2" | L2@3.90 | CLF | 917.00 | 155.00 | 1,072.00 |
| 3" | L2@4.00 | CLF | 1,220.00 | 159.00 | 1,379.00 |
| 4" | L2@4.50 | CLF | 1,780.00 | 178.00 | 1,958.00 |
| 5" | L2@5.00 | CLF | 2,560.00 | 198.00 | 2,758.00 |
| 6" | L2@6.00 | CLF | 2,730.00 | 238.00 | 2,968.00 |



30 degree Schedule 40 PVC elbows

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.05 | Ea | 1.62 | 1.98 | 3.60 |
| 3/4" | L1@0.06 | Ea | 1.67 | 2.38 | 4.05 |
| 1" | L1@0.08 | Ea | 2.00 | 3.17 | 5.17 |
| 1-1/4" | L1@0.10 | Ea | 2.86 | 3.96 | 6.82 |
| 1-1/2" | L1@0.10 | Ea | 3.94 | 3.96 | 7.90 |
| 2" | L1@0.15 | Ea | 5.77 | 5.94 | 11.71 |
| 2-1/2" | L2@0.15 | Ea | 10.90 | 5.94 | 16.84 |
| 3" | L2@0.20 | Ea | 18.60 | 7.93 | 26.53 |
| 4" | L2@0.25 | Ea | 30.90 | 9.91 | 40.81 |
| 5" | L2@0.30 | Ea | 49.80 | 11.90 | 61.70 |
| 6" | L2@0.50 | Ea | 58.00 | 19.80 | 77.80 |



Use these figures to estimate the cost of PVC conduit and elbows installed underground or in a building under the conditions described on pages 5 and 6. Costs listed are for 100 linear feet of conduit installed or for each elbow installed. The crew is one electrician for diameters to 2" and two electricians for 2-1/2" and larger conduit. The labor cost is \$39.63 per manhour. These costs include making up joints with cement (glue), layout, material handling, and normal waste. Add for bends, connectors, end bell, spacers, wire, trenching, encasement, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Conduit runs are assumed to be 50' long. Shorter runs will take more labor and longer runs will take less labor per linear foot.

PVC Elbows and Couplings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|-----------|------|---------------|------------|----------------|
| 45 degree Schedule 40 PVC elbows | | | | | |
| 1/2" | L1@0.05 | Ea | 1.20 | 1.98 | 3.18 |
| 3/4" | L1@0.06 | Ea | 1.27 | 2.38 | 3.65 |
| 1" | L1@0.08 | Ea | 1.99 | 3.17 | 5.16 |
| 1-1/4" | L1@0.10 | Ea | 2.82 | 3.96 | 6.78 |
| 1-1/2" | L1@0.10 | Ea | 3.84 | 3.96 | 7.80 |
| 2" | L1@0.15 | Ea | 5.32 | 5.94 | 11.26 |
| 2-1/2" | L1@0.15 | Ea | 9.10 | 5.94 | 15.04 |
| 3" | L1@0.20 | Ea | 12.80 | 7.93 | 20.73 |
| 4" | L1@0.25 | Ea | 28.20 | 9.91 | 38.11 |
| 5" | L1@0.35 | Ea | 46.10 | 13.90 | 60.00 |
| 6" | L1@0.50 | Ea | 27.10 | 19.80 | 46.90 |

| | | | | | |
|---|---------|----|-------|-------|--------|
| 90 degree Schedule 40 PVC elbows | | | | | |
| 1/2" | L1@0.05 | Ea | 1.22 | 1.98 | 3.20 |
| 3/4" | L1@0.06 | Ea | 1.38 | 2.38 | 3.76 |
| 1" | L1@0.08 | Ea | 2.33 | 3.17 | 5.50 |
| 1-1/4" | L1@0.10 | Ea | 3.09 | 3.96 | 7.05 |
| 1-1/2" | L1@0.10 | Ea | 4.11 | 3.96 | 8.07 |
| 2" | L1@0.15 | Ea | 4.34 | 5.94 | 10.28 |
| 2-1/2" | L1@0.15 | Ea | 9.75 | 5.94 | 15.69 |
| 3" | L1@0.20 | Ea | 17.40 | 7.93 | 25.33 |
| 4" | L1@0.25 | Ea | 29.70 | 9.91 | 39.61 |
| 5" | L1@0.35 | Ea | 52.40 | 13.90 | 66.30 |
| 6" | L1@0.50 | Ea | 88.00 | 19.80 | 107.80 |


| | | | | | |
|---|---------|----|-------|-------|-------|
| 90 degree Schedule 80 PVC elbows | | | | | |
| 1/2" | L1@0.06 | Ea | 1.35 | 2.38 | 3.73 |
| 3/4" | L1@0.08 | Ea | 1.47 | 3.17 | 4.64 |
| 1" | L1@0.10 | Ea | 2.20 | 3.96 | 6.16 |
| 1-1/4" | L1@0.15 | Ea | 2.97 | 5.94 | 8.91 |
| 1-1/2" | L1@0.15 | Ea | 4.46 | 5.94 | 10.40 |
| 2" | L1@0.20 | Ea | 5.04 | 7.93 | 12.97 |
| 2-1/2" | L1@0.20 | Ea | 11.20 | 7.93 | 19.13 |
| 3" | L1@0.25 | Ea | 30.70 | 9.91 | 40.61 |
| 4" | L1@0.30 | Ea | 45.50 | 11.90 | 57.40 |

| | | | | | |
|----------------------------------|---------|----|------|------|------|
| Schedule 40 PVC couplings | | | | | |
| 1/2" | L1@0.02 | Ea | .31 | .79 | 1.10 |
| 3/4" | L1@0.03 | Ea | .37 | 1.19 | 1.56 |
| 1" | L1@0.05 | Ea | .59 | 1.98 | 2.57 |
| 1-1/4" | L1@0.06 | Ea | .78 | 2.38 | 3.16 |
| 1-1/2" | L1@0.08 | Ea | 1.09 | 3.17 | 4.26 |

Use these figures to estimate the cost of PVC elbows and couplings installed on PVC conduit under the conditions described on pages 5 and 6. Costs listed are for each elbow or coupling installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include applying cement (glue), layout, material handling, and normal waste. Add for conduit, couplings, connectors, end bells, spacers, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Material costs assume purchase of full box quantities.


PVC Couplings, Adapters and Expansion Couplings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------------------------------|-----------|------|---------------|------------|----------------|
| Schedule 40 PVC couplings | | | | | |
| 2" | L1@0.10 | Ea | 1.43 | 3.96 | 5.39 |
| 2-1/2" | L1@0.10 | Ea | 2.51 | 3.96 | 6.47 |
| 3" | L1@0.15 | Ea | 4.15 | 5.94 | 10.09 |
| 4" | L1@0.15 | Ea | 6.42 | 5.94 | 12.36 |
| 5" | L1@0.20 | Ea | 16.30 | 7.93 | 24.23 |
| 6" | L1@0.25 | Ea | 20.80 | 9.91 | 30.71 |




Type FA female PVC adapters

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.05 | Ea | .49 | 1.98 | 2.47 |
| 3/4" | L1@0.06 | Ea | .78 | 2.38 | 3.16 |
| 1" | L1@0.08 | Ea | 1.06 | 3.17 | 4.23 |
| 1-1/4" | L1@0.10 | Ea | 1.40 | 3.96 | 5.36 |
| 1-1/2" | L1@0.10 | Ea | 1.50 | 3.96 | 5.46 |
| 2" | L1@0.15 | Ea | 2.05 | 5.94 | 7.99 |
| 2-1/2" | L1@0.15 | Ea | 4.52 | 5.94 | 10.46 |
| 3" | L1@0.20 | Ea | 5.65 | 7.93 | 13.58 |
| 4" | L1@0.25 | Ea | 7.56 | 9.91 | 17.47 |
| 5" | L1@0.30 | Ea | 18.90 | 11.90 | 30.80 |
| 6" | L1@0.40 | Ea | 24.80 | 15.90 | 40.70 |




Type TA terminal PVC adapters

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.05 | Ea | .43 | 1.98 | 2.41 |
| 3/4" | L1@0.06 | Ea | .74 | 2.38 | 3.12 |
| 1" | L1@0.08 | Ea | .92 | 3.17 | 4.09 |
| 1-1/4" | L1@0.10 | Ea | 1.18 | 3.96 | 5.14 |
| 1-1/2" | L1@0.10 | Ea | 1.43 | 3.96 | 5.39 |
| 2" | L1@0.15 | Ea | 2.06 | 5.94 | 8.00 |
| 2-1/2" | L1@0.15 | Ea | 3.50 | 5.94 | 9.44 |
| 3" | L1@0.20 | Ea | 5.12 | 7.93 | 13.05 |
| 4" | L1@0.25 | Ea | 8.80 | 9.91 | 18.71 |
| 5" | L1@0.30 | Ea | 18.90 | 11.90 | 30.80 |
| 6" | L1@0.40 | Ea | 24.80 | 15.90 | 40.70 |



2" range expansion PVC couplings

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.15 | Ea | 17.00 | 5.94 | 22.94 |
| 3/4" | L1@0.20 | Ea | 17.30 | 7.93 | 25.23 |
| 1" | L1@0.25 | Ea | 24.80 | 9.91 | 34.71 |
| 1-1/4" | L1@0.30 | Ea | 36.80 | 11.90 | 48.70 |
| 1-1/2" | L1@0.30 | Ea | 46.60 | 11.90 | 58.50 |
| 2" | L1@0.40 | Ea | 57.40 | 15.90 | 73.30 |



Use these figures to estimate the cost of PVC fittings installed on PVC conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include applying cement (glue), removal of knockouts, layout, material handling, and normal waste. Add for conduit, couplings, connectors, end bells, spacers, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

PVC Expansion Couplings, End Bells, Caps and Plugs

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|-----------|------|---------------|------------|----------------|
| 6" range expansion PVC couplings | | | | | |
| 1/2" | L1@0.15 | Ea | 33.80 | 5.94 | 39.74 |
| 3/4" | L1@0.20 | Ea | 34.50 | 7.93 | 42.43 |
| 1" | L1@0.25 | Ea | 36.50 | 9.91 | 46.41 |
| 1-1/4" | L1@0.30 | Ea | 37.30 | 11.90 | 49.20 |
| 1-1/2" | L1@0.30 | Ea | 39.40 | 11.90 | 51.30 |
| 2" | L1@0.40 | Ea | 42.70 | 15.90 | 58.60 |
| 2-1/2" | L1@0.40 | Ea | 43.70 | 15.90 | 59.60 |
| 3" | L1@0.50 | Ea | 49.80 | 19.80 | 69.60 |
| 4" | L1@0.60 | Ea | 73.40 | 23.80 | 97.20 |
| 5" | L1@0.70 | Ea | 91.70 | 27.70 | 119.40 |
| 6" | L1@0.75 | Ea | 116.00 | 29.70 | 145.70 |

PVC end bells

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1" | L1@0.10 | Ea | 6.01 | 3.96 | 9.97 |
| 1-1/4" | L1@0.15 | Ea | 7.41 | 5.94 | 13.35 |
| 1-1/2" | L1@0.15 | Ea | 7.48 | 5.94 | 13.42 |
| 2" | L1@0.20 | Ea | 11.10 | 7.93 | 19.03 |
| 2-1/2" | L1@0.20 | Ea | 12.20 | 7.93 | 20.13 |
| 3" | L1@0.25 | Ea | 12.90 | 9.91 | 22.81 |
| 4" | L1@0.30 | Ea | 15.40 | 11.90 | 27.30 |
| 5" | L1@0.35 | Ea | 24.30 | 13.90 | 38.20 |
| 6" | L1@0.40 | Ea | 26.50 | 15.90 | 42.40 |

PVC caps and plugs

| | | | | | |
|--------------|---------|----|-------|------|-------|
| 1/2" caps | L1@0.05 | Ea | 1.87 | 1.98 | 3.85 |
| 3/4" caps | L1@0.06 | Ea | 2.30 | 2.38 | 4.68 |
| 1" caps | L1@0.08 | Ea | 2.45 | 3.17 | 5.62 |
| 1-1/4" caps | L1@0.10 | Ea | 3.36 | 3.96 | 7.32 |
| 1-1/2" plugs | L1@0.10 | Ea | 3.98 | 3.96 | 7.94 |
| 2" plugs | L1@0.10 | Ea | 4.30 | 3.96 | 8.26 |
| 2-1/2" plugs | L1@0.10 | Ea | 4.63 | 3.96 | 8.59 |
| 3" plugs | L1@0.15 | Ea | 3.39 | 5.94 | 9.33 |
| 4" plugs | L1@0.15 | Ea | 7.07 | 5.94 | 13.01 |
| 5" plugs | L1@0.20 | Ea | 31.70 | 7.93 | 39.63 |
| 6" plugs | L1@0.20 | Ea | 53.10 | 7.93 | 61.03 |

Use these figures to estimate the cost of PVC fittings installed on PVC conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include applying cement (glue), removal of knockouts, layout, material handling, and normal waste. Add for conduit, locknuts, insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

PVC Reducing Bushings and Conduit Bodies

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


PVC reducing bushings

| | | | | | |
|------------------|---------|----|-------|------|-------|
| 3/4" to 1/2" | L1@0.03 | Ea | 2.27 | 1.19 | 3.46 |
| 1" to 1/2" | L1@0.03 | Ea | 2.50 | 1.19 | 3.69 |
| 1" to 3/4" | L1@0.03 | Ea | 2.60 | 1.19 | 3.79 |
| 1-1/4" to 3/4" | L1@0.05 | Ea | 2.73 | 1.98 | 4.71 |
| 1-1/4" to 1" | L1@0.05 | Ea | 2.77 | 1.98 | 4.75 |
| 1-1/2" to 1" | L1@0.10 | Ea | 2.90 | 3.96 | 6.86 |
| 1-1/2" to 1-1/4" | L1@0.10 | Ea | 3.09 | 3.96 | 7.05 |
| 2" to 1-1/4" | L1@0.15 | Ea | 3.21 | 5.94 | 9.15 |
| 2-1/2" to 2" | L1@0.15 | Ea | 3.60 | 5.94 | 9.54 |
| 3" to 2" | L1@0.20 | Ea | 10.80 | 7.93 | 18.73 |
| 4" to 3" | L1@0.25 | Ea | 12.70 | 9.91 | 22.61 |



Type C PVC conduit bodies

| | | | | | |
|----------|---------|----|-------|------|-------|
| C 1/2" | L1@0.10 | Ea | 10.80 | 3.96 | 14.76 |
| C 3/4" | L1@0.10 | Ea | 13.20 | 3.96 | 17.16 |
| C 1" | L1@0.15 | Ea | 13.80 | 5.94 | 19.74 |
| C 1-1/4" | L1@0.15 | Ea | 22.40 | 5.94 | 28.34 |
| C 1-1/2" | L1@0.20 | Ea | 29.60 | 7.93 | 37.53 |
| C 2" | L1@0.25 | Ea | 41.90 | 9.91 | 51.81 |




Type E PVC conduit bodies

| | | | | | |
|----------|---------|----|-------|------|-------|
| E 1/2" | L1@0.10 | Ea | 8.73 | 3.96 | 12.69 |
| E 3/4" | L1@0.10 | Ea | 12.80 | 3.96 | 16.76 |
| E 1" | L1@0.15 | Ea | 15.10 | 5.94 | 21.04 |
| E 1-1/4" | L1@0.15 | Ea | 18.70 | 5.94 | 24.64 |
| E 1-1/2" | L1@0.20 | Ea | 22.40 | 7.93 | 30.33 |
| E 2" | L1@0.25 | Ea | 39.70 | 9.91 | 49.61 |



Type LB PVC conduit bodies

| | | | | | |
|-----------|---------|----|-------|------|-------|
| LB 1/2" | L1@0.10 | Ea | 8.29 | 3.96 | 12.25 |
| LB 3/4" | L1@0.10 | Ea | 10.80 | 3.96 | 14.76 |
| LB 1" | L1@0.15 | Ea | 11.80 | 5.94 | 17.74 |
| LB 1-1/4" | L1@0.15 | Ea | 17.90 | 5.94 | 23.84 |




Use these figures to estimate the cost of PVC fittings installed on PVC conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include applying cement (glue), removal of knockouts, layout, material handling, and normal waste. Add for conduit, locknuts, insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

PVC Conduit Bodies and Service Entrance Caps

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Type LB PVC conduit bodies

| | | | | | |
|-----------|---------|----|--------|-------|--------|
| LB 1-1/2" | L1@0.20 | Ea | 21.60 | 7.93 | 29.53 |
| LB 2" | L1@0.25 | Ea | 38.20 | 9.91 | 48.11 |
| LB 2-1/2" | L1@0.30 | Ea | 139.00 | 11.90 | 150.90 |
| LB 3" | L1@0.30 | Ea | 143.00 | 11.90 | 154.90 |
| LB 4" | L1@0.40 | Ea | 156.00 | 15.90 | 171.90 |




Type LL PVC conduit bodies

| | | | | | |
|-----------|---------|----|-------|------|-------|
| LL 1/2" | L1@0.10 | Ea | 8.58 | 3.96 | 12.54 |
| LL 3/4" | L1@0.10 | Ea | 12.80 | 3.96 | 16.76 |
| LL 1" | L1@0.15 | Ea | 13.20 | 5.94 | 19.14 |
| LL 1-1/4" | L1@0.15 | Ea | 19.00 | 5.94 | 24.94 |
| LL 1-1/2" | L1@0.20 | Ea | 22.40 | 7.93 | 30.33 |
| LL 2" | L1@0.25 | Ea | 38.90 | 9.91 | 48.81 |




Type LR PVC conduit bodies

| | | | | | |
|-----------|---------|----|-------|------|-------|
| LR 1/2" | L1@0.10 | Ea | 8.58 | 3.96 | 12.54 |
| LR 3/4" | L1@0.10 | Ea | 12.80 | 3.96 | 16.76 |
| LR 1" | L1@0.15 | Ea | 13.20 | 5.94 | 19.14 |
| LR 1-1/4" | L1@0.15 | Ea | 19.00 | 5.94 | 24.94 |
| LR 1-1/2" | L1@0.20 | Ea | 22.40 | 7.93 | 30.33 |
| LR 2" | L1@0.25 | Ea | 38.90 | 9.91 | 48.81 |




Type T PVC conduit bodies

| | | | | | |
|----------|---------|----|-------|-------|-------|
| T 1/2" | L1@0.10 | Ea | 10.80 | 3.96 | 14.76 |
| T 3/4" | L1@0.15 | Ea | 13.20 | 5.94 | 19.14 |
| T 1" | L1@0.15 | Ea | 13.80 | 5.94 | 19.74 |
| T 1-1/4" | L1@0.20 | Ea | 23.10 | 7.93 | 31.03 |
| T 1-1/2" | L1@0.25 | Ea | 29.60 | 9.91 | 39.51 |
| T 2" | L1@0.30 | Ea | 41.90 | 11.90 | 53.80 |



PVC slip-fitter entrance caps


| | | | | | |
|--------|---------|----|--------|-------|--------|
| 3/4" | L1@0.15 | Ea | 9.61 | 5.94 | 15.55 |
| 1" | L1@0.15 | Ea | 12.90 | 5.94 | 18.84 |
| 1-1/4" | L1@0.25 | Ea | 16.00 | 9.91 | 25.91 |
| 1-1/2" | L1@0.30 | Ea | 19.30 | 11.90 | 31.20 |
| 2" | L1@0.50 | Ea | 32.40 | 19.80 | 52.20 |
| 2-1/2" | L1@0.60 | Ea | 167.00 | 23.80 | 190.80 |
| 3" | L1@0.60 | Ea | 175.00 | 23.80 | 198.80 |
| 4" | L1@0.75 | Ea | 489.00 | 29.70 | 518.70 |



Use these figures to estimate the cost of PVC fittings installed on PVC conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include applying cement (glue), removal of knockouts, layout, material handling, and normal waste. Add for conduit, locknuts, insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.


PVC Boxes, Covers and Elbows

| Material | | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|--------------------------|------|-----------|------|---------------|------------|----------------|
| Type FS PVC boxes | | | | | | |
| FS1 | 1/2" | L1@0.20 | Ea | 20.60 | 7.93 | 28.53 |
| FS2 | 3/4" | L1@0.20 | Ea | 20.60 | 7.93 | 28.53 |
| FS3 | 1" | L1@0.25 | Ea | 20.60 | 9.91 | 30.51 |
| FSC1 | 1/2" | L1@0.25 | Ea | 22.50 | 9.91 | 32.41 |
| FSC2 | 3/4" | L1@0.25 | Ea | 22.50 | 9.91 | 32.41 |
| FSC3 | 1" | L1@0.30 | Ea | 22.50 | 11.90 | 34.40 |
| FSS1 | 1/2" | L1@0.25 | Ea | 22.50 | 9.91 | 32.41 |
| FSS2 | 3/4" | L1@0.25 | Ea | 22.50 | 9.91 | 32.41 |
| FSS3 | 1" | L1@0.30 | Ea | 22.50 | 11.90 | 34.40 |
| FCSS1 | 1/2" | L1@0.30 | Ea | 23.10 | 11.90 | 35.00 |
| FCSS2 | 3/4" | L1@0.30 | Ea | 23.10 | 11.90 | 35.00 |
| FCSS3 | 1" | L1@0.35 | Ea | 23.10 | 13.90 | 37.00 |



Type FS, WP PVC box covers

| | | | | | |
|----------------------|---------|----|------|------|-------|
| 1 gang blank | L1@0.10 | Ea | 4.27 | 3.96 | 8.23 |
| 1 gang single outlet | L1@0.10 | Ea | 5.61 | 3.96 | 9.57 |
| 1 gang duplex outlet | L1@0.10 | Ea | 8.95 | 3.96 | 12.91 |
| 1 gang single switch | L1@0.10 | Ea | 8.95 | 3.96 | 12.91 |
| 1 gang GFCI | L1@0.10 | Ea | 8.95 | 3.96 | 12.91 |




PVC junction boxes

| | | | | | |
|----------------|---------|----|--------|-------|--------|
| 4" x 4" x 2" | L1@0.25 | Ea | 28.40 | 9.91 | 38.31 |
| 4" x 4" x 4" | L1@0.25 | Ea | 46.60 | 9.91 | 56.51 |
| 4" x 4" x 6" | L1@0.30 | Ea | 53.80 | 11.90 | 65.70 |
| 5" x 5" x 2" | L1@0.30 | Ea | 55.90 | 11.90 | 67.80 |
| 6" x 6" x 4" | L1@0.35 | Ea | 57.00 | 13.90 | 70.90 |
| 6" x 6" x 6" | L1@0.40 | Ea | 66.60 | 15.90 | 82.50 |
| 8" x 8" x 4" | L1@0.40 | Ea | 109.00 | 15.90 | 124.90 |
| 8" x 8" x 7" | L1@0.50 | Ea | 160.00 | 19.80 | 179.80 |
| 12" x 12" x 4" | L1@0.70 | Ea | 167.00 | 27.70 | 194.70 |
| 12" x 12" x 6" | L1@0.75 | Ea | 170.00 | 29.70 | 199.70 |




30 degree sweeping PVC elbows

| | | | | | |
|---------------|---------|----|--------|-------|--------|
| 2" 24" radius | L1@0.15 | Ea | 37.30 | 5.94 | 43.24 |
| 2" 36" radius | L1@0.20 | Ea | 42.00 | 7.93 | 49.93 |
| 2" 48" radius | L1@0.25 | Ea | 46.70 | 9.91 | 56.61 |
| 3" 24" radius | L1@0.20 | Ea | 74.10 | 7.93 | 82.03 |
| 3" 36" radius | L1@0.25 | Ea | 79.90 | 9.91 | 89.81 |
| 3" 48" radius | L1@0.30 | Ea | 85.80 | 11.90 | 97.70 |
| 4" 24" radius | L1@0.25 | Ea | 108.00 | 9.91 | 117.91 |
| 4" 36" radius | L1@0.30 | Ea | 127.00 | 11.90 | 138.90 |
| 4" 48" radius | L1@0.40 | Ea | 146.00 | 15.90 | 161.90 |




Use these figures to estimate the cost of PVC fittings installed on PVC conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include applying cement (glue), removal of knockouts, layout, material handling, and normal waste. Add for conduit, locknuts, insulated bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities.

PVC Elbows




30 degree sweeping PVC elbows

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---------------|-----------|------|---------------|------------|----------------|
| 5" 36" radius | L1@0.40 | Ea | 190.00 | 15.90 | 205.90 |
| 5" 48" radius | L1@0.50 | Ea | 219.00 | 19.80 | 238.80 |
| 6" 36" radius | L1@0.75 | Ea | 309.00 | 29.70 | 338.70 |
| 6" 48" radius | L1@1.00 | Ea | 332.00 | 39.60 | 371.60 |



45 degree sweeping PVC elbows

| | | | | | |
|-------------------|---------|----|--------|-------|--------|
| 2" 24" radius | L1@0.15 | Ea | 37.30 | 5.94 | 43.24 |
| 2" 30" radius | L1@0.15 | Ea | 39.70 | 5.94 | 45.64 |
| 2" 36" radius | L1@0.20 | Ea | 42.00 | 7.93 | 49.93 |
| 2" 48" radius | L1@0.30 | Ea | 46.70 | 11.90 | 58.60 |
| 2-1/2" 30" radius | L1@0.20 | Ea | 55.80 | 7.93 | 63.73 |
| 2-1/2" 36" radius | L1@0.25 | Ea | 61.10 | 9.91 | 71.01 |
| 2-1/2" 48" radius | L1@0.30 | Ea | 66.20 | 11.90 | 78.10 |
| 3" 24" radius | L1@0.25 | Ea | 74.10 | 9.91 | 84.01 |
| 3" 30" radius | L1@0.30 | Ea | 77.10 | 11.90 | 89.00 |
| 3" 36" radius | L1@0.30 | Ea | 79.90 | 11.90 | 91.80 |
| 3" 48" radius | L1@0.40 | Ea | 85.80 | 15.90 | 101.70 |
| 4" 24" radius | L1@0.30 | Ea | 108.00 | 11.90 | 119.90 |
| 4" 30" radius | L1@0.30 | Ea | 117.00 | 11.90 | 128.90 |
| 4" 36" radius | L1@0.35 | Ea | 127.00 | 13.90 | 140.90 |
| 4" 48" radius | L1@0.40 | Ea | 146.00 | 15.90 | 161.90 |
| 5" 30" radius | L1@0.35 | Ea | 173.00 | 13.90 | 186.90 |
| 5" 36" radius | L1@0.40 | Ea | 190.00 | 15.90 | 205.90 |
| 5" 48" radius | L1@0.50 | Ea | 219.00 | 19.80 | 238.80 |
| 6" 36" radius | L1@0.75 | Ea | 309.00 | 29.70 | 338.70 |
| 6" 48" radius | L1@1.00 | Ea | 332.00 | 39.60 | 371.60 |



90 degree sweeping PVC elbows

| | | | | | |
|-------------------|---------|----|-------|-------|-------|
| 2" 24" radius | L1@0.20 | Ea | 39.70 | 7.93 | 47.63 |
| 2" 30" radius | L1@0.25 | Ea | 42.00 | 9.91 | 51.91 |
| 2" 36" radius | L1@0.30 | Ea | 46.70 | 11.90 | 58.60 |
| 2" 48" radius | L1@0.35 | Ea | 49.10 | 13.90 | 63.00 |
| 2-1/2" 30" radius | L1@0.30 | Ea | 43.00 | 11.90 | 54.90 |
| 2-1/2" 36" radius | L1@0.35 | Ea | 46.10 | 13.90 | 60.00 |
| 2-1/2" 48" radius | L1@0.40 | Ea | 49.80 | 15.90 | 65.70 |


Use these figures and the table at the top of the next page to estimate the cost of PVC sweeps installed on PVC conduit under the conditions described on pages 5 and 6. Costs listed are for each sweep installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include applying cement (glue), layout, material handling, and normal waste. Add for couplings, connectors, end bells, spacers, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full packages.

PVC Elbows, Power & Communication (P&C) Duct

| Material | | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|--|-----------|------|---------------|------------|----------------|
|----------|--|-----------|------|---------------|------------|----------------|

90 degree sweeping PVC elbows

| | | | | | | |
|----|------------|---------|----|--------|-------|--------|
| 3" | 24" radius | L2@0.30 | Ea | 74.10 | 11.90 | 86.00 |
| 3" | 30" radius | L2@0.35 | Ea | 77.10 | 13.90 | 91.00 |
| 3" | 36" radius | L2@0.40 | Ea | 79.90 | 15.90 | 95.80 |
| 3" | 48" radius | L2@0.50 | Ea | 82.10 | 19.80 | 101.90 |
| 4" | 24" radius | L2@0.35 | Ea | 108.00 | 13.90 | 121.90 |
| 4" | 30" radius | L2@0.40 | Ea | 117.00 | 15.90 | 132.90 |
| 4" | 36" radius | L2@0.45 | Ea | 127.00 | 17.80 | 144.80 |
| 4" | 48" radius | L2@0.55 | Ea | 146.00 | 21.80 | 167.80 |
| 5" | 30" radius | L2@0.45 | Ea | 173.00 | 17.80 | 190.80 |
| 5" | 36" radius | L2@0.50 | Ea | 190.00 | 19.80 | 209.80 |
| 5" | 48" radius | L2@0.60 | Ea | 219.00 | 23.80 | 242.80 |
| 6" | 36" radius | L2@0.60 | Ea | 309.00 | 23.80 | 332.80 |
| 6" | 48" radius | L2@0.75 | Ea | 332.00 | 29.70 | 361.70 |



Type EB power and communication duct

| | | | | | |
|----|---------|-----|--------|--------|--------|
| 2" | L2@3.30 | CLF | 155.00 | 131.00 | 286.00 |
| 3" | L2@3.50 | CLF | 225.00 | 139.00 | 364.00 |
| 4" | L2@4.00 | CLF | 368.00 | 159.00 | 527.00 |
| 5" | L2@4.50 | CLF | 558.00 | 178.00 | 736.00 |
| 6" | L2@5.00 | CLF | 799.00 | 198.00 | 997.00 |




Type DB power and communication duct

| | | | | | |
|----|---------|-----|--------|--------|--------|
| 2" | L2@3.30 | CLF | 173.00 | 131.00 | 304.00 |
| 4" | L2@4.00 | CLF | 512.00 | 159.00 | 671.00 |
| 5" | L2@4.50 | CLF | 785.00 | 178.00 | 963.00 |
| 6" | L2@5.00 | CLF | 111.00 | 198.00 | 309.00 |




Type EB or DB power and communication duct couplings

| | | | | | |
|----|---------|----|-------|------|-------|
| 2" | L1@0.05 | Ea | 2.31 | 1.98 | 4.29 |
| 3" | L1@0.10 | Ea | 5.32 | 3.96 | 9.28 |
| 4" | L1@0.10 | Ea | 8.29 | 3.96 | 12.25 |
| 5" | L1@0.15 | Ea | 15.20 | 5.94 | 21.14 |
| 6" | L1@0.15 | Ea | 46.60 | 5.94 | 52.54 |



45 degree Type EB or DB power and communication duct elbows

| | | | | | | |
|----|------------|---------|----|-------|-------|-------|
| 2" | 24" radius | L1@0.15 | Ea | 15.80 | 5.94 | 21.74 |
| 3" | 36" radius | L1@0.30 | Ea | 21.90 | 11.90 | 33.80 |
| 3" | 48" radius | L1@0.40 | Ea | 35.90 | 15.90 | 51.80 |
| 4" | 36" radius | L1@0.40 | Ea | 28.80 | 15.90 | 44.70 |
| 4" | 48" radius | L1@0.75 | Ea | 40.40 | 29.70 | 70.10 |
| 5" | 48" radius | L1@0.50 | Ea | 52.00 | 19.80 | 71.80 |



Use these figures to estimate the cost of PVC elbows (top table) and power and communication duct couplings and elbows (bottom tables). The footnote on the previous page applies to PVC sweep elbows. P&C duct is installed underground under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet installed. The crew is two electricians working at a labor cost of \$39.63 per manhour. These costs include one coupling, applying cement (glue), multiple runs in the same trench, layout, material handling, and normal waste. Add for trenching, encasement, spacers and chairs, single duct runs, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Encased burial requires spacers or chairs every 5 feet. Costs for spacers, chairs, encasement and trenching are listed elsewhere in this manual.

Power & Communication Duct Couplings, Elbows & Adapters

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

90 degree Type EB or DB power and communication duct elbows

| | | | | | | |
|----|------------|---------|----|--------|-------|--------|
| 2" | 18" radius | L1@0.20 | Ea | 12.70 | 7.93 | 20.63 |
| 2" | 24" radius | L1@0.30 | Ea | 16.20 | 11.90 | 28.10 |
| 2" | 36" radius | L1@0.35 | Ea | 21.90 | 13.90 | 35.80 |
| 3" | 24" radius | L1@0.30 | Ea | 21.90 | 11.90 | 33.80 |
| 3" | 36" radius | L1@0.40 | Ea | 23.10 | 15.90 | 39.00 |
| 3" | 48" radius | L1@0.50 | Ea | 24.40 | 19.80 | 44.20 |
| 4" | 24" radius | L1@0.35 | Ea | 18.50 | 13.90 | 32.40 |
| 4" | 36" radius | L1@0.45 | Ea | 26.20 | 17.80 | 44.00 |
| 4" | 48" radius | L1@0.55 | Ea | 72.80 | 21.80 | 94.60 |
| 5" | 36" radius | L1@0.50 | Ea | 62.00 | 19.80 | 81.80 |
| 5" | 48" radius | L1@0.60 | Ea | 81.40 | 23.80 | 105.20 |
| 6" | 48" radius | L1@0.75 | Ea | 107.00 | 29.70 | 136.70 |

5 degree power and communication bend couplings

| | | | | | |
|----|---------|----|-------|------|-------|
| 2" | L1@0.05 | Ea | 19.00 | 1.98 | 20.98 |
| 3" | L1@0.10 | Ea | 24.00 | 3.96 | 27.96 |
| 4" | L1@0.10 | Ea | 28.40 | 3.96 | 32.36 |
| 5" | L1@0.15 | Ea | 30.90 | 5.94 | 36.84 |
| 6" | L1@0.15 | Ea | 31.90 | 5.94 | 37.84 |

Power and communication duct plugs

| | | | | | |
|----|---------|----|------|------|-------|
| 2" | L1@0.05 | Ea | 3.35 | 1.98 | 5.33 |
| 3" | L1@0.10 | Ea | 4.93 | 3.96 | 8.89 |
| 4" | L1@0.10 | Ea | 5.57 | 3.96 | 9.53 |
| 5" | L1@0.15 | Ea | 7.56 | 5.94 | 13.50 |
| 6" | L1@0.15 | Ea | 9.46 | 5.94 | 15.40 |

Type FA female power and communication duct adapters

| | | | | | |
|----|---------|----|-------|-------|-------|
| 2" | L1@0.20 | Ea | 2.05 | 7.93 | 9.98 |
| 3" | L1@0.25 | Ea | 5.65 | 9.91 | 15.56 |
| 4" | L1@0.30 | Ea | 7.56 | 11.90 | 19.46 |
| 5" | L1@0.40 | Ea | 18.90 | 15.90 | 34.80 |
| 6" | L1@0.50 | Ea | 24.80 | 19.80 | 44.60 |

Type TA terminal power and communication adapters

| | | | | | |
|----|---------|----|-------|-------|-------|
| 2" | L1@0.20 | Ea | 2.06 | 7.93 | 9.99 |
| 3" | L1@0.25 | Ea | 5.12 | 9.91 | 15.03 |
| 4" | L1@0.30 | Ea | 8.80 | 11.90 | 20.70 |
| 5" | L1@0.40 | Ea | 17.30 | 15.90 | 33.20 |
| 6" | L1@0.50 | Ea | 20.80 | 19.80 | 40.60 |


Use these figures to estimate the cost of PVC fittings installed on PVC power and communication duct under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include cutting and fitting, applying cement (glue), layout, material handling, and normal waste. Add for extra couplings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs are based on purchase of full packages. All of these fittings can be used either on type EB or type DB duct.

Power & Communication Duct End Bells and Plastic Spacers

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Power and communication duct end bells

| | | | | | |
|----|---------|----|-------|-------|-------|
| 2" | L1@0.15 | Ea | 10.70 | 5.94 | 16.64 |
| 3" | L1@0.20 | Ea | 12.80 | 7.93 | 20.73 |
| 4" | L1@0.25 | Ea | 15.40 | 9.91 | 25.31 |
| 5" | L1@0.30 | Ea | 24.30 | 11.90 | 36.20 |
| 6" | L1@0.50 | Ea | 26.50 | 19.80 | 46.30 |




Base type plastic duct spacers

| | | | | | | |
|----|-------------------|---------|----|------|------|------|
| 2" | 1-1/2" separation | L1@0.05 | Ea | 2.05 | 1.98 | 4.03 |
| 3" | 1-1/2" separation | L1@0.05 | Ea | 2.22 | 1.98 | 4.20 |
| 4" | 1-1/2" separation | L1@0.05 | Ea | 2.45 | 1.98 | 4.43 |
| 5" | 1-1/2" separation | L1@0.05 | Ea | 2.65 | 1.98 | 4.63 |
| 6" | 1-1/2" separation | L1@0.05 | Ea | 4.27 | 1.98 | 6.25 |
| 2" | 2" separation | L1@0.05 | Ea | 2.22 | 1.98 | 4.20 |
| 3" | 2" separation | L1@0.05 | Ea | 2.45 | 1.98 | 4.43 |
| 4" | 2" separation | L1@0.05 | Ea | 2.62 | 1.98 | 4.60 |
| 5" | 2" separation | L1@0.05 | Ea | 2.73 | 1.98 | 4.71 |
| 6" | 2" separation | L1@0.05 | Ea | 4.55 | 1.98 | 6.53 |
| 2" | 3" separation | L1@0.05 | Ea | 2.40 | 1.98 | 4.38 |
| 3" | 3" separation | L1@0.05 | Ea | 2.66 | 1.98 | 4.64 |
| 4" | 3" separation | L1@0.05 | Ea | 2.81 | 1.98 | 4.79 |
| 5" | 3" separation | L1@0.05 | Ea | 3.45 | 1.98 | 5.43 |
| 6" | 3" separation | L1@0.05 | Ea | 4.83 | 1.98 | 6.81 |



Intermediate type plastic duct spacers

| | | | | | | |
|----|-------------------|---------|----|------|------|------|
| 2" | 1-1/2" separation | L1@0.05 | Ea | 2.05 | 1.98 | 4.03 |
| 3" | 1-1/2" separation | L1@0.05 | Ea | 2.22 | 1.98 | 4.20 |
| 4" | 1-1/2" separation | L1@0.05 | Ea | 2.45 | 1.98 | 4.43 |
| 5" | 1-1/2" separation | L1@0.05 | Ea | 2.65 | 1.98 | 4.63 |
| 6" | 1-1/2" separation | L1@0.05 | Ea | 4.27 | 1.98 | 6.25 |
| 2" | 2" separation | L1@0.05 | Ea | 2.22 | 1.98 | 4.20 |
| 3" | 2" separation | L1@0.05 | Ea | 2.45 | 1.98 | 4.43 |
| 4" | 2" separation | L1@0.05 | Ea | 2.62 | 1.98 | 4.60 |
| 5" | 2" separation | L1@0.05 | Ea | 2.73 | 1.98 | 4.71 |
| 6" | 2" separation | L1@0.05 | Ea | 4.55 | 1.98 | 6.53 |
| 2" | 3" separation | L1@0.05 | Ea | 2.40 | 1.98 | 4.38 |
| 3" | 3" separation | L1@0.05 | Ea | 2.66 | 1.98 | 4.64 |
| 4" | 3" separation | L1@0.05 | Ea | 2.81 | 1.98 | 4.79 |
| 5" | 3" separation | L1@0.05 | Ea | 3.45 | 1.98 | 5.43 |
| 6" | 3" separation | L1@0.05 | Ea | 4.83 | 1.98 | 6.81 |



Use these figures to estimate the cost of P&C end bell or plastic spacer installed with duct systems under the conditions described on pages 5 and 6. Costs listed are for each end bell or spacer installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include ganging spacers, tying duct to the spacer, layout, material handling, and normal waste. Add for duct, other fittings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs are based on purchase of full packages. Tie wire should never be tied completely around the duct, it should be tied in a figure 8 pattern through open spaces in the side of the spacer and over the top part of the duct. Running wire completely around the duct will cause the wire to pick up an induction field from the current passing through the conductor, generating heat which will weaken the insulation.

ENT Conduit and Fittings



| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|-----------|------|---------------|------------|----------------|
| ENT conduit, non-metallic tubing | | | | | |
| 1/2" | L1@2.15 | CLF | 70.00 | 85.20 | 155.20 |
| 3/4" | L1@2.25 | CLF | 96.10 | 89.20 | 185.30 |
| 1" | L1@2.50 | CLF | 155.00 | 99.10 | 254.10 |

ENT connectors

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.03 | Ea | 1.92 | 1.19 | 3.11 |
| 3/4" | L1@0.04 | Ea | 2.96 | 1.59 | 4.55 |
| 1" | L1@0.05 | Ea | 4.46 | 1.98 | 6.44 |

ENT couplings

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.03 | Ea | 1.36 | 1.19 | 2.55 |
| 3/4" | L1@0.04 | Ea | 1.78 | 1.59 | 3.37 |
| 1" | L1@0.05 | Ea | 3.13 | 1.98 | 5.11 |



ENT male adapters

| | | | | | |
|------|---------|----|------|------|------|
| 1/2" | L1@0.03 | Ea | 1.41 | 1.19 | 2.60 |
| 3/4" | L1@0.04 | Ea | 1.93 | 1.59 | 3.52 |
| 1" | L1@0.05 | Ea | 3.22 | 1.98 | 5.20 |

Use these figures to estimate the cost of ENT conduit and fittings installed under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet installed and for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include cutting and fitting, applying cement (glue), layout, material handling, and normal waste. Add for extra couplings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs are based on purchase of full packages.

Galvanized Rigid Steel (GRS) Conduit and Elbows

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Standard wall galvanized rigid steel conduit

| | | | | | |
|--------|---------|-----|-----------|----------|-----------|
| 1/2" | L1@4.00 | CLF | 442.00 | 159.00 | 601.00 |
| 3/4" | L1@4.50 | CLF | 482.00 | 178.00 | 660.00 |
| 1" | L1@5.00 | CLF | 695.00 | 198.00 | 893.00 |
| 1-1/4" | L1@7.00 | CLF | 970.00 | 277.00 | 1,247.00 |
| 1-1/2" | L1@8.00 | CLF | 1,130.00 | 317.00 | 1,447.00 |
| 2" | L1@10.0 | CLF | 1,440.00 | 396.00 | 1,836.00 |
| 2-1/2" | L1@12.0 | CLF | 2,560.00 | 476.00 | 3,036.00 |
| 3" | L1@14.0 | CLF | 3,110.00 | 555.00 | 3,665.00 |
| 3-1/2" | L1@16.0 | CLF | 3,730.00 | 634.00 | 4,364.00 |
| 4" | L1@18.0 | CLF | 4,340.00 | 713.00 | 5,053.00 |
| 5" | L1@25.0 | CLF | 7,750.00 | 991.00 | 8,741.00 |
| 6" | L1@30.0 | CLF | 11,300.00 | 1,190.00 | 12,490.00 |




45 degree galvanized rigid steel elbows

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 11.10 | 3.96 | 15.06 |
| 3/4" | L1@0.10 | Ea | 11.50 | 3.96 | 15.46 |
| 1" | L1@0.12 | Ea | 17.80 | 4.76 | 22.56 |
| 1-1/4" | L1@0.15 | Ea | 24.40 | 5.94 | 30.34 |
| 1-1/2" | L1@0.15 | Ea | 30.10 | 5.94 | 36.04 |
| 2" | L1@0.20 | Ea | 43.60 | 7.93 | 51.53 |
| 2-1/2" | L1@0.25 | Ea | 81.40 | 9.91 | 91.31 |
| 3" | L1@0.25 | Ea | 112.00 | 9.91 | 121.91 |
| 3-1/2" | L1@0.30 | Ea | 179.00 | 11.90 | 190.90 |
| 4" | L1@0.30 | Ea | 202.00 | 11.90 | 213.90 |
| 5" | L1@0.50 | Ea | 559.00 | 19.80 | 578.80 |
| 6" | L1@1.00 | Ea | 838.00 | 39.60 | 877.60 |



90 degree galvanized rigid steel elbows

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 7.26 | 3.96 | 11.22 |
| 3/4" | L1@0.10 | Ea | 7.99 | 3.96 | 11.95 |
| 1" | L1@0.12 | Ea | 12.20 | 4.76 | 16.96 |
| 1-1/4" | L1@0.15 | Ea | 15.00 | 5.94 | 20.94 |
| 1-1/2" | L1@0.15 | Ea | 17.50 | 5.94 | 23.44 |
| 2" | L1@0.20 | Ea | 25.70 | 7.93 | 33.63 |
| 2-1/2" | L1@0.25 | Ea | 62.60 | 9.91 | 72.51 |
| 3" | L1@0.25 | Ea | 92.90 | 9.91 | 102.81 |
| 3-1/2" | L1@0.30 | Ea | 125.00 | 11.90 | 136.90 |
| 4" | L1@0.30 | Ea | 244.00 | 11.90 | 255.90 |
| 5" | L1@0.50 | Ea | 310.00 | 19.80 | 329.80 |
| 6" | L1@1.00 | Ea | 425.00 | 39.60 | 464.60 |



Use these figures to estimate the cost of GRS conduit and elbows installed in buildings under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet of conduit or for each elbow installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include one coupling on each length of conduit, threading, cutting, straps, layout, material handling, and normal waste. Add for other fittings, boxes, wires, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Couplings are not included with elbows. The elbows listed are factory made and have a standard radius. Conduit runs are assumed to be 50' long. Installation costs per linear foot will be less on longer runs and more on shorter runs.

GRS Hand Benders are on page 52.

Galvanized Rigid Steel Large Radius Elbows

| Material | | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|------------|-----------|------|---------------|------------|----------------|
| 90 degree galvanized rigid steel large radius elbows | | | | | | |
| 1" | 12" radius | L1@0.10 | Ea | 23.00 | 3.96 | 26.96 |
| 1-1/4" | 12" radius | L1@0.15 | Ea | 26.90 | 5.94 | 32.84 |
| 1-1/2" | 12" radius | L1@0.15 | Ea | 31.90 | 5.94 | 37.84 |
| 2" | 12" radius | L1@0.20 | Ea | 41.30 | 7.93 | 49.23 |
| 2-1/2" | 12" radius | L2@0.20 | Ea | 56.60 | 7.93 | 64.53 |
| 1" | 15" radius | L1@0.10 | Ea | 23.80 | 3.96 | 27.76 |
| 1-1/4" | 15" radius | L1@0.15 | Ea | 27.20 | 5.94 | 33.14 |
| 1-1/2" | 15" radius | L1@0.15 | Ea | 33.40 | 5.94 | 39.34 |
| 2" | 15" radius | L1@0.20 | Ea | 38.50 | 7.93 | 46.43 |
| 2-1/2" | 15" radius | L2@0.20 | Ea | 52.00 | 7.93 | 59.93 |
| 1" | 18" radius | L1@0.10 | Ea | 25.10 | 3.96 | 29.06 |
| 1-1/4" | 18" radius | L1@0.15 | Ea | 27.70 | 5.94 | 33.64 |
| 1-1/2" | 18" radius | L1@0.15 | Ea | 32.90 | 5.94 | 38.84 |
| 2" | 18" radius | L1@0.20 | Ea | 40.10 | 7.93 | 48.03 |
| 2-1/2" | 18" radius | L2@0.20 | Ea | 53.50 | 7.93 | 61.43 |
| 3" | 18" radius | L2@0.25 | Ea | 68.00 | 9.91 | 77.91 |
| 3-1/2" | 18" radius | L2@0.25 | Ea | 77.50 | 9.91 | 87.41 |
| 4" | 18" radius | L2@0.30 | Ea | 85.20 | 11.90 | 97.10 |
| 1" | 24" radius | L1@0.10 | Ea | 27.20 | 3.96 | 31.16 |
| 1-1/4" | 24" radius | L1@0.15 | Ea | 28.70 | 5.94 | 34.64 |
| 1-1/2" | 24" radius | L1@0.15 | Ea | 34.60 | 5.94 | 40.54 |
| 2" | 24" radius | L1@0.20 | Ea | 42.50 | 7.93 | 50.43 |
| 2-1/2" | 24" radius | L2@0.20 | Ea | 56.60 | 7.93 | 64.53 |
| 3" | 24" radius | L2@0.25 | Ea | 82.90 | 9.91 | 92.81 |
| 3-1/2" | 24" radius | L2@0.25 | Ea | 111.00 | 9.91 | 120.91 |
| 4" | 24" radius | L2@0.30 | Ea | 127.00 | 11.90 | 138.90 |
| 1" | 30" radius | L1@0.15 | Ea | 67.00 | 5.94 | 72.94 |
| 1-1/4" | 30" radius | L1@0.20 | Ea | 69.70 | 7.93 | 77.63 |
| 1-1/2" | 30" radius | L1@0.20 | Ea | 89.00 | 7.93 | 96.93 |
| 2" | 30" radius | L1@0.25 | Ea | 108.00 | 9.91 | 117.91 |
| 2-1/2" | 30" radius | L2@0.25 | Ea | 84.50 | 9.91 | 94.41 |
| 3" | 30" radius | L2@0.30 | Ea | 108.00 | 11.90 | 119.90 |
| 3-1/2" | 30" radius | L2@0.30 | Ea | 128.00 | 11.90 | 139.90 |
| 4" | 30" radius | L2@0.35 | Ea | 160.00 | 13.90 | 173.90 |
| 5" | 30" radius | L2@0.50 | Ea | 223.00 | 19.80 | 242.80 |
| 1" | 36" radius | L1@0.20 | Ea | 52.60 | 7.93 | 60.53 |
| 1-1/4" | 36" radius | L1@0.25 | Ea | 80.60 | 9.91 | 90.51 |
| 1-1/2" | 36" radius | L1@0.25 | Ea | 97.00 | 9.91 | 106.91 |
| 2" | 36" radius | L1@0.30 | Ea | 127.00 | 11.90 | 138.90 |
| 2-1/2" | 36" radius | L2@0.30 | Ea | 259.00 | 11.90 | 270.90 |
| 3" | 36" radius | L2@0.35 | Ea | 300.00 | 13.90 | 313.90 |


Use these figures to estimate the cost of large radius GRS elbows installed on GRS conduit under the conditions described on pages 5 and 6. Costs listed are for each elbow installed. The crew is one electrician for size to 2" and two electricians for sizes over 2". The labor cost is \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for other GRS fittings, conduit, field bending, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: All elbows are assumed to be factory made.

Galvanized Rigid Steel Elbows and Couplings

| Material | | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|--|-----------|------|---------------|------------|----------------|
|----------|--|-----------|------|---------------|------------|----------------|


90 degree galvanized rigid steel large radius elbows

| | | | | | | |
|--------|------------|---------|----|--------|-------|--------|
| 3-1/2" | 36" radius | L2@0.35 | Ea | 137.00 | 13.90 | 150.90 |
| 4" | 36" radius | L2@0.40 | Ea | 150.00 | 15.90 | 165.90 |
| 5" | 36" radius | L2@0.60 | Ea | 278.00 | 23.80 | 301.80 |
| 6" | 36" radius | L2@1.00 | Ea | 311.00 | 39.60 | 350.60 |
| 1" | 42" radius | L1@0.25 | Ea | 71.80 | 9.91 | 81.71 |
| 1-1/4" | 42" radius | L1@0.30 | Ea | 86.80 | 11.90 | 98.70 |
| 1-1/2" | 42" radius | L1@0.30 | Ea | 97.00 | 11.90 | 108.90 |
| 2" | 42" radius | L1@0.35 | Ea | 128.00 | 13.90 | 141.90 |
| 2-1/2" | 42" radius | L2@0.35 | Ea | 176.00 | 13.90 | 189.90 |
| 3" | 42" radius | L2@0.40 | Ea | 228.00 | 15.90 | 243.90 |
| 3-1/2" | 42" radius | L2@0.40 | Ea | 306.00 | 15.90 | 321.90 |
| 4" | 42" radius | L2@0.50 | Ea | 209.00 | 19.80 | 228.80 |
| 5" | 42" radius | L2@0.75 | Ea | 406.00 | 29.70 | 435.70 |
| 6" | 42" radius | L2@1.25 | Ea | 425.00 | 49.50 | 474.50 |
| 1" | 48" radius | L1@0.30 | Ea | 83.80 | 11.90 | 95.70 |
| 1-1/4" | 48" radius | L1@0.35 | Ea | 97.00 | 13.90 | 110.90 |
| 1-1/2" | 48" radius | L1@0.35 | Ea | 106.00 | 13.90 | 119.90 |
| 2" | 48" radius | L1@0.40 | Ea | 161.00 | 15.90 | 176.90 |
| 2-1/2" | 48" radius | L2@0.40 | Ea | 203.00 | 15.90 | 218.90 |
| 3" | 48" radius | L2@0.50 | Ea | 314.00 | 19.80 | 333.80 |
| 3-1/2" | 48" radius | L2@0.50 | Ea | 392.00 | 19.80 | 411.80 |
| 4" | 48" radius | L2@0.70 | Ea | 491.00 | 27.70 | 518.70 |
| 5" | 48" radius | L2@1.00 | Ea | 660.00 | 39.60 | 699.60 |
| 6" | 48" radius | L2@1.50 | Ea | 683.00 | 59.40 | 742.40 |



Galvanized rigid steel couplings

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | .70 | 1.98 | 2.68 |
| 3/4" | L1@0.06 | Ea | .85 | 2.38 | 3.23 |
| 1" | L1@0.08 | Ea | 1.25 | 3.17 | 4.42 |
| 1-1/4" | L1@0.10 | Ea | 2.14 | 3.96 | 6.10 |
| 1-1/2" | L1@0.10 | Ea | 2.69 | 3.96 | 6.65 |
| 2" | L1@0.15 | Ea | 3.55 | 5.94 | 9.49 |
| 2-1/2" | L2@0.15 | Ea | 8.29 | 5.94 | 14.23 |
| 3" | L2@0.20 | Ea | 10.80 | 7.93 | 18.73 |
| 3-1/2" | L2@0.20 | Ea | 14.50 | 7.93 | 22.43 |
| 4" | L2@0.25 | Ea | 38.60 | 9.91 | 48.51 |
| 5" | L2@0.30 | Ea | 81.40 | 11.90 | 93.30 |
| 6" | L2@0.50 | Ea | 124.00 | 19.80 | 143.80 |




Use these figures to estimate the cost of large radius GRS elbows and couplings installed on GRS conduit under the conditions described on pages 5 and 6. Costs listed are for each elbow or coupling installed. The crew is one electrician for sizes to 2" and two electricians for sizes over 2". The labor cost is \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for other GRS fittings, conduit, field bending, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: All elbows are assumed to be factory made.

GRS Terminations, Intermediate Metal Conduit (IMC) and Elbows

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Galvanized rigid steel conduit terminations

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | .84 | 1.98 | 2.82 |
| 3/4" | L1@0.06 | Ea | 1.15 | 2.38 | 3.53 |
| 1" | L1@0.08 | Ea | 1.80 | 3.17 | 4.97 |
| 1-1/4" | L1@0.10 | Ea | 2.24 | 3.96 | 6.20 |
| 1-1/2" | L1@0.10 | Ea | 3.40 | 3.96 | 7.36 |
| 2" | L1@0.15 | Ea | 4.68 | 5.94 | 10.62 |
| 2-1/2" | L2@0.15 | Ea | 11.30 | 5.94 | 17.24 |
| 3" | L2@0.20 | Ea | 14.50 | 7.93 | 22.43 |
| 3-1/2" | L2@0.20 | Ea | 28.80 | 7.93 | 36.73 |
| 4" | L2@0.25 | Ea | 33.20 | 9.91 | 43.11 |
| 5" | L2@0.30 | Ea | 69.80 | 11.90 | 81.70 |
| 6" | L2@0.50 | Ea | 133.00 | 19.80 | 152.80 |



Intermediate metal conduit

| | | | | | |
|--------|---------|-----|--------|--------|----------|
| 1/2" | L1@3.75 | CLF | 56.00 | 149.00 | 205.00 |
| 3/4" | L1@4.00 | CLF | 58.90 | 159.00 | 217.90 |
| 1" | L1@4.50 | CLF | 94.40 | 178.00 | 272.40 |
| 1-1/4" | L1@6.50 | CLF | 114.00 | 258.00 | 372.00 |
| 1-1/2" | L1@7.25 | CLF | 146.00 | 287.00 | 433.00 |
| 2" | L1@9.00 | CLF | 194.00 | 357.00 | 551.00 |
| 2-1/2" | L2@11.0 | CLF | 398.00 | 436.00 | 834.00 |
| 3" | L2@13.0 | CLF | 478.00 | 515.00 | 993.00 |
| 3-1/2" | L2@15.0 | CLF | 552.00 | 594.00 | 1,146.00 |
| 4" | L2@17.0 | CLF | 652.00 | 674.00 | 1,326.00 |



45 degree intermediate metal conduit elbows

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 7.91 | 3.96 | 11.87 |
| 3/4" | L1@0.10 | Ea | 9.70 | 3.96 | 13.66 |
| 1" | L1@0.10 | Ea | 15.00 | 3.96 | 18.96 |
| 1-1/4" | L1@0.15 | Ea | 22.80 | 5.94 | 28.74 |
| 1-1/2" | L1@0.15 | Ea | 25.00 | 5.94 | 30.94 |
| 2" | L1@0.20 | Ea | 36.20 | 7.93 | 44.13 |
| 2-1/2" | L2@0.20 | Ea | 63.40 | 7.93 | 71.33 |
| 3" | L2@0.25 | Ea | 97.00 | 9.91 | 106.91 |
| 3-1/2" | L2@0.25 | Ea | 146.00 | 9.91 | 155.91 |
| 4" | L2@0.30 | Ea | 172.00 | 11.90 | 183.90 |



Galvanized rigid steel hand benders

| | | | | | |
|--------|----|----|-------|----|-------|
| 1/2" | -- | Ea | 31.30 | -- | 31.30 |
| 3/4" | -- | Ea | 49.30 | -- | 49.30 |
| 1" | -- | Ea | 67.20 | -- | 67.20 |
| 1-1/4" | -- | Ea | 85.20 | -- | 85.20 |


Use these figures to estimate the cost of GRS terminations, intermediate metal conduit and IMC elbows installed under the conditions described on pages 5 and 6. Costs listed are for each fitting or 100 linear feet installed. The crew is one electrician for GRS terminations and IMC to 2" and two electricians for GRS or IMC over 2". The labor cost is \$39.63 per manhour. These costs include removing the knockout, field bending of the IMC and one coupling for each 10' length, layout, material handling, and normal waste. Add for straps and other fittings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full packages. Conduit runs are assumed to be 50' long. Installation costs per linear foot will be less on longer runs and more on shorter runs.

IMC Elbows, Couplings and Running Thread

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


90 degree intermediate metal conduit elbows

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 8.99 | 3.96 | 12.95 |
| 3/4" | L1@0.10 | Ea | 10.80 | 3.96 | 14.76 |
| 1" | L1@0.10 | Ea | 14.50 | 3.96 | 18.46 |
| 1-1/4" | L1@0.15 | Ea | 22.80 | 5.94 | 28.74 |
| 1-1/2" | L1@0.15 | Ea | 24.10 | 5.94 | 30.04 |
| 2" | L1@0.20 | Ea | 36.70 | 7.93 | 44.63 |
| 2-1/2" | L1@0.20 | Ea | 62.60 | 7.93 | 70.53 |
| 3" | L1@0.25 | Ea | 98.90 | 9.91 | 108.81 |
| 3-1/2" | L1@0.25 | Ea | 149.00 | 9.91 | 158.91 |
| 4" | L1@0.30 | Ea | 176.00 | 11.90 | 187.90 |




Rigid steel couplings (used on IMC)

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | .70 | 1.98 | 2.68 |
| 3/4" | L1@0.06 | Ea | .85 | 2.38 | 3.23 |
| 1" | L1@0.08 | Ea | 1.25 | 3.17 | 4.42 |
| 1-1/4" | L1@0.10 | Ea | 2.14 | 3.96 | 6.10 |
| 1-1/2" | L1@0.10 | Ea | 2.69 | 3.96 | 6.65 |
| 2" | L1@0.15 | Ea | 3.55 | 5.94 | 9.49 |
| 2-1/2" | L1@0.15 | Ea | 8.29 | 5.94 | 14.23 |
| 3" | L1@0.20 | Ea | 10.80 | 7.93 | 18.73 |
| 3-1/2" | L1@0.20 | Ea | 14.50 | 7.93 | 22.43 |
| 4" | L1@0.25 | Ea | 38.60 | 9.91 | 48.51 |
| 5" | L1@0.30 | Ea | 82.90 | 11.90 | 94.80 |
| 6" | L1@0.50 | Ea | 124.00 | 19.80 | 143.80 |



Steel running thread in 36" lengths

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.15 | Ea | 15.20 | 5.94 | 21.14 |
| 3/4" | L1@0.15 | Ea | 16.70 | 5.94 | 22.64 |
| 1" | L1@0.20 | Ea | 28.20 | 7.93 | 36.13 |
| 1-1/4" | L1@0.20 | Ea | 32.00 | 7.93 | 39.93 |
| 1-1/2" | L1@0.25 | Ea | 34.80 | 9.91 | 44.71 |
| 2" | L1@0.25 | Ea | 47.00 | 9.91 | 56.91 |
| 2-1/2" | L1@0.30 | Ea | 73.90 | 11.90 | 85.80 |
| 3" | L1@0.30 | Ea | 93.70 | 11.90 | 105.60 |
| 3-1/2" | L1@0.35 | Ea | 113.00 | 13.90 | 126.90 |
| 4" | L1@0.40 | Ea | 133.00 | 15.90 | 148.90 |
| 5" | L1@0.50 | Ea | 310.00 | 19.80 | 329.80 |
| 6" | L1@0.75 | Ea | 313.00 | 29.70 | 342.70 |



Use these figures to estimate the cost of elbows, couplings and running thread installed on intermediate metal conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include cutting, removal of the knockout, layout, material handling, and normal waste. Add for elbow couplings, terminations, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Elbows and running thread are factory made. Job specifications may prohibit the use of running thread.

Galvanized Steel Locknuts and Plastic or Insulated Bushings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------------------------------|-----------|------|---------------|------------|----------------|
| Galvanized steel locknuts | | | | | |
| 1/2" | L1@0.02 | Ea | .18 | .79 | .97 |
| 3/4" | L1@0.02 | Ea | .29 | .79 | 1.08 |
| 1" | L1@0.02 | Ea | .50 | .79 | 1.29 |
| 1-1/4" | L1@0.03 | Ea | .65 | 1.19 | 1.84 |
| 1-1/2" | L1@0.03 | Ea | .94 | 1.19 | 2.13 |
| 2" | L1@0.05 | Ea | 1.39 | 1.98 | 3.37 |
| 2-1/2" | L1@0.05 | Ea | 3.43 | 1.98 | 5.41 |
| 3" | L1@0.07 | Ea | 4.37 | 2.77 | 7.14 |
| 3-1/2" | L1@0.07 | Ea | 8.38 | 2.77 | 11.15 |
| 4" | L1@0.09 | Ea | 9.29 | 3.57 | 12.86 |
| 5" | L1@0.10 | Ea | 18.70 | 3.96 | 22.66 |
| 6" | L1@0.20 | Ea | 41.00 | 7.93 | 48.93 |

| | | | | | |
|-------------------------|---------|----|-------|------|-------|
| Plastic bushings | | | | | |
| 1/2" | L1@0.02 | Ea | .17 | .79 | .96 |
| 3/4" | L1@0.02 | Ea | .31 | .79 | 1.10 |
| 1" | L1@0.03 | Ea | .49 | 1.19 | 1.68 |
| 1-1/4" | L1@0.04 | Ea | .71 | 1.59 | 2.30 |
| 1-1/2" | L1@0.04 | Ea | .97 | 1.59 | 2.56 |
| 2" | L1@0.05 | Ea | 1.80 | 1.98 | 3.78 |
| 2-1/2" | L1@0.05 | Ea | 4.24 | 1.98 | 6.22 |
| 3" | L1@0.07 | Ea | 4.25 | 2.77 | 7.02 |
| 3-1/2" | L1@0.07 | Ea | 5.98 | 2.77 | 8.75 |
| 4" | L1@0.09 | Ea | 6.42 | 3.57 | 9.99 |
| 5" | L1@0.10 | Ea | 12.20 | 3.96 | 16.16 |
| 6" | L1@0.20 | Ea | 21.40 | 7.93 | 29.33 |



| | | | | | |
|----------------------------------|---------|----|--------|-------|--------|
| Insulated ground bushings | | | | | |
| 1/2" | L1@0.10 | Ea | 4.28 | 3.96 | 8.24 |
| 3/4" | L1@0.10 | Ea | 5.50 | 3.96 | 9.46 |
| 1" | L1@0.10 | Ea | 6.12 | 3.96 | 10.08 |
| 1-1/4" | L1@0.15 | Ea | 8.45 | 5.94 | 14.39 |
| 1-1/2" | L1@0.15 | Ea | 9.22 | 5.94 | 15.16 |
| 2" | L1@0.20 | Ea | 5.89 | 7.93 | 13.82 |
| 2-1/2" | L1@0.20 | Ea | 22.00 | 7.93 | 29.93 |
| 3" | L1@0.25 | Ea | 28.70 | 9.91 | 38.61 |
| 3-1/2" | L1@0.25 | Ea | 35.30 | 9.91 | 45.21 |
| 4" | L1@0.30 | Ea | 43.60 | 11.90 | 55.50 |
| 5" | L1@0.40 | Ea | 59.40 | 15.90 | 75.30 |
| 6" | L1@0.50 | Ea | 106.00 | 19.80 | 125.80 |

Use these figures to estimate the cost of locknuts and bushings installed on GRS or IMC conduit under the conditions described on pages 5 and 6. Costs listed are for each locknut or bushing installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include removal of the knockout, layout, material handling, and normal waste. Add for conduit, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume purchase of full box quantities. The locknuts are steel for sizes up to 2" and malleable for sizes over 2". On conduit terminations at boxes or cabinets, one locknut is used inside the box and one locknut is used outside the box. A bushing is used at the end of each conduit run to protect the wire. An insulated ground bushing is used when connecting a ground wire to the conduit system.





Galvanized Rigid Steel Nipples

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---------------------------------------|-----------|------|---------------|------------|----------------|
| Galvanized rigid steel nipples | | | | | |
| 1/2" x close | L1@0.05 | Ea | 1.01 | 1.98 | 2.99 |
| 1/2" x 1-1/2" | L1@0.05 | Ea | 1.08 | 1.98 | 3.06 |
| 1/2" x 2" | L1@0.05 | Ea | 1.18 | 1.98 | 3.16 |
| 1/2" x 2-1/2" | L1@0.05 | Ea | 1.25 | 1.98 | 3.23 |
| 1/2" x 3" | L1@0.05 | Ea | 1.46 | 1.98 | 3.44 |
| 1/2" x 3-1/2" | L1@0.05 | Ea | 1.70 | 1.98 | 3.68 |
| 1/2" x 4" | L1@0.05 | Ea | 2.24 | 1.98 | 4.22 |
| 1/2" x 5" | L1@0.05 | Ea | 3.52 | 1.98 | 5.50 |
| 1/2" x 6" | L1@0.05 | Ea | 4.19 | 1.98 | 6.17 |
| 1/2" x 8" | L1@0.05 | Ea | 7.28 | 1.98 | 9.26 |
| 1/2" x 10" | L1@0.05 | Ea | 8.38 | 1.98 | 10.36 |
| 1/2" x 12" | L1@0.05 | Ea | 9.70 | 1.98 | 11.68 |
| 3/4" x close | L1@0.06 | Ea | 2.15 | 2.38 | 4.53 |
| 3/4" x 2" | L1@0.06 | Ea | 2.56 | 2.38 | 4.94 |
| 3/4" x 2-1/2" | L1@0.06 | Ea | 2.82 | 2.38 | 5.20 |
| 3/4" x 3" | L1@0.06 | Ea | 3.10 | 2.38 | 5.48 |
| 3/4" x 3-1/2" | L1@0.06 | Ea | 3.23 | 2.38 | 5.61 |
| 3/4" x 4" | L1@0.06 | Ea | 3.66 | 2.38 | 6.04 |
| 3/4" x 5" | L1@0.06 | Ea | 4.20 | 2.38 | 6.58 |
| 3/4" x 6" | L1@0.06 | Ea | 4.90 | 2.38 | 7.28 |
| 3/4" x 8" | L1@0.06 | Ea | 8.06 | 2.38 | 10.44 |
| 3/4" x 10" | L1@0.06 | Ea | 9.70 | 2.38 | 12.08 |
| 3/4" x 12" | L1@0.06 | Ea | 10.90 | 2.38 | 13.28 |
| 1" x close | L1@0.08 | Ea | 3.24 | 3.17 | 6.41 |
| 1" x 2" | L1@0.08 | Ea | 3.55 | 3.17 | 6.72 |
| 1" x 2-1/2" | L1@0.08 | Ea | 3.86 | 3.17 | 7.03 |
| 1" x 3" | L1@0.08 | Ea | 4.30 | 3.17 | 7.47 |
| 1" x 3-1/2" | L1@0.08 | Ea | 4.90 | 3.17 | 8.07 |
| 1" x 4" | L1@0.08 | Ea | 5.39 | 3.17 | 8.56 |
| 1" x 5" | L1@0.08 | Ea | 6.12 | 3.17 | 9.29 |
| 1" x 6" | L1@0.08 | Ea | 6.68 | 3.17 | 9.85 |
| 1" x 8" | L1@0.08 | Ea | 10.60 | 3.17 | 13.77 |
| 1" x 10" | L1@0.08 | Ea | 13.70 | 3.17 | 16.87 |
| 1" x 12" | L1@0.08 | Ea | 15.50 | 3.17 | 18.67 |

Use these figures to estimate the cost of nipples installed on GRS conduit under the conditions described on pages 5 and 6. Costs listed are for each nipple installed. The crew is one electrician at a labor cost of \$39.63 per manhour. These costs include removal of the knockout, layout, material handling, and normal waste. Add for terminations, couplings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Nipples are factory made, not field made. In many cases a coupling will be needed with a nipple.









Galvanized Rigid Steel Nipples

| | Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|-----------------|-----------|------|---------------|------------|----------------|
| Galvanized rigid steel nipples (continued) | | | | | | |
|  | 1-1/4" x close | L1@0.10 | Ea | 4.33 | 3.96 | 8.29 |
| | 1-1/4" x 2" | L1@0.10 | Ea | 4.84 | 3.96 | 8.80 |
| | 1-1/4" x 2-1/2" | L1@0.10 | Ea | 5.09 | 3.96 | 9.05 |
| | 1-1/4" x 3" | L1@0.10 | Ea | 5.48 | 3.96 | 9.44 |
| | 1-1/4" x 3-1/2" | L1@0.10 | Ea | 6.24 | 3.96 | 10.20 |
| | 1-1/4" x 4" | L1@0.10 | Ea | 6.60 | 3.96 | 10.56 |
| | 1-1/4" x 5" | L1@0.10 | Ea | 7.66 | 3.96 | 11.62 |
| | 1-1/4" x 6" | L1@0.10 | Ea | 8.60 | 3.96 | 12.56 |
| | 1-1/4" x 8" | L1@0.10 | Ea | 14.20 | 3.96 | 18.16 |
| | 1-1/4" x 10" | L1@0.10 | Ea | 17.80 | 3.96 | 21.76 |
| | 1-1/4" x 12" | L1@0.10 | Ea | 20.60 | 3.96 | 24.56 |
|  | 1-1/2" x close | L1@0.10 | Ea | 5.21 | 3.96 | 9.17 |
| | 1-1/2" x 2" | L1@0.10 | Ea | 5.51 | 3.96 | 9.47 |
| | 1-1/2" x 2-1/2" | L1@0.10 | Ea | 6.22 | 3.96 | 10.18 |
| | 1-1/2" x 3" | L1@0.10 | Ea | 8.52 | 3.96 | 12.48 |
| | 1-1/2" x 3-1/2" | L1@0.10 | Ea | 9.79 | 3.96 | 13.75 |
| | 1-1/2" x 4" | L1@0.10 | Ea | 10.70 | 3.96 | 14.66 |
| | 1-1/2" x 5" | L1@0.10 | Ea | 12.10 | 3.96 | 16.06 |
| | 1-1/2" x 6" | L1@0.10 | Ea | 14.80 | 3.96 | 18.76 |
| | 1-1/2" x 8" | L1@0.10 | Ea | 22.40 | 3.96 | 26.36 |
| | 1-1/2" x 10" | L1@0.10 | Ea | 23.30 | 3.96 | 27.26 |
| | 1-1/2" x 12" | L1@0.10 | Ea | 25.20 | 3.96 | 29.16 |
|  | 2" x close | L1@0.15 | Ea | 6.22 | 5.94 | 12.16 |
| | 2" x 2-1/2" | L1@0.15 | Ea | 7.30 | 5.94 | 13.24 |
| | 2" x 3" | L1@0.15 | Ea | 8.45 | 5.94 | 14.39 |
| | 2" x 3-1/2" | L1@0.15 | Ea | 9.60 | 5.94 | 15.54 |
| | 2" x 4" | L1@0.15 | Ea | 10.70 | 5.94 | 16.64 |
| | 2" x 5" | L1@0.15 | Ea | 12.40 | 5.94 | 18.34 |
| | 2" x 6" | L1@0.15 | Ea | 14.20 | 5.94 | 20.14 |
| | 2" x 8" | L1@0.15 | Ea | 20.40 | 5.94 | 26.34 |
| | 2" x 10" | L1@0.15 | Ea | 24.60 | 5.94 | 30.54 |
| | 2" x 12" | L1@0.15 | Ea | 27.80 | 5.94 | 33.74 |
|  | 2-1/2" x close | L1@0.15 | Ea | 17.30 | 5.94 | 23.24 |
| | 2-1/2" x 3" | L1@0.15 | Ea | 17.50 | 5.94 | 23.44 |
| | 2-1/2" x 3-1/2" | L1@0.15 | Ea | 20.50 | 5.94 | 26.44 |
| | 2-1/2" x 4" | L1@0.15 | Ea | 21.60 | 5.94 | 27.54 |
| | 2-1/2" x 5" | L1@0.15 | Ea | 25.70 | 5.94 | 31.64 |
| | 2-1/2" x 6" | L1@0.15 | Ea | 29.00 | 5.94 | 34.94 |

Use these figures to estimate the cost of nipples installed on GRS conduit under the conditions described on pages 5 and 6. Costs listed are for each nipple installed. The crew is one electrician at a labor cost of \$39.63 per manhour. These costs include removal of the knockout, layout, material handling, and normal waste. Add for terminations, couplings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Nipples are factory made, not field made. In many cases a coupling will be needed with a nipple.


Galvanized Rigid Steel Nipples

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost | |
|---|-----------|------|---------------|------------|----------------|---|
| Galvanized rigid steel nipples (continued) | | | | | | |
| 2-1/2" x 8" | L1@0.15 | Ea | 38.20 | 5.94 | 44.14 |  |
| 2-1/2" x 10" | L1@0.15 | Ea | 44.40 | 5.94 | 50.34 | |
| 2-1/2" x 12" | L1@0.15 | Ea | 51.60 | 5.94 | 57.54 | |
| 3" x close | L1@0.20 | Ea | 20.30 | 7.93 | 28.23 |  |
| 3" x 3" | L1@0.20 | Ea | 21.50 | 7.93 | 29.43 | |
| 3" x 3-1/2" | L1@0.20 | Ea | 24.20 | 7.93 | 32.13 | |
| 3" x 4" | L1@0.20 | Ea | 26.20 | 7.93 | 34.13 | |
| 3" x 5" | L1@0.20 | Ea | 30.50 | 7.93 | 38.43 | |
| 3" x 6" | L1@0.20 | Ea | 34.80 | 7.93 | 42.73 | |
| 3" x 8" | L1@0.20 | Ea | 52.10 | 7.93 | 60.03 | |
| 3" x 10" | L1@0.20 | Ea | 62.60 | 7.93 | 70.53 |  |
| 3" x 12" | L1@0.20 | Ea | 65.00 | 7.93 | 72.93 | |
| 3-1/2" x close | L1@0.25 | Ea | 24.80 | 9.91 | 34.71 | |
| 3-1/2" x 4" | L1@0.25 | Ea | 31.90 | 9.91 | 41.81 | |
| 3-1/2" x 5" | L1@0.25 | Ea | 36.20 | 9.91 | 46.11 | |
| 3-1/2" x 6" | L1@0.25 | Ea | 41.30 | 9.91 | 51.21 | |
| 3-1/2" x 8" | L1@0.25 | Ea | 52.10 | 9.91 | 62.01 | |
| 3-1/2" x 10" | L1@0.25 | Ea | 62.60 | 9.91 | 72.51 |  |
| 3-1/2" x 12" | L1@0.25 | Ea | 73.20 | 9.91 | 83.11 | |
| 4" x close | L1@0.25 | Ea | 29.50 | 9.91 | 39.41 | |
| 4" x 4" | L1@0.25 | Ea | 35.90 | 9.91 | 45.81 | |
| 4" x 5" | L1@0.25 | Ea | 42.10 | 9.91 | 52.01 | |
| 4" x 6" | L1@0.25 | Ea | 46.90 | 9.91 | 56.81 | |
| 4" x 8" | L1@0.25 | Ea | 58.60 | 9.91 | 68.51 | |
| 4" x 10" | L1@0.25 | Ea | 72.40 | 9.91 | 82.31 |  |
| 4" x 12" | L1@0.25 | Ea | 86.00 | 9.91 | 95.91 | |
| 5" x close | L1@0.40 | Ea | 21.80 | 15.90 | 37.70 | |
| 5" x 5" | L1@0.40 | Ea | 55.60 | 15.90 | 71.50 | |
| 5" x 6" | L1@0.40 | Ea | 60.50 | 15.90 | 76.40 | |
| 5" x 8" | L1@0.40 | Ea | 148.00 | 15.90 | 163.90 | |
| 5" x 10" | L1@0.40 | Ea | 84.50 | 15.90 | 100.40 | |
| 5" x 12" | L1@0.40 | Ea | 210.00 | 15.90 | 225.90 |  |
| 6" x close | L1@0.60 | Ea | 50.20 | 23.80 | 74.00 | |
| 6" x 5" | L1@0.60 | Ea | 89.00 | 23.80 | 112.80 | |
| 6" x 6" | L1@0.60 | Ea | 111.00 | 23.80 | 134.80 | |
| 6" x 8" | L1@0.60 | Ea | 124.00 | 23.80 | 147.80 | |
| 6" x 10" | L1@0.60 | Ea | 143.00 | 23.80 | 166.80 | |
| 6" x 12" | L1@0.60 | Ea | 158.00 | 23.80 | 181.80 | |

Use these figures to estimate the cost of nipples installed on GRS conduit under the conditions described on pages 5 and 6. Costs listed are for each nipple installed. The crew is one electrician working at a cost of \$39.63 per manhour. These costs include removal of the knockout, layout, material handling, and normal waste. Add for terminations, couplings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Nipples are factory made, not field made. In many cases a coupling will be needed with a nipple.


Aluminum Rigid Conduit (ARC), Elbows and Nipples

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|-------------------------------|-----------|------|---------------|------------|----------------|
| Aluminum rigid conduit | | | | | |
| 1/2" | L1@3.75 | CLF | 178.00 | 149.00 | 327.00 |
| 3/4" | L1@4.00 | CLF | 239.00 | 159.00 | 398.00 |
| 1" | L1@4.50 | CLF | 339.00 | 178.00 | 517.00 |
| 1-1/4" | L1@6.00 | CLF | 473.00 | 238.00 | 711.00 |
| 1-1/2" | L1@7.00 | CLF | 433.00 | 277.00 | 710.00 |
| 2" | L1@8.50 | CLF | 738.00 | 337.00 | 1,075.00 |
| 2-1/2" | L2@10.0 | CLF | 999.00 | 396.00 | 1,395.00 |
| 3" | L2@12.0 | CLF | 1,260.00 | 476.00 | 1,736.00 |
| 3-1/2" | L2@14.0 | CLF | 1,500.00 | 555.00 | 2,055.00 |
| 4" | L2@16.0 | CLF | 1,780.00 | 634.00 | 2,414.00 |
| 5" | L2@20.0 | CLF | 2,710.00 | 793.00 | 3,503.00 |
| 6" | L2@25.0 | CLF | 3,740.00 | 991.00 | 4,731.00 |




90 degree aluminum rigid conduit elbows

| | | | | | |
|--------|---------|----|----------|-------|----------|
| 1/2" | L1@0.10 | Ea | 12.50 | 3.96 | 16.46 |
| 3/4" | L1@0.10 | Ea | 16.10 | 3.96 | 20.06 |
| 1" | L1@0.10 | Ea | 26.50 | 3.96 | 30.46 |
| 1-1/4" | L1@0.15 | Ea | 27.60 | 5.94 | 33.54 |
| 1-1/2" | L1@0.15 | Ea | 105.00 | 5.94 | 110.94 |
| 2" | L1@0.20 | Ea | 156.00 | 7.93 | 163.93 |
| 2-1/2" | L2@0.20 | Ea | 263.00 | 7.93 | 270.93 |
| 3" | L2@0.25 | Ea | 405.00 | 9.91 | 414.91 |
| 3-1/2" | L2@0.25 | Ea | 634.00 | 9.91 | 643.91 |
| 4" | L2@0.30 | Ea | 1,070.00 | 11.90 | 1,081.90 |
| 5" | L2@0.40 | Ea | 2,220.00 | 15.90 | 2,235.90 |
| 6" | L2@0.70 | Ea | 3,060.00 | 27.70 | 3,087.70 |



Aluminum rigid conduit nipples

| | | | | | |
|---------------|---------|----|-------|------|-------|
| 1/2" x close | L1@0.05 | Ea | 13.70 | 1.98 | 15.68 |
| 1/2" x 1-1/2" | L1@0.05 | Ea | 10.40 | 1.98 | 12.38 |
| 1/2" x 2" | L1@0.05 | Ea | 11.30 | 1.98 | 13.28 |
| 1/2" x 2-1/2" | L1@0.05 | Ea | 13.40 | 1.98 | 15.38 |
| 1/2" x 3" | L1@0.05 | Ea | 14.00 | 1.98 | 15.98 |
| 1/2" x 3-1/2" | L1@0.05 | Ea | 15.20 | 1.98 | 17.18 |
| 1/2" x 4" | L1@0.05 | Ea | 16.40 | 1.98 | 18.38 |
| 1/2" x 5" | L1@0.05 | Ea | 18.60 | 1.98 | 20.58 |
| 1/2" x 6" | L1@0.05 | Ea | 19.70 | 1.98 | 21.68 |
| 1/2" x 8" | L1@0.05 | Ea | 26.40 | 1.98 | 28.38 |
| 1/2" x 10" | L1@0.05 | Ea | 32.00 | 1.98 | 33.98 |
| 1/2" x 12" | L1@0.05 | Ea | 37.20 | 1.98 | 39.18 |
| 3/4" x close | L1@0.06 | Ea | 13.70 | 2.38 | 16.08 |
| 3/4" x 2" | L1@0.06 | Ea | 14.80 | 2.38 | 17.18 |
| 3/4" x 2-1/2" | L1@0.06 | Ea | 15.80 | 2.38 | 18.18 |




Use these figures to estimate the cost of aluminum rigid conduit, elbows and nipples installed in a building under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet of conduit or each fitting installed. The crew is one electrician for conduit sizes to 2" and two electricians for conduit over 2". The labor cost is \$39.63 per manhour. These costs include conduit bending, one coupling for each length of conduit, layout, material handling, and normal waste. Add for extra couplings, straps, terminations, wire, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Elbows and nipples are factory made. Do not install ARC in concrete or masonry construction. Conduit runs are assumed to be 50' long. Installation costs per linear foot will be less on longer runs and more on shorter runs.




ARC Nipples

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---------------------------------------|-----------|------|---------------|------------|----------------|
| Aluminum rigid conduit nipples | | | | | |
| 3/4" x 3" | L1@0.06 | Ea | 17.00 | 2.38 | 19.38 |
| 3/4" x 3-1/2" | L1@0.06 | Ea | 17.60 | 2.38 | 19.98 |
| 3/4" x 4" | L1@0.06 | Ea | 18.50 | 2.38 | 20.88 |
| 3/4" x 5" | L1@0.06 | Ea | 22.30 | 2.38 | 24.68 |
| 3/4" x 6" | L1@0.06 | Ea | 25.30 | 2.38 | 27.68 |
| 3/4" x 8" | L1@0.06 | Ea | 33.40 | 2.38 | 35.78 |
| 3/4" x 10" | L1@0.06 | Ea | 39.10 | 2.38 | 41.48 |
| 3/4" x 12" | L1@0.06 | Ea | 47.80 | 2.38 | 50.18 |
| 1" x close | L1@0.08 | Ea | 16.70 | 3.17 | 19.87 |
| 1" x 2" | L1@0.08 | Ea | 18.50 | 3.17 | 21.67 |
| 1" x 2-1/2" | L1@0.08 | Ea | 20.30 | 3.17 | 23.47 |
| 1" x 3" | L1@0.08 | Ea | 21.90 | 3.17 | 25.07 |
| 1" x 3-1/2" | L1@0.08 | Ea | 24.40 | 3.17 | 27.57 |
| 1" x 4" | L1@0.08 | Ea | 27.00 | 3.17 | 30.17 |
| 1" x 5" | L1@0.08 | Ea | 31.90 | 3.17 | 35.07 |
| 1" x 6" | L1@0.08 | Ea | 37.60 | 3.17 | 40.77 |
| 1" x 8" | L1@0.08 | Ea | 46.80 | 3.17 | 49.97 |
| 1" x 10" | L1@0.08 | Ea | 58.80 | 3.17 | 61.97 |
| 1" x 12" | L1@0.08 | Ea | 69.60 | 3.17 | 72.77 |
| 1-1/4" x close | L1@0.10 | Ea | 22.40 | 3.96 | 26.36 |
| 1-1/4" x 2" | L1@0.10 | Ea | 23.00 | 3.96 | 26.96 |
| 1-1/4" x 2-1/2" | L1@0.10 | Ea | 25.20 | 3.96 | 29.16 |
| 1-1/4" x 3" | L1@0.10 | Ea | 28.40 | 3.96 | 32.36 |
| 1-1/4" x 3-1/2" | L1@0.10 | Ea | 32.50 | 3.96 | 36.46 |
| 1-1/4" x 4" | L1@0.10 | Ea | 41.90 | 3.96 | 45.86 |
| 1-1/4" x 5" | L1@0.10 | Ea | 48.80 | 3.96 | 52.76 |
| 1-1/4" x 6" | L1@0.10 | Ea | 48.80 | 3.96 | 52.76 |
| 1-1/4" x 8" | L1@0.10 | Ea | 62.00 | 3.96 | 65.96 |
| 1-1/4" x 10" | L1@0.10 | Ea | 75.60 | 3.96 | 79.56 |
| 1-1/4" x 12" | L1@0.10 | Ea | 88.70 | 3.96 | 92.66 |
| 1-1/2" x close | L1@0.10 | Ea | 27.90 | 3.96 | 31.86 |
| 1-1/2" x 2" | L1@0.10 | Ea | 28.60 | 3.96 | 32.56 |
| 1-1/2" x 2-1/2" | L1@0.10 | Ea | 30.50 | 3.96 | 34.46 |
| 1-1/2" x 3" | L1@0.10 | Ea | 34.70 | 3.96 | 38.66 |
| 1-1/2" x 3-1/2" | L1@0.10 | Ea | 43.70 | 3.96 | 47.66 |
| 1-1/2" x 4" | L1@0.10 | Ea | 43.80 | 3.96 | 47.76 |
| 1-1/2" x 5" | L1@0.10 | Ea | 50.30 | 3.96 | 54.26 |
| 1-1/2" x 6" | L1@0.10 | Ea | 58.10 | 3.96 | 62.06 |
| 1-1/2" x 8" | L1@0.10 | Ea | 74.70 | 3.96 | 78.66 |
| 1-1/2" x 10" | L1@0.10 | Ea | 90.90 | 3.96 | 94.86 |
| 1-1/2" x 12" | L1@0.10 | Ea | 106.00 | 3.96 | 109.96 |

Use these figures to estimate the cost of ARC nipples installed on ARC conduit under the conditions described on pages 5 and 6. Costs listed are for each nipple installed. The crew is one electrician at a labor cost of \$39.63 per manhour. These costs include removing the knockout, layout, material handling, and normal waste. Add for extra couplings, straps, boxes, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume the purchase of full packages.



ARC Nipples

| | Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|-----------------|-----------|------|---------------|------------|----------------|
| Aluminum rigid conduit nipples (continued) | | | | | | |
|  | 2" x close | L1@0.15 | Ea | 28.60 | 5.94 | 34.54 |
| | 2" x 2-1/2" | L1@0.15 | Ea | 39.70 | 5.94 | 45.64 |
| | 2" x 3" | L1@0.15 | Ea | 44.40 | 5.94 | 50.34 |
| | 2" x 3-1/2" | L1@0.15 | Ea | 52.40 | 5.94 | 58.34 |
| | 2" x 4" | L1@0.15 | Ea | 54.70 | 5.94 | 60.64 |
| | 2" x 5" | L1@0.15 | Ea | 54.70 | 5.94 | 60.64 |
| | 2" x 6" | L1@0.15 | Ea | 75.20 | 5.94 | 81.14 |
| | 2" x 8" | L1@0.15 | Ea | 95.90 | 5.94 | 101.84 |
| | 2" x 10" | L1@0.15 | Ea | 116.00 | 5.94 | 121.94 |
| | 2" x 12" | L1@0.15 | Ea | 138.00 | 5.94 | 143.94 |
|  | 2-1/2" x close | L1@0.15 | Ea | 78.40 | 5.94 | 84.34 |
| | 2-1/2" x 3" | L1@0.15 | Ea | 80.60 | 5.94 | 86.54 |
| | 2-1/2" x 3-1/2" | L1@0.15 | Ea | 89.80 | 5.94 | 95.74 |
| | 2-1/2" x 4" | L1@0.15 | Ea | 95.00 | 5.94 | 100.94 |
| | 2-1/2" x 5" | L1@0.15 | Ea | 106.00 | 5.94 | 111.94 |
| | 2-1/2" x 6" | L1@0.15 | Ea | 116.00 | 5.94 | 121.94 |
| | 2-1/2" x 8" | L1@0.15 | Ea | 148.00 | 5.94 | 153.94 |
| | 2-1/2" x 10" | L1@0.15 | Ea | 179.00 | 5.94 | 184.94 |
| | 2-1/2" x 12" | L1@0.15 | Ea | 201.00 | 5.94 | 206.94 |
|  | 3" x close | L1@0.20 | Ea | 51.00 | 7.93 | 58.93 |
| | 3" x 3-1/2" | L1@0.20 | Ea | 68.20 | 7.93 | 76.13 |
| | 3" x 4" | L1@0.20 | Ea | 71.30 | 7.93 | 79.23 |
| | 3" x 5" | L1@0.20 | Ea | 81.30 | 7.93 | 89.23 |
| | 3" x 6" | L1@0.20 | Ea | 93.30 | 7.93 | 101.23 |
| | 3" x 8" | L1@0.20 | Ea | 119.00 | 7.93 | 126.93 |
| | 3" x 10" | L1@0.20 | Ea | 144.00 | 7.93 | 151.93 |
| | 3" x 12" | L1@0.20 | Ea | 170.00 | 7.93 | 177.93 |
| | 3-1/2" x close | L1@0.25 | Ea | 65.10 | 9.91 | 75.01 |
| | 3-1/2" x 4" | L1@0.25 | Ea | 82.00 | 9.91 | 91.91 |
| | 3-1/2" x 5" | L1@0.25 | Ea | 98.60 | 9.91 | 108.51 |
| | 3-1/2" x 6" | L1@0.25 | Ea | 114.00 | 9.91 | 123.91 |
| | 3-1/2" x 8" | L1@0.25 | Ea | 142.00 | 9.91 | 151.91 |
| | 3-1/2" x 10" | L1@0.25 | Ea | 176.00 | 9.91 | 185.91 |
| | 3-1/2" x 12" | L1@0.25 | Ea | 205.00 | 9.91 | 214.91 |

Use these figures to estimate the cost of ARC nipples installed on ARC conduit under the conditions described on pages 5 and 6. Costs listed are for each nipple installed. The crew is one electrician at a labor cost of \$39.63 per manhour. These costs include removing the knockout, layout, material handling, and normal waste. Add for extra couplings, straps, boxes, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs assume the purchase of full packages. Nipples are factory made, not field made. In many cases a coupling will be needed with each nipple. Do not install aluminum fittings in concrete or masonry. The bending, cutting and threading tools for aluminum conduit are the same as used for GRS. Don't mix aluminum fittings with other types of fittings.

ARC Nipples, Locknuts and Bushings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Aluminum rigid conduit nipples (continued)

| | | | | | |
|------------|---------|----|--------|-------|--------|
| 4" x close | L1@0.25 | Ea | 68.40 | 9.91 | 78.31 |
| 4" x 4" | L1@0.25 | Ea | 85.70 | 9.91 | 95.61 |
| 4" x 5" | L1@0.25 | Ea | 98.60 | 9.91 | 108.51 |
| 4" x 6" | L1@0.25 | Ea | 114.00 | 9.91 | 123.91 |
| 4" x 8" | L1@0.25 | Ea | 144.00 | 9.91 | 153.91 |
| 4" x 10" | L1@0.25 | Ea | 176.00 | 9.91 | 185.91 |
| 4" x 12" | L1@0.25 | Ea | 207.00 | 9.91 | 216.91 |
| 5" x close | L1@0.40 | Ea | 159.00 | 15.90 | 174.90 |
| 5" x 5" | L1@0.40 | Ea | 187.00 | 15.90 | 202.90 |
| 5" x 6" | L1@0.40 | Ea | 195.00 | 15.90 | 210.90 |
| 5" x 8" | L1@0.40 | Ea | 249.00 | 15.90 | 264.90 |
| 5" x 10" | L1@0.40 | Ea | 300.00 | 15.90 | 315.90 |
| 5" x 12" | L1@0.40 | Ea | 345.00 | 15.90 | 360.90 |
| 6" x close | L1@0.60 | Ea | 192.00 | 23.80 | 215.80 |
| 6" x 5" | L1@0.60 | Ea | 224.00 | 23.80 | 247.80 |
| 6" x 6" | L1@0.60 | Ea | 245.00 | 23.80 | 268.80 |
| 6" x 8" | L1@0.60 | Ea | 334.00 | 23.80 | 357.80 |
| 6" x 10" | L1@0.60 | Ea | 401.00 | 23.80 | 424.80 |
| 6" x 12" | L1@0.60 | Ea | 442.00 | 23.80 | 465.80 |




Aluminum locknuts

| | | | | | |
|--------|---------|----|--------|------|--------|
| 1/2" | L1@0.02 | Ea | .47 | .79 | 1.26 |
| 3/4" | L1@0.02 | Ea | .85 | .79 | 1.64 |
| 1" | L1@0.02 | Ea | 1.27 | .79 | 2.06 |
| 1-1/4" | L1@0.03 | Ea | 1.69 | 1.19 | 2.88 |
| 1-1/2" | L1@0.03 | Ea | 2.39 | 1.19 | 3.58 |
| 2" | L1@0.05 | Ea | 3.82 | 1.98 | 5.80 |
| 2-1/2" | L1@0.05 | Ea | 7.29 | 1.98 | 9.27 |
| 3" | L1@0.07 | Ea | 8.06 | 2.77 | 10.83 |
| 3-1/2" | L1@0.07 | Ea | 22.70 | 2.77 | 25.47 |
| 4" | L1@0.09 | Ea | 24.90 | 3.57 | 28.47 |
| 5" | L1@0.10 | Ea | 63.30 | 3.96 | 67.26 |
| 6" | L1@0.20 | Ea | 112.00 | 7.93 | 119.93 |



Aluminum bushings

| | | | | | |
|------|---------|----|-------|------|-------|
| 1/2" | L1@0.02 | Ea | 4.36 | .79 | 5.15 |
| 3/4" | L1@0.02 | Ea | 7.98 | .79 | 8.77 |
| 1" | L1@0.03 | Ea | 10.50 | 1.19 | 11.69 |




Use these figures to estimate the cost of ARC nipples, locknuts and bushings installed on ARC conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include removing the knockout, layout, material handling, and normal waste. Add for extra couplings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs are based on purchase of full packages. Nipples are factory made, not field made. In many cases a coupling will be needed with each nipple. Do not install aluminum fittings in concrete or masonry.

Aluminum Bushings and Terminations


| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Aluminum bushings (continued)




| | | | | | |
|--------|---------|----|--------|------|--------|
| 1-1/4" | L1@0.04 | Ea | 16.50 | 1.59 | 18.09 |
| 1-1/2" | L1@0.04 | Ea | 20.90 | 1.59 | 22.49 |
| 2" | L1@0.05 | Ea | 25.70 | 1.98 | 27.68 |
| 2-1/2" | L1@0.05 | Ea | 34.60 | 1.98 | 36.58 |
| 3" | L1@0.07 | Ea | 36.70 | 2.77 | 39.47 |
| 3-1/2" | L1@0.07 | Ea | 73.40 | 2.77 | 76.17 |
| 4" | L1@0.09 | Ea | 85.10 | 3.57 | 88.67 |
| 5" | L1@0.10 | Ea | 142.00 | 3.96 | 145.96 |
| 6" | L1@0.20 | Ea | 217.00 | 7.93 | 224.93 |

Insulated aluminum ground bushings



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 10.50 | 3.96 | 14.46 |
| 3/4" | L1@0.10 | Ea | 11.80 | 3.96 | 15.76 |
| 1" | L1@0.10 | Ea | 17.20 | 3.96 | 21.16 |
| 1-1/4" | L1@0.15 | Ea | 17.40 | 5.94 | 23.34 |
| 1-1/2" | L1@0.15 | Ea | 22.10 | 5.94 | 28.04 |
| 2" | L1@0.20 | Ea | 29.70 | 7.93 | 37.63 |
| 2-1/2" | L1@0.20 | Ea | 53.40 | 7.93 | 61.33 |
| 3" | L1@0.25 | Ea | 81.00 | 9.91 | 90.91 |
| 3-1/2" | L1@0.25 | Ea | 97.70 | 9.91 | 107.61 |
| 4" | L1@0.30 | Ea | 131.00 | 11.90 | 142.90 |
| 5" | L1@0.40 | Ea | 207.00 | 15.90 | 222.90 |
| 6" | L1@0.50 | Ea | 319.00 | 19.80 | 338.80 |

Conduit termination, two aluminum locknuts & one plastic bushing



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 4.19 | 1.98 | 6.17 |
| 3/4" | L1@0.06 | Ea | 6.46 | 2.38 | 8.84 |
| 1" | L1@0.08 | Ea | 10.60 | 3.17 | 13.77 |
| 1-1/4" | L1@0.10 | Ea | 13.10 | 3.96 | 17.06 |
| 1-1/2" | L1@0.10 | Ea | 30.90 | 3.96 | 34.86 |
| 2" | L1@0.15 | Ea | 34.00 | 5.94 | 39.94 |
| 2-1/2" | L1@0.15 | Ea | 56.10 | 5.94 | 62.04 |
| 3" | L1@0.20 | Ea | 65.60 | 7.93 | 73.53 |
| 3-1/2" | L1@0.20 | Ea | 104.00 | 7.93 | 111.93 |
| 4" | L1@0.25 | Ea | 116.00 | 9.91 | 125.91 |
| 5" | L1@0.40 | Ea | 144.00 | 15.90 | 159.90 |
| 6" | L1@0.60 | Ea | 256.00 | 23.80 | 279.80 |


Use these figures to estimate the cost of aluminum bushings, ground bushings, and terminations under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include removal of knockouts, layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs are based on purchase of full boxes. One locknut is used outside the box and inside the box on each conduit termination. A bushing is needed at each conduit end to protect the wire.

Cast Metal Entrance Elbows and Conduit Bodies

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Cast metal Type SLB entrance elbows

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 4.78 | 3.96 | 8.74 |
| 3/4" | L1@0.15 | Ea | 5.89 | 5.94 | 11.83 |
| 1" | L1@0.15 | Ea | 10.70 | 5.94 | 16.64 |
| 1-1/4" | L1@0.20 | Ea | 16.40 | 7.93 | 24.33 |
| 1-1/2" | L1@0.20 | Ea | 29.50 | 7.93 | 37.43 |
| 2" | L1@0.25 | Ea | 33.60 | 9.91 | 43.51 |
| 2-1/2" | L1@0.30 | Ea | 119.00 | 11.90 | 130.90 |
| 3" | L1@0.40 | Ea | 153.00 | 15.90 | 168.90 |




Galvanized cast metal Types LB, LL or LR conduit bodies

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 7.69 | 3.96 | 11.65 |
| 3/4" | L1@0.15 | Ea | 9.06 | 5.94 | 15.00 |
| 1" | L1@0.20 | Ea | 13.60 | 7.93 | 21.53 |
| 1-1/4" | L1@0.25 | Ea | 23.40 | 9.91 | 33.31 |
| 1-1/2" | L1@0.25 | Ea | 30.50 | 9.91 | 40.41 |
| 2" | L1@0.30 | Ea | 51.00 | 11.90 | 62.90 |
| 2-1/2" | L1@0.40 | Ea | 103.00 | 15.90 | 118.90 |
| 3" | L1@0.50 | Ea | 136.00 | 19.80 | 155.80 |
| 3-1/2" | L1@0.70 | Ea | 230.00 | 27.70 | 257.70 |
| 4" | L1@1.00 | Ea | 260.00 | 39.60 | 299.60 |




Galvanized cast metal Type T conduit bodies

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.15 | Ea | 6.60 | 5.94 | 12.54 |
| 3/4" | L1@0.20 | Ea | 9.15 | 7.93 | 17.08 |
| 1" | L1@0.25 | Ea | 13.40 | 9.91 | 23.31 |
| 1-1/4" | L1@0.30 | Ea | 20.00 | 11.90 | 31.90 |
| 1-1/2" | L1@0.30 | Ea | 30.00 | 11.90 | 41.90 |
| 2" | L1@0.40 | Ea | 46.30 | 15.90 | 62.20 |
| 2-1/2" | L1@0.50 | Ea | 92.40 | 19.80 | 112.20 |
| 3" | L1@0.70 | Ea | 122.00 | 27.70 | 149.70 |
| 3-1/2" | L1@0.90 | Ea | 316.00 | 35.70 | 351.70 |
| 4" | L1@1.25 | Ea | 405.00 | 49.50 | 454.50 |



Galvanized cast metal Type X conduit bodies

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.20 | Ea | 22.20 | 7.93 | 30.13 |
| 3/4" | L1@0.25 | Ea | 26.00 | 9.91 | 35.91 |
| 1" | L1@0.30 | Ea | 35.90 | 11.90 | 47.80 |
| 1-1/4" | L1@0.40 | Ea | 50.30 | 15.90 | 66.20 |
| 1-1/2" | L1@0.40 | Ea | 63.30 | 15.90 | 79.20 |
| 2" | L1@0.50 | Ea | 112.00 | 19.80 | 131.80 |



Use these figures to estimate the cost of conduit bodies installed on EMT or GRS conduit under the conditions described on pages 5 and 6. Costs listed are for each body installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for conduit, nipples, boxes, covers, gaskets, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Using a larger conduit body or a mogul size can reduce the installation time when wire sizes are larger.

Blank Conduit Body Covers

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Steel blank conduit body covers

| | | | | | |
|-------------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | 1.11 | 1.98 | 3.09 |
| 3/4" | L1@0.05 | Ea | 2.47 | 1.98 | 4.45 |
| 1" | L1@0.05 | Ea | 2.03 | 1.98 | 4.01 |
| 1-1/4" | L1@0.10 | Ea | 2.90 | 3.96 | 6.86 |
| 1-1/2" | L1@0.10 | Ea | 3.55 | 3.96 | 7.51 |
| 2" | L1@0.10 | Ea | 5.33 | 3.96 | 9.29 |
| 2-1/2" - 3" | L1@0.15 | Ea | 7.61 | 5.94 | 13.55 |
| 2-1/2" - 4" | L1@0.20 | Ea | 13.70 | 7.93 | 21.63 |

Malleable blank conduit body covers

| | | | | | |
|-------------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | 4.15 | 1.98 | 6.13 |
| 3/4" | L1@0.05 | Ea | 3.45 | 1.98 | 5.43 |
| 1" | L1@0.10 | Ea | 5.54 | 3.96 | 9.50 |
| 1-1/4" | L1@0.10 | Ea | 6.68 | 3.96 | 10.64 |
| 1-1/2" | L1@0.10 | Ea | 7.83 | 3.96 | 11.79 |
| 2" | L1@0.15 | Ea | 15.50 | 5.94 | 21.44 |
| 2-1/2" - 3" | L1@0.20 | Ea | 24.80 | 7.93 | 32.73 |
| 2-1/2" - 4" | L1@0.25 | Ea | 35.60 | 9.91 | 45.51 |

Aluminum blank conduit body covers

| | | | | | |
|-------------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | 1.80 | 1.98 | 3.78 |
| 3/4" | L1@0.05 | Ea | 2.47 | 1.98 | 4.45 |
| 1" | L1@0.05 | Ea | 2.98 | 1.98 | 4.96 |
| 1-1/4" | L1@0.10 | Ea | 4.00 | 3.96 | 7.96 |
| 1-1/2" | L1@0.10 | Ea | 5.92 | 3.96 | 9.88 |
| 2" | L1@0.10 | Ea | 7.83 | 3.96 | 11.79 |
| 2-1/2" - 3" | L1@0.15 | Ea | 12.00 | 5.94 | 17.94 |
| 2-1/2" - 4" | L1@0.20 | Ea | 14.50 | 7.93 | 22.43 |


Use these figures to estimate the cost of blank conduit body covers installed on conduit bodies under the conditions described on pages 5 and 6. Costs listed are for each cover installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for conduit bodies, other fittings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: These figures assume that the conduit body is readily accessible.

Conduit Body Gaskets, Conduit Bodies and Capped Elbows

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Conduit body gaskets

| | | | | | |
|-------------|---------|----|------|------|-------|
| 1/2" | L1@0.02 | Ea | 2.00 | .79 | 2.79 |
| 3/4" | L1@0.02 | Ea | 2.24 | .79 | 3.03 |
| 1" | L1@0.03 | Ea | 2.47 | 1.19 | 3.66 |
| 1-1/4" | L1@0.05 | Ea | 2.71 | 1.98 | 4.69 |
| 1-1/2" | L1@0.05 | Ea | 3.16 | 1.98 | 5.14 |
| 2" | L1@0.07 | Ea | 3.33 | 2.77 | 6.10 |
| 2-1/2" - 3" | L1@0.10 | Ea | 6.23 | 3.96 | 10.19 |
| 2-1/2" - 4" | L1@0.15 | Ea | 7.39 | 5.94 | 13.33 |




Type LB, LL or LR aluminum conduit bodies with covers

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 10.70 | 3.96 | 14.66 |
| 3/4" | L1@0.15 | Ea | 12.70 | 5.94 | 18.64 |
| 1" | L1@0.15 | Ea | 18.80 | 5.94 | 24.74 |
| 1-1/4" | L1@0.20 | Ea | 29.80 | 7.93 | 37.73 |
| 1-1/2" | L1@0.20 | Ea | 38.70 | 7.93 | 46.63 |
| 2" | L1@0.25 | Ea | 63.90 | 9.91 | 73.81 |
| 2-1/2" | L1@0.30 | Ea | 133.00 | 11.90 | 144.90 |
| 3" | L1@0.40 | Ea | 178.00 | 15.90 | 193.90 |




Type LB, LL or LR mogul aluminum conduit bodies with covers & gaskets

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1" | L1@0.25 | Ea | 80.50 | 9.91 | 90.41 |
| 1-1/4" | L1@0.30 | Ea | 84.50 | 11.90 | 96.40 |
| 1-1/2" | L1@0.30 | Ea | 150.00 | 11.90 | 161.90 |
| 2" | L1@0.50 | Ea | 231.00 | 19.80 | 250.80 |
| 2-1/2" | L1@0.70 | Ea | 354.00 | 27.70 | 381.70 |
| 3" | L1@0.75 | Ea | 538.00 | 29.70 | 567.70 |
| 3-1/2" | L1@1.00 | Ea | 623.00 | 39.60 | 662.60 |
| 4" | L1@1.00 | Ea | 690.00 | 39.60 | 729.60 |




Galvanized capped elbows

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.10 | Ea | 10.60 | 3.96 | 14.56 |
| 3/4" | L1@0.15 | Ea | 15.90 | 5.94 | 21.84 |
| 1" | L1@0.20 | Ea | 19.70 | 7.93 | 27.63 |
| 1-1/4" | L1@0.25 | Ea | 24.00 | 9.91 | 33.91 |
| 1-1/2" | L1@0.25 | Ea | 31.30 | 9.91 | 41.21 |



Use these figures to estimate the cost of conduit body gaskets, aluminum conduit bodies and capped elbows installed with covers and aluminum conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for covers, conduit, nipples, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Standard conduit bodies do not include covers and gaskets. Cost of mogul bodies includes covers and gaskets.

Galvanized Cast Boxes



| Material | | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|---------------|-----------|------|---------------|------------|----------------|
| Galvanized cast boxes with threaded hubs | | | | | | |
| FS-1 | 1/2" one gang | L1@0.20 | Ea | 13.80 | 7.93 | 21.73 |
| FS-2 | 3/4" one gang | L1@0.25 | Ea | 13.70 | 9.91 | 23.61 |
| FS-3 | 1" one gang | L1@0.30 | Ea | 15.70 | 11.90 | 27.60 |
| FS-12 | 1/2" two gang | L1@0.25 | Ea | 23.60 | 9.91 | 33.51 |
| FS-22 | 3/4" two gang | L1@0.30 | Ea | 25.30 | 11.90 | 37.20 |
| FS-32 | 1" two gang | L1@0.35 | Ea | 26.60 | 13.90 | 40.50 |
| FSC-1 | 1/2" one gang | L1@0.25 | Ea | 23.80 | 9.91 | 33.71 |
| FSC-2 | 3/4" one gang | L1@0.30 | Ea | 26.00 | 11.90 | 37.90 |
| FSC-3 | 1" one gang | L1@0.35 | Ea | 32.30 | 13.90 | 46.20 |
| FSC-12 | 1/2" two gang | L1@0.30 | Ea | 29.00 | 11.90 | 40.90 |
| FSC-22 | 3/4" two gang | L1@0.35 | Ea | 26.00 | 13.90 | 39.90 |
| FSC-32 | 1" two gang | L1@0.40 | Ea | 34.60 | 15.90 | 50.50 |
| FSCC-1 | 1/2" one gang | L1@0.35 | Ea | 18.90 | 13.90 | 32.80 |
| FSCC-2 | 3/4" one gang | L1@0.40 | Ea | 32.00 | 15.90 | 47.90 |
| FSCT-1 | 1/2" one gang | L1@0.35 | Ea | 20.60 | 13.90 | 34.50 |
| FSCT-2 | 3/4" one gang | L1@0.40 | Ea | 25.70 | 15.90 | 41.60 |
| FSL-1 | 1/2" one gang | L1@0.30 | Ea | 15.90 | 11.90 | 27.80 |
| FSL-2 | 3/4" one gang | L1@0.35 | Ea | 17.70 | 13.90 | 31.60 |
| FSR-1 | 1/2" one gang | L1@0.30 | Ea | 17.90 | 11.90 | 29.80 |
| FSR-2 | 3/4" one gang | L1@0.35 | Ea | 19.40 | 13.90 | 33.30 |
| FSS-1 | 1/2" one gang | L1@0.35 | Ea | 16.90 | 13.90 | 30.80 |
| FSS-2 | 3/4" one gang | L1@0.40 | Ea | 18.30 | 15.90 | 34.20 |
| FST-1 | 1/2" one gang | L1@0.35 | Ea | 16.90 | 13.90 | 30.80 |
| FST-2 | 3/4" one gang | L1@0.40 | Ea | 18.30 | 15.90 | 34.20 |
| FSX-1 | 1/2" one gang | L1@0.40 | Ea | 15.90 | 15.90 | 31.80 |
| FSX-2 | 3/4" one gang | L1@0.45 | Ea | 17.70 | 17.80 | 35.50 |
| FD-1 | 1/2" one gang | L1@0.25 | Ea | 22.40 | 9.91 | 32.31 |
| FD-2 | 3/4" one gang | L1@0.30 | Ea | 17.40 | 11.90 | 29.30 |
| FD-3 | 1" one gang | L1@0.35 | Ea | 18.60 | 13.90 | 32.50 |
| FDC-1 | 1/2" one gang | L1@0.30 | Ea | 20.90 | 11.90 | 32.80 |
| FDC-2 | 3/4" one gang | L1@0.35 | Ea | 22.60 | 13.90 | 36.50 |
| FDC-3 | 1" one gang | L1@0.40 | Ea | 26.70 | 15.90 | 42.60 |


Use these figures to estimate the cost of galvanized cast boxes installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each box installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include box mounting, layout, material handling, and normal waste. Add for covers, gaskets, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Boxes are raintight or weatherproof when fitted with the proper cover. These figures assume that the boxes are surface mounted in accessible locations.

Covers for Galvanized Cast Boxes

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Single gang stamped metal covers

| | | | | | |
|------------------------|---------|----|------|------|------|
| DS21 single receptacle | L1@0.05 | Ea | 3.82 | 1.98 | 5.80 |
| DS23 duplex receptacle | L1@0.05 | Ea | 3.82 | 1.98 | 5.80 |
| DS32 switch | L1@0.05 | Ea | 3.82 | 1.98 | 5.80 |
| DS100 blank | L1@0.05 | Ea | 3.04 | 1.98 | 5.02 |




Two gang stamped metal covers

| | | | | | |
|--------------------|---------|----|------|------|------|
| S322 2 switches | L1@0.06 | Ea | 6.94 | 2.38 | 9.32 |
| S1002 blank | L1@0.06 | Ea | 6.94 | 2.38 | 9.32 |
| S32212 duplex | L1@0.06 | Ea | 6.94 | 2.38 | 9.32 |
| S32232 Sw & duplex | L1@0.06 | Ea | 6.94 | 2.38 | 9.32 |

Single gang cast metal covers

| | | | | | |
|---------------|---------|----|------|------|-------|
| DS100G switch | L1@0.05 | Ea | 8.31 | 1.98 | 10.29 |
| DS100G blank | L1@0.05 | Ea | 9.33 | 1.98 | 11.31 |




Two gang cast metal covers

| | | | | | |
|------------------|---------|----|-------|------|-------|
| S322G 2 switches | L1@0.06 | Ea | 27.40 | 2.38 | 29.78 |
| S1002G blank | L1@0.06 | Ea | 24.90 | 2.38 | 27.28 |

Single gang cast weatherproof covers

| | | | | | |
|----------------------|---------|----|-------|------|-------|
| DS128 Sw rod type | L1@0.10 | Ea | 31.90 | 3.96 | 35.86 |
| DS181 Sw rocker type | L1@0.10 | Ea | 34.40 | 3.96 | 38.36 |



Two gang cast weatherproof covers

| | | | | | |
|----------------------|---------|----|-------|------|-------|
| DS1282 2 Sw rod type | L1@0.15 | Ea | 58.30 | 5.94 | 64.24 |
|----------------------|---------|----|-------|------|-------|

Single gang cast with hinged cover weatherproof

| | | | | | |
|----------------------|---------|----|-------|------|-------|
| WLRS-1 single recept | L1@0.10 | Ea | 33.00 | 3.96 | 36.96 |
| WLRD-1 duplex recept | L1@0.10 | Ea | 36.30 | 3.96 | 40.26 |




Use these figures to estimate the cost of covers installed on galvanized boxes under the conditions described on pages 5 and 6. Costs listed are for each cover installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the cover, mounting, layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. These figures assume that the boxes for the covers are surface mounted in accessible locations.

Galvanized Cast Expansion Fittings and Jumpers

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Galvanized 4" cast expansion fitting




| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.25 | Ea | 43.40 | 9.91 | 53.31 |
| 3/4" | L1@0.30 | Ea | 44.50 | 11.90 | 56.40 |
| 1" | L1@0.40 | Ea | 54.30 | 15.90 | 70.20 |
| 1-1/4" | L1@0.50 | Ea | 72.20 | 19.80 | 92.00 |
| 1-1/2" | L1@0.50 | Ea | 80.10 | 19.80 | 99.90 |
| 2" | L1@0.60 | Ea | 119.00 | 23.80 | 142.80 |
| 2-1/2" | L1@0.70 | Ea | 236.00 | 27.70 | 263.70 |
| 3" | L1@0.70 | Ea | 235.00 | 27.70 | 262.70 |
| 3-1/2" | L1@0.80 | Ea | 370.00 | 31.70 | 401.70 |
| 4" | L1@1.00 | Ea | 503.00 | 39.60 | 542.60 |

Galvanized 8" cast expansion fitting




| | | | | | |
|--------|---------|----|----------|-------|----------|
| 1/2" | L1@0.30 | Ea | 88.40 | 11.90 | 100.30 |
| 3/4" | L1@0.40 | Ea | 96.90 | 15.90 | 112.80 |
| 1" | L1@0.50 | Ea | 129.00 | 19.80 | 148.80 |
| 1-1/4" | L1@0.60 | Ea | 157.00 | 23.80 | 180.80 |
| 1-1/2" | L1@0.60 | Ea | 238.00 | 23.80 | 261.80 |
| 2" | L1@0.70 | Ea | 333.00 | 27.70 | 360.70 |
| 2-1/2" | L1@0.80 | Ea | 564.00 | 31.70 | 595.70 |
| 3" | L1@1.00 | Ea | 690.00 | 39.60 | 729.60 |
| 3-1/2" | L1@1.25 | Ea | 944.00 | 49.50 | 993.50 |
| 4" | L1@1.30 | Ea | 1,040.00 | 51.50 | 1,091.50 |

4" bonding jumpers for galvanized cast expansion fitting



| | | | | | |
|-------------|---------|----|--------|-------|--------|
| 1/2" - 3/4" | L1@0.15 | Ea | 49.90 | 5.94 | 55.84 |
| 1" - 1-1/4" | L1@0.20 | Ea | 50.70 | 7.93 | 58.63 |
| 1-1/2" - 2" | L1@0.30 | Ea | 62.60 | 11.90 | 74.50 |
| 2-1/2" - 3" | L1@0.40 | Ea | 66.30 | 15.90 | 82.20 |
| 3-1/2" - 4" | L1@0.50 | Ea | 137.00 | 19.80 | 156.80 |

8" bonding jumpers for galvanized cast expansion fitting



| | | | | | |
|-------------|---------|----|--------|-------|--------|
| 1/2" - 3/4" | L1@0.15 | Ea | 52.20 | 5.94 | 58.14 |
| 1" - 1-1/4" | L1@0.25 | Ea | 60.50 | 9.91 | 70.41 |
| 1-1/2" - 2" | L1@0.35 | Ea | 72.50 | 13.90 | 86.40 |
| 2-1/2" - 3" | L1@0.45 | Ea | 99.50 | 17.80 | 117.30 |
| 3-1/2" - 4" | L1@0.60 | Ea | 102.00 | 23.80 | 125.80 |
| 5" | L1@0.80 | Ea | 145.00 | 31.70 | 176.70 |

Use these figures to estimate the cost of expansion fittings and bonding jumpers installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for conduit, supports, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: These fittings are installed at construction expansion joints and are suitable for installation in concrete. The bonding jumper provides grounding continuity.



Reducing Bushings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|---|-----------|------|---------------|------------|----------------|
| Steel or malleable reducing bushings | | | | | |
| 3/4" - 1/2" | L1@0.05 | Ea | .92 | 1.98 | 2.90 |
| 1" - 1/2" | L1@0.05 | Ea | 1.37 | 1.98 | 3.35 |
| 1" - 3/4" | L1@0.05 | Ea | 1.37 | 1.98 | 3.35 |
| 1-1/4" - 1/2" | L1@0.06 | Ea | 2.40 | 2.38 | 4.78 |
| 1-1/4" - 3/4" | L1@0.06 | Ea | 2.40 | 2.38 | 4.78 |
| 1-1/4" - 1" | L1@0.06 | Ea | 2.40 | 2.38 | 4.78 |
| 1-1/2" - 1/2" | L1@0.08 | Ea | 3.10 | 3.17 | 6.27 |
| 1-1/2" - 3/4" | L1@0.08 | Ea | 3.10 | 3.17 | 6.27 |
| 1-1/2" - 1" | L1@0.08 | Ea | 3.10 | 3.17 | 6.27 |
| 1-1/2" - 1-1/4" | L1@0.08 | Ea | 3.10 | 3.17 | 6.27 |
| 2" - 1/2" | L1@0.10 | Ea | 6.61 | 3.96 | 10.57 |
| 2" - 3/4" | L1@0.10 | Ea | 6.61 | 3.96 | 10.57 |
| 2" - 1" | L1@0.10 | Ea | 8.23 | 3.96 | 12.19 |
| 2" - 1-1/4" | L1@0.10 | Ea | 6.02 | 3.96 | 9.98 |
| 2" - 1-1/2" | L1@0.10 | Ea | 6.61 | 3.96 | 10.57 |
| 2-1/2" - 1-1/2" | L1@0.15 | Ea | 10.40 | 5.94 | 16.34 |
| 2-1/2" - 2" | L1@0.15 | Ea | 10.40 | 5.94 | 16.34 |
| 3" - 2-1/2" | L1@0.20 | Ea | 28.20 | 7.93 | 36.13 |
| 3-1/2" - 2" | L1@0.25 | Ea | 28.20 | 9.91 | 38.11 |
| 3-1/2" - 2-1/2" | L1@0.25 | Ea | 28.20 | 9.91 | 38.11 |
| 3-1/2" - 3" | L1@0.25 | Ea | 31.00 | 9.91 | 40.91 |
| 4" - 2-1/2" | L1@0.30 | Ea | 24.90 | 11.90 | 36.80 |
| 4" - 3" | L1@0.30 | Ea | 24.90 | 11.90 | 36.80 |
| 4" - 3-1/2" | L1@0.30 | Ea | 22.90 | 11.90 | 34.80 |

Aluminum reducing bushings

| | | | | | |
|-----------------|---------|----|-------|------|-------|
| 3/4" - 1/2" | L1@0.05 | Ea | 2.99 | 1.98 | 4.97 |
| 1" - 1/2" | L1@0.05 | Ea | 3.01 | 1.98 | 4.99 |
| 1" - 3/4" | L1@0.05 | Ea | 3.01 | 1.98 | 4.99 |
| 1-1/4" - 1/2" | L1@0.06 | Ea | 5.89 | 2.38 | 8.27 |
| 1-1/4" - 3/4" | L1@0.06 | Ea | 5.86 | 2.38 | 8.24 |
| 1-1/4" - 1" | L1@0.06 | Ea | 6.50 | 2.38 | 8.88 |
| 1-1/2" - 1/2" | L1@0.08 | Ea | 9.86 | 3.17 | 13.03 |
| 1-1/2" - 3/4" | L1@0.08 | Ea | 9.86 | 3.17 | 13.03 |
| 1-1/2" - 1" | L1@0.08 | Ea | 9.86 | 3.17 | 13.03 |
| 1-1/2" - 1-1/4" | L1@0.08 | Ea | 9.86 | 3.17 | 13.03 |
| 2" - 1/2" | L1@0.10 | Ea | 13.20 | 3.96 | 17.16 |
| 2" - 3/4" | L1@0.10 | Ea | 13.20 | 3.96 | 17.16 |
| 2" - 1" | L1@0.10 | Ea | 13.20 | 3.96 | 17.16 |
| 2" - 1-1/4" | L1@0.10 | Ea | 13.20 | 3.96 | 17.16 |
| 2" - 1-1/2" | L1@0.10 | Ea | 13.20 | 3.96 | 17.16 |

Use these figures to estimate the cost of reducing bushings installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each bushing installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full boxes. These bushings are used to reduce the threaded hub size in cast boxes when smaller conduit is used.



Reducing Bushings and Reducing Washers

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|-----------------------------------|-----------|------|---------------|------------|----------------|
| Aluminum reducing bushings | | | | | |
| 2-1/2" - 1" | L1@0.15 | Ea | 12.60 | 5.94 | 18.54 |
| 2-1/2" - 1-1/4" | L1@0.15 | Ea | 12.60 | 5.94 | 18.54 |
| 2-1/2" - 1-1/2" | L1@0.15 | Ea | 12.60 | 5.94 | 18.54 |
| 2-1/2" - 2" | L1@0.15 | Ea | 12.60 | 5.94 | 18.54 |
| 3" - 1-1/4" | L1@0.20 | Ea | 26.00 | 7.93 | 33.93 |
| 3" - 1-1/2" | L1@0.20 | Ea | 26.00 | 7.93 | 33.93 |
| 3" - 2" | L1@0.20 | Ea | 26.00 | 7.93 | 33.93 |
| 3" - 2-1/2" | L1@0.20 | Ea | 26.00 | 7.93 | 33.93 |
| 3-1/2" - 2" | L1@0.25 | Ea | 28.80 | 9.91 | 38.71 |
| 3-1/2" - 2-1/2" | L1@0.25 | Ea | 28.80 | 9.91 | 38.71 |
| 3-1/2" - 3" | L1@0.25 | Ea | 28.80 | 9.91 | 38.71 |
| 4" - 2" | L1@0.30 | Ea | 44.50 | 11.90 | 56.40 |
| 4" - 2-1/2" | L1@0.30 | Ea | 44.50 | 11.90 | 56.40 |
| 4" - 3" | L1@0.30 | Ea | 44.50 | 11.90 | 56.40 |
| 4" - 3-1/2" | L1@0.30 | Ea | 44.50 | 11.90 | 56.40 |

Steel reducing washers, set of 2

| | | | | | |
|-----------------|---------|----|-------|-------|-------|
| 3/4" - 1/2" | L1@0.05 | Pr | .26 | 1.98 | 2.24 |
| 1" - 1/2" | L1@0.06 | Pr | .40 | 2.38 | 2.78 |
| 1" - 3/4" | L1@0.06 | Pr | .37 | 2.38 | 2.75 |
| 1-1/4" - 1/2" | L1@0.08 | Pr | .71 | 3.17 | 3.88 |
| 1-1/4" - 3/4" | L1@0.08 | Pr | .64 | 3.17 | 3.81 |
| 1-1/4" - 1" | L1@0.08 | Pr | .66 | 3.17 | 3.83 |
| 1-1/2" - 1/2" | L1@0.10 | Pr | .82 | 3.96 | 4.78 |
| 1-1/2" - 3/4" | L1@0.10 | Pr | .92 | 3.96 | 4.88 |
| 1-1/2" - 1" | L1@0.10 | Pr | .77 | 3.96 | 4.73 |
| 1-1/2" - 1-1/4" | L1@0.10 | Pr | .78 | 3.96 | 4.74 |
| 2" - 1/2" | L1@0.15 | Pr | 1.34 | 5.94 | 7.28 |
| 2" - 3/4" | L1@0.15 | Pr | 1.18 | 5.94 | 7.12 |
| 2" - 1" | L1@0.15 | Pr | 1.11 | 5.94 | 7.05 |
| 2" - 1-1/4" | L1@0.15 | Pr | 1.11 | 5.94 | 7.05 |
| 2" - 1-1/2" | L1@0.15 | Pr | 1.11 | 5.94 | 7.05 |
| 2-1/2" - 1" | L1@0.20 | Pr | 1.46 | 7.93 | 9.39 |
| 2-1/2" - 1-1/4" | L1@0.20 | Pr | 1.46 | 7.93 | 9.39 |
| 2-1/2" - 1-1/2" | L1@0.20 | Pr | 1.46 | 7.93 | 9.39 |
| 2-1/2" - 2" | L1@0.20 | Pr | 1.46 | 7.93 | 9.39 |
| 3" - 1-1/4" | L1@0.25 | Pr | 1.84 | 9.91 | 11.75 |
| 3" - 1-1/2" | L1@0.25 | Pr | 1.84 | 9.91 | 11.75 |
| 3" - 2" | L1@0.25 | Pr | 1.84 | 9.91 | 11.75 |
| 3" - 2-1/2" | L1@0.25 | Pr | 1.84 | 9.91 | 11.75 |
| 3-1/2" - 2" | L1@0.30 | Pr | 5.30 | 11.90 | 17.20 |
| 3-1/2" - 2-1/2" | L1@0.30 | Pr | 5.30 | 11.90 | 17.20 |
| 3-1/2" - 3" | L1@0.30 | Pr | 5.30 | 11.90 | 17.20 |
| 4" - 2" | L1@0.35 | Pr | 15.00 | 13.90 | 28.90 |
| 4" - 2-1/2" | L1@0.35 | Pr | 15.00 | 13.90 | 28.90 |
| 4" - 3" | L1@0.35 | Pr | 15.00 | 13.90 | 28.90 |
| 4" - 3-1/2" | L1@0.35 | Pr | 15.00 | 13.90 | 28.90 |

Use these figures to estimate the cost of reducing bushings and reducing washers installed on conduit under the conditions described on pages 5 and 6. Costs for bushings are for each bushing installed. Costs for reducing washers are per pair of washers installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full boxes. These bushings are used to reduce the threaded hub size in cast boxes when smaller conduit is used.

Bushed Nipples

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|--------------------------------|-----------|------|---------------|------------|----------------|
| Die cast bushed nipples | | | | | |
| 1/2" | L1@0.05 | Ea | .23 | 1.98 | 2.21 |
| 3/4" | L1@0.06 | Ea | .42 | 2.38 | 2.80 |
| 1" | L1@0.08 | Ea | .79 | 3.17 | 3.96 |
| 1-1/4" | L1@0.10 | Ea | 1.21 | 3.96 | 5.17 |
| 1-1/2" | L1@0.10 | Ea | 1.70 | 3.96 | 5.66 |
| 2" | L1@0.15 | Ea | 2.64 | 5.94 | 8.58 |
| 2-1/2" | L1@0.20 | Ea | 4.30 | 7.93 | 12.23 |
| 3" | L1@0.20 | Ea | 7.00 | 7.93 | 14.93 |
| 3-1/2" | L1@0.25 | Ea | 12.00 | 9.91 | 21.91 |
| 4" | L1@0.25 | Ea | 12.60 | 9.91 | 22.51 |



Malleable bushed nipples

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .58 | 1.98 | 2.56 |
| 3/4" | L1@0.06 | Ea | 1.11 | 2.38 | 3.49 |
| 1" | L1@0.08 | Ea | 2.01 | 3.17 | 5.18 |
| 1-1/4" | L1@0.10 | Ea | 1.96 | 3.96 | 5.92 |
| 1-1/2" | L1@0.10 | Ea | 2.09 | 3.96 | 6.05 |
| 2" | L1@0.15 | Ea | 2.77 | 5.94 | 8.71 |
| 2-1/2" | L1@0.20 | Ea | 5.07 | 7.93 | 13.00 |
| 3" | L1@0.20 | Ea | 10.40 | 7.93 | 18.33 |
| 3-1/2" | L1@0.25 | Ea | 16.20 | 9.91 | 26.11 |
| 4" | L1@0.25 | Ea | 26.20 | 9.91 | 36.11 |




Insulated die cast bushed nipples

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .26 | 1.98 | 2.24 |
| 3/4" | L1@0.06 | Ea | .48 | 2.38 | 2.86 |
| 1" | L1@0.08 | Ea | .89 | 3.17 | 4.06 |
| 1-1/4" | L1@0.10 | Ea | 1.35 | 3.96 | 5.31 |
| 1-1/2" | L1@0.10 | Ea | 1.89 | 3.96 | 5.85 |
| 2" | L1@0.15 | Ea | 2.95 | 5.94 | 8.89 |
| 2-1/2" | L1@0.20 | Ea | 4.77 | 7.93 | 12.70 |
| 3" | L1@0.20 | Ea | 7.79 | 7.93 | 15.72 |
| 3-1/2" | L1@0.25 | Ea | 13.40 | 9.91 | 23.31 |
| 4" | L1@0.25 | Ea | 15.00 | 9.91 | 24.91 |



Insulated malleable bushed nipples

| | | | | | |
|--------|---------|----|------|------|-------|
| 1/2" | L1@0.05 | Ea | .53 | 1.98 | 2.51 |
| 3/4" | L1@0.06 | Ea | .99 | 2.38 | 3.37 |
| 1" | L1@0.08 | Ea | 1.84 | 3.17 | 5.01 |
| 1-1/4" | L1@0.10 | Ea | 2.77 | 3.96 | 6.73 |
| 1-1/2" | L1@0.10 | Ea | 3.68 | 3.96 | 7.64 |
| 2" | L1@0.15 | Ea | 4.88 | 5.94 | 10.82 |




Use these figures to estimate the cost of bushed nipples installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each nipple installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for locknut, bushing, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full boxes. Bushed nipples are often used in threaded hubs.

Bushed Nipples, Couplings and Offset Nipples


| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Insulated malleable bushed nipples




| | | | | | |
|--------|---------|----|--------|-------|--------|
| 2-1/2" | L1@0.20 | Ea | 6.34 | 7.93 | 14.27 |
| 3" | L1@0.20 | Ea | 20.10 | 7.93 | 28.03 |
| 3-1/2" | L1@0.25 | Ea | 28.30 | 9.91 | 38.21 |
| 4" | L1@0.25 | Ea | 44.50 | 9.91 | 54.41 |
| 5" | L1@0.30 | Ea | 135.00 | 11.90 | 146.90 |
| 6" | L1@0.40 | Ea | 204.00 | 15.90 | 219.90 |

Malleable three-piece couplings or unions



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 3.02 | 3.96 | 6.98 |
| 3/4" | L1@0.10 | Ea | 4.92 | 3.96 | 8.88 |
| 1" | L1@0.15 | Ea | 7.52 | 5.94 | 13.46 |
| 1-1/4" | L1@0.20 | Ea | 13.50 | 7.93 | 21.43 |
| 1-1/2" | L1@0.20 | Ea | 16.70 | 7.93 | 24.63 |
| 2" | L1@0.25 | Ea | 32.90 | 9.91 | 42.81 |
| 2-1/2" | L1@0.30 | Ea | 79.50 | 11.90 | 91.40 |
| 3" | L1@0.30 | Ea | 109.00 | 11.90 | 120.90 |
| 3-1/2" | L1@0.50 | Ea | 184.00 | 19.80 | 203.80 |
| 4" | L1@0.50 | Ea | 225.00 | 19.80 | 244.80 |
| 5" | L1@1.00 | Ea | 329.00 | 39.60 | 368.60 |
| 6" | L1@1.25 | Ea | 502.00 | 49.50 | 551.50 |

Malleable offset nipples



| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.10 | Ea | 6.14 | 3.96 | 10.10 |
| 3/4" | L1@0.10 | Ea | 6.49 | 3.96 | 10.45 |
| 1" | L1@0.15 | Ea | 8.05 | 5.94 | 13.99 |
| 1-1/4" | L1@0.20 | Ea | 18.10 | 7.93 | 26.03 |
| 1-1/2" | L1@0.20 | Ea | 22.20 | 7.93 | 30.13 |
| 2" | L1@0.25 | Ea | 35.20 | 9.91 | 45.11 |

Die cast offset nipples



| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.10 | Ea | 2.24 | 3.96 | 6.20 |
| 3/4" | L1@0.15 | Ea | 3.14 | 5.94 | 9.08 |
| 1" | L1@0.20 | Ea | 4.02 | 7.93 | 11.95 |
| 1-1/4" | L1@0.25 | Ea | 5.79 | 9.91 | 15.70 |
| 1-1/2" | L1@0.25 | Ea | 7.25 | 9.91 | 17.16 |
| 2" | L1@0.30 | Ea | 15.40 | 11.90 | 27.30 |


Use these figures to estimate the cost of bushed nipples, unions, and offset nipples installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for locknut, bushing, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full boxes. Three-piece couplings are made to fit the flat thread used on electrical fittings. Unions made for plumbing pipe should not be used in electrical systems.

Offset Nipples, Connectors and Couplings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Die cast offset nipples (continued)

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 2-1/2" | L1@0.35 | Ea | 56.80 | 13.90 | 70.70 |
| 3" | L1@0.35 | Ea | 71.00 | 13.90 | 84.90 |
| 3-1/2" | L1@0.40 | Ea | 104.00 | 15.90 | 119.90 |
| 4" | L1@0.45 | Ea | 128.00 | 17.80 | 145.80 |




Malleable threadless connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 1.67 | 1.98 | 3.65 |
| 3/4" | L1@0.06 | Ea | 2.75 | 2.38 | 5.13 |
| 1" | L1@0.08 | Ea | 3.89 | 3.17 | 7.06 |
| 1-1/4" | L1@0.10 | Ea | 7.73 | 3.96 | 11.69 |
| 1-1/2" | L1@0.10 | Ea | 10.70 | 3.96 | 14.66 |
| 2" | L1@0.15 | Ea | 21.00 | 5.94 | 26.94 |
| 2-1/2" | L1@0.25 | Ea | 99.50 | 9.91 | 109.41 |
| 3" | L1@0.30 | Ea | 132.00 | 11.90 | 143.90 |
| 3-1/2" | L1@0.35 | Ea | 173.00 | 13.90 | 186.90 |
| 4" | L1@0.40 | Ea | 212.00 | 15.90 | 227.90 |




Insulated malleable threadless connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 3.87 | 1.98 | 5.85 |
| 3/4" | L1@0.06 | Ea | 6.19 | 2.38 | 8.57 |
| 1" | L1@0.08 | Ea | 9.18 | 3.17 | 12.35 |
| 1-1/4" | L1@0.10 | Ea | 17.50 | 3.96 | 21.46 |
| 1-1/2" | L1@0.10 | Ea | 24.30 | 3.96 | 28.26 |
| 2" | L1@0.15 | Ea | 56.80 | 5.94 | 62.74 |
| 2-1/2" | L1@0.25 | Ea | 139.00 | 9.91 | 148.91 |
| 3" | L1@0.30 | Ea | 184.00 | 11.90 | 195.90 |
| 3-1/2" | L1@0.35 | Ea | 238.00 | 13.90 | 251.90 |
| 4" | L1@0.40 | Ea | 281.00 | 15.90 | 296.90 |



Malleable threadless couplings

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.10 | Ea | 2.64 | 3.96 | 6.60 |
| 3/4" | L1@0.10 | Ea | 4.06 | 3.96 | 8.02 |
| 1" | L1@0.15 | Ea | 6.81 | 5.94 | 12.75 |
| 1-1/4" | L1@0.20 | Ea | 11.30 | 7.93 | 19.23 |
| 1-1/2" | L1@0.20 | Ea | 14.20 | 7.93 | 22.13 |
| 2" | L1@0.25 | Ea | 31.70 | 9.91 | 41.61 |




Use these figures to estimate the cost of offset nipples, connectors, and couplings installed in conduit systems under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include removing the knockout, layout, material handling, and normal waste. Add for locknuts, bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material costs are based on purchase of full boxes. Threadless fittings are made for rigid conduit only and do not fit EMT conduit. They're rated for raintight or weatherproof applications.

Couplings and Connectors


| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Malleable threadless couplings (continued)




| | | | | | |
|--------|---------|----|--------|-------|--------|
| 2-1/2" | L1@0.30 | Ea | 138.00 | 11.90 | 149.90 |
| 3" | L1@0.40 | Ea | 190.00 | 15.90 | 205.90 |
| 3-1/2" | L1@0.50 | Ea | 244.00 | 19.80 | 263.80 |
| 4" | L1@0.60 | Ea | 320.00 | 23.80 | 343.80 |

Malleable set screw couplings




| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 3.05 | 3.96 | 7.01 |
| 3/4" | L1@0.10 | Ea | 4.13 | 3.96 | 8.09 |
| 1" | L1@0.15 | Ea | 7.01 | 5.94 | 12.95 |
| 1-1/4" | L1@0.20 | Ea | 10.10 | 7.93 | 18.03 |
| 1-1/2" | L1@0.20 | Ea | 13.00 | 7.93 | 20.93 |
| 2" | L1@0.25 | Ea | 29.20 | 9.91 | 39.11 |
| 2-1/2" | L1@0.30 | Ea | 60.90 | 11.90 | 72.80 |
| 3" | L1@0.40 | Ea | 73.10 | 15.90 | 89.00 |
| 3-1/2" | L1@0.50 | Ea | 96.10 | 19.80 | 115.90 |
| 4" | L1@0.60 | Ea | 122.00 | 23.80 | 145.80 |

Steel set screw connectors



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 3.00 | 1.98 | 4.98 |
| 3/4" | L1@0.06 | Ea | 3.61 | 2.38 | 5.99 |
| 1" | L1@0.08 | Ea | 4.80 | 3.17 | 7.97 |
| 1-1/4" | L1@0.10 | Ea | 8.67 | 3.96 | 12.63 |
| 1-1/2" | L1@0.10 | Ea | 12.70 | 3.96 | 16.66 |
| 2" | L1@0.15 | Ea | 19.20 | 5.94 | 25.14 |
| 2-1/2" | L1@0.25 | Ea | 69.00 | 9.91 | 78.91 |
| 3" | L1@0.30 | Ea | 88.40 | 11.90 | 100.30 |
| 3-1/2" | L1@0.35 | Ea | 132.00 | 13.90 | 145.90 |
| 4" | L1@0.40 | Ea | 164.00 | 15.90 | 179.90 |

Insulated steel set screw connectors



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 3.15 | 1.98 | 5.13 |
| 3/4" | L1@0.06 | Ea | 3.81 | 2.38 | 6.19 |
| 1" | L1@0.08 | Ea | 4.94 | 3.17 | 8.11 |
| 1-1/4" | L1@0.10 | Ea | 8.84 | 3.96 | 12.80 |
| 1-1/2" | L1@0.10 | Ea | 12.80 | 3.96 | 16.76 |
| 2" | L1@0.15 | Ea | 21.00 | 5.94 | 26.94 |
| 2-1/2" | L1@0.25 | Ea | 71.10 | 9.91 | 81.01 |
| 3" | L1@0.30 | Ea | 91.80 | 11.90 | 103.70 |
| 3-1/2" | L1@0.35 | Ea | 141.00 | 13.90 | 154.90 |
| 4" | L1@0.40 | Ea | 185.00 | 15.90 | 200.90 |


Use these figures to estimate the cost of couplings and connectors installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include removing the knockout, the locknut, layout, material handling, and normal waste. Add for bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full boxes.

Connectors and Straps

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Malleable set screw connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 2.20 | 1.98 | 4.18 |
| 3/4" | L1@0.06 | Ea | 3.05 | 2.38 | 5.43 |
| 1" | L1@0.08 | Ea | 4.91 | 3.17 | 8.08 |
| 1-1/4" | L1@0.10 | Ea | 8.50 | 3.96 | 12.46 |
| 1-1/2" | L1@0.10 | Ea | 12.30 | 3.96 | 16.26 |
| 2" | L1@0.15 | Ea | 24.50 | 5.94 | 30.44 |
| 2-1/2" | L1@0.25 | Ea | 71.60 | 9.91 | 81.51 |
| 3" | L1@0.30 | Ea | 95.20 | 11.90 | 107.10 |
| 3-1/2" | L1@0.35 | Ea | 131.00 | 13.90 | 144.90 |
| 4" | L1@0.40 | Ea | 160.00 | 15.90 | 175.90 |



Insulated malleable set screw connectors

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 3.60 | 1.98 | 5.58 |
| 3/4" | L1@0.06 | Ea | 4.35 | 2.38 | 6.73 |
| 1" | L1@0.08 | Ea | 7.03 | 3.17 | 10.20 |
| 1-1/4" | L1@0.10 | Ea | 9.95 | 3.96 | 13.91 |
| 1-1/2" | L1@0.10 | Ea | 15.60 | 3.96 | 19.56 |
| 2" | L1@0.15 | Ea | 26.40 | 5.94 | 32.34 |
| 2-1/2" | L1@0.25 | Ea | 78.80 | 9.91 | 88.71 |
| 3" | L1@0.30 | Ea | 111.00 | 11.90 | 122.90 |
| 3-1/2" | L1@0.35 | Ea | 139.00 | 13.90 | 152.90 |
| 4" | L1@0.40 | Ea | 174.00 | 15.90 | 189.90 |



Steel one hole straps

| | | | | | |
|--------|---------|----|------|------|-------|
| 1/2" | L1@0.05 | Ea | .13 | 1.98 | 2.11 |
| 3/4" | L1@0.06 | Ea | .19 | 2.38 | 2.57 |
| 1" | L1@0.08 | Ea | .29 | 3.17 | 3.46 |
| 1-1/4" | L1@0.10 | Ea | .43 | 3.96 | 4.39 |
| 1-1/2" | L1@0.10 | Ea | .65 | 3.96 | 4.61 |
| 2" | L1@0.10 | Ea | .82 | 3.96 | 4.78 |
| 2-1/2" | L1@0.15 | Ea | 1.45 | 5.94 | 7.39 |
| 3" | L1@0.20 | Ea | 1.75 | 7.93 | 9.68 |
| 3-1/2" | L1@0.20 | Ea | 2.30 | 7.93 | 10.23 |
| 4" | L1@0.20 | Ea | 2.93 | 7.93 | 10.86 |



Malleable one hole straps

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .26 | 1.98 | 2.24 |
| 3/4" | L1@0.06 | Ea | .36 | 2.38 | 2.74 |
| 1" | L1@0.08 | Ea | .58 | 3.17 | 3.75 |
| 1-1/4" | L1@0.10 | Ea | .83 | 3.96 | 4.79 |
| 1-1/2" | L1@0.10 | Ea | 1.21 | 3.96 | 5.17 |
| 2" | L1@0.10 | Ea | 1.93 | 3.96 | 5.89 |
| 2-1/2" | L1@0.15 | Ea | 3.76 | 5.94 | 9.70 |
| 3" | L1@0.20 | Ea | 5.65 | 7.93 | 13.58 |
| 3-1/2" | L1@0.20 | Ea | 8.47 | 7.93 | 16.40 |
| 4" | L1@0.25 | Ea | 15.40 | 9.91 | 25.31 |



Use these figures to estimate the cost of connectors and straps installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include removing the knockout, the locknut, layout, material handling, and normal waste. Add for bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full boxes.

Straps and Spacers

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

Steel two hole straps

| | | | | | |
|--------|---------|----|------|------|-------|
| 1/2" | L1@0.05 | Ea | .12 | 1.98 | 2.10 |
| 3/4" | L1@0.06 | Ea | .17 | 2.38 | 2.55 |
| 1" | L1@0.08 | Ea | .27 | 3.17 | 3.44 |
| 1-1/4" | L1@0.10 | Ea | .37 | 3.96 | 4.33 |
| 1-1/2" | L1@0.10 | Ea | .48 | 3.96 | 4.44 |
| 2" | L1@0.10 | Ea | .68 | 3.96 | 4.64 |
| 2-1/2" | L1@0.15 | Ea | 1.57 | 5.94 | 7.51 |
| 3" | L1@0.20 | Ea | 2.21 | 7.93 | 10.14 |
| 3-1/2" | L1@0.25 | Ea | 3.03 | 9.91 | 12.94 |
| 4" | L1@0.25 | Ea | 3.10 | 9.91 | 13.01 |

Aluminum one hole straps

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .76 | 1.98 | 2.74 |
| 3/4" | L1@0.06 | Ea | 1.11 | 2.38 | 3.49 |
| 1" | L1@0.08 | Ea | 1.65 | 3.17 | 4.82 |
| 1-1/4" | L1@0.10 | Ea | 3.06 | 3.96 | 7.02 |
| 1-1/2" | L1@0.10 | Ea | 3.19 | 3.96 | 7.15 |
| 2" | L1@0.10 | Ea | 6.55 | 3.96 | 10.51 |
| 2-1/2" | L1@0.15 | Ea | 13.00 | 5.94 | 18.94 |
| 3" | L1@0.20 | Ea | 18.40 | 7.93 | 26.33 |
| 3-1/2" | L1@0.20 | Ea | 24.20 | 7.93 | 32.13 |
| 4" | L1@0.25 | Ea | 28.60 | 9.91 | 38.51 |

Malleable clamp backs

| | | | | | |
|--------|---------|----|-------|------|-------|
| 1/2" | L1@0.05 | Ea | .36 | 1.98 | 2.34 |
| 3/4" | L1@0.05 | Ea | .40 | 1.98 | 2.38 |
| 1" | L1@0.05 | Ea | .60 | 1.98 | 2.58 |
| 1-1/4" | L1@0.10 | Ea | .91 | 3.96 | 4.87 |
| 1-1/2" | L1@0.10 | Ea | 1.17 | 3.96 | 5.13 |
| 2" | L1@0.10 | Ea | 1.90 | 3.96 | 5.86 |
| 2-1/2" | L1@0.15 | Ea | 4.56 | 5.94 | 10.50 |
| 3" | L1@0.15 | Ea | 7.17 | 5.94 | 13.11 |
| 3-1/2" | L1@0.20 | Ea | 23.70 | 7.93 | 31.63 |
| 4" | L1@0.20 | Ea | 32.50 | 7.93 | 40.43 |
| 5" | L1@0.25 | Ea | 81.40 | 9.91 | 91.31 |
| 6" | L1@0.25 | Ea | 82.90 | 9.91 | 92.81 |


Use these figures to estimate the cost of straps and spacers installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for screws, bolts, anchors, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full boxes.

Conduit Clamps and Entrance Caps

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


Rigid steel conduit clamps without bolts

| | | | | | |
|--------|---------|----|------|------|-------|
| 1/2" | L1@0.05 | Ea | .37 | 1.98 | 2.35 |
| 3/4" | L1@0.06 | Ea | .41 | 2.38 | 2.79 |
| 1" | L1@0.08 | Ea | .64 | 3.17 | 3.81 |
| 1-1/4" | L1@0.10 | Ea | .78 | 3.96 | 4.74 |
| 1-1/2" | L1@0.10 | Ea | .81 | 3.96 | 4.77 |
| 2" | L1@0.10 | Ea | 1.05 | 3.96 | 5.01 |
| 2-1/2" | L1@0.15 | Ea | 1.56 | 5.94 | 7.50 |
| 3" | L1@0.15 | Ea | 1.77 | 5.94 | 7.71 |
| 3-1/2" | L1@0.20 | Ea | 2.24 | 7.93 | 10.17 |
| 4" | L1@0.20 | Ea | 2.66 | 7.93 | 10.59 |




Rigid steel conduit clamps with bolts

| | | | | | |
|--------|---------|----|------|------|-------|
| 1/2" | L1@0.05 | Ea | .48 | 1.98 | 2.46 |
| 3/4" | L1@0.06 | Ea | .52 | 2.38 | 2.90 |
| 1" | L1@0.08 | Ea | .74 | 3.17 | 3.91 |
| 1-1/4" | L1@0.10 | Ea | .99 | 3.96 | 4.95 |
| 1-1/2" | L1@0.10 | Ea | 1.20 | 3.96 | 5.16 |
| 2" | L1@0.10 | Ea | 1.35 | 3.96 | 5.31 |
| 2-1/2" | L1@0.15 | Ea | 1.96 | 5.94 | 7.90 |
| 3" | L1@0.15 | Ea | 1.98 | 5.94 | 7.92 |
| 3-1/2" | L1@0.20 | Ea | 2.33 | 7.93 | 10.26 |
| 4" | L1@0.20 | Ea | 2.86 | 7.93 | 10.79 |




Clamp-type entrance caps

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.15 | Ea | 8.41 | 5.94 | 14.35 |
| 3/4" | L1@0.20 | Ea | 9.86 | 7.93 | 17.79 |
| 1" | L1@0.25 | Ea | 11.60 | 9.91 | 21.51 |
| 1-1/4" | L1@0.30 | Ea | 13.10 | 11.90 | 25.00 |
| 1-1/2" | L1@0.30 | Ea | 22.20 | 11.90 | 34.10 |
| 2" | L1@0.50 | Ea | 30.30 | 19.80 | 50.10 |
| 2-1/2" | L1@0.60 | Ea | 107.00 | 23.80 | 130.80 |
| 3" | L1@0.75 | Ea | 171.00 | 29.70 | 200.70 |
| 3-1/2" | L1@1.00 | Ea | 210.00 | 39.60 | 249.60 |
| 4" | L1@1.25 | Ea | 220.00 | 49.50 | 269.50 |



Slip fitter entrance caps

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.15 | Ea | 7.17 | 5.94 | 13.11 |
| 3/4" | L1@0.20 | Ea | 8.93 | 7.93 | 16.86 |
| 1" | L1@0.25 | Ea | 10.50 | 9.91 | 20.41 |
| 1-1/4" | L1@0.30 | Ea | 12.80 | 11.90 | 24.70 |
| 1-1/2" | L1@0.30 | Ea | 22.90 | 11.90 | 34.80 |
| 2" | L1@0.50 | Ea | 42.10 | 19.80 | 61.90 |



Use these figures to estimate the cost of clamps and entrance caps installed on conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for screws, bolts, anchors, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: Material cost is based on purchase of full boxes. Many other types of fittings are available. Those listed here are the most common.

PVC Coated Conduit, Elbows and Couplings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

PVC coated steel conduit, 40 mil coating

| | | | | | |
|--------|---------|-----|----------|--------|----------|
| 1/2" | L1@4.50 | CLF | 392.00 | 178.00 | 570.00 |
| 3/4" | L1@5.50 | CLF | 455.00 | 218.00 | 673.00 |
| 1" | L1@7.00 | CLF | 590.00 | 277.00 | 867.00 |
| 1-1/4" | L1@9.00 | CLF | 981.00 | 357.00 | 1,338.00 |
| 1-1/2" | L1@11.0 | CLF | 909.00 | 436.00 | 1,345.00 |
| 2" | L1@13.0 | CLF | 1,180.00 | 515.00 | 1,695.00 |
| 2-1/2" | L2@15.0 | CLF | 2,350.00 | 594.00 | 2,944.00 |
| 3" | L2@17.0 | CLF | 2,270.00 | 674.00 | 2,944.00 |
| 3-1/2" | L2@19.0 | CLF | 3,640.00 | 753.00 | 4,393.00 |
| 4" | L2@21.0 | CLF | 3,270.00 | 832.00 | 4,102.00 |
| 5" | L2@25.0 | CLF | 7,590.00 | 991.00 | 8,581.00 |

PVC coated steel 90 degree elbows

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 19.00 | 3.96 | 22.96 |
| 3/4" | L1@0.10 | Ea | 19.80 | 3.96 | 23.76 |
| 1" | L1@0.15 | Ea | 13.90 | 5.94 | 19.84 |
| 1-1/4" | L1@0.20 | Ea | 27.90 | 7.93 | 35.83 |
| 1-1/2" | L1@0.20 | Ea | 34.20 | 7.93 | 42.13 |
| 2" | L1@0.25 | Ea | 29.60 | 9.91 | 39.51 |
| 2-1/2" | L2@0.30 | Ea | 59.10 | 11.90 | 71.00 |
| 3" | L2@0.35 | Ea | 94.50 | 13.90 | 108.40 |
| 3-1/2" | L2@0.40 | Ea | 132.00 | 15.90 | 147.90 |
| 4" | L2@0.50 | Ea | 248.00 | 19.80 | 267.80 |
| 5" | L2@0.75 | Ea | 382.00 | 29.70 | 411.70 |

PVC coated steel couplings

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 4.59 | 1.98 | 6.57 |
| 3/4" | L1@0.06 | Ea | 4.82 | 2.38 | 7.20 |
| 1" | L1@0.08 | Ea | 6.25 | 3.17 | 9.42 |
| 1-1/4" | L1@0.10 | Ea | 7.27 | 3.96 | 11.23 |
| 1-1/2" | L1@0.10 | Ea | 8.67 | 3.96 | 12.63 |
| 2" | L1@0.15 | Ea | 12.70 | 5.94 | 18.64 |
| 2-1/2" | L2@0.20 | Ea | 31.40 | 7.93 | 39.33 |
| 3" | L2@0.20 | Ea | 38.20 | 7.93 | 46.13 |
| 3-1/2" | L2@0.25 | Ea | 49.00 | 9.91 | 58.91 |
| 4" | L2@0.25 | Ea | 57.20 | 9.91 | 67.11 |
| 5" | L2@0.30 | Ea | 185.00 | 11.90 | 196.90 |

Use these figures to estimate the cost of PVC coated conduit, elbows and couplings installed in corrosive areas under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet of conduit or for each fitting installed. The crew is one electrician for sizes up to 2" and two electricians for sizes over 2". The labor cost is \$39.63 per manhour. These costs include cutting and threading, one coupling for each length of conduit, layout, material handling, and normal waste. Add for straps, locknuts, bushings, sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: PVC patching material is available in spray cans for repairing any damaged PVC coating. Bending tools must be ground out when used on PVC conduit. Threading equipment must be modified for use on PVC conduit.

PVC Coated Straps and Clamps

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

PVC coated steel one hole straps

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.05 | Ea | 11.30 | 1.98 | 13.28 |
| 3/4" | L1@0.06 | Ea | 11.30 | 2.38 | 13.68 |
| 1" | L1@0.08 | Ea | 11.60 | 3.17 | 14.77 |
| 1-1/4" | L1@0.10 | Ea | 16.90 | 3.96 | 20.86 |
| 1-1/2" | L1@0.10 | Ea | 18.00 | 3.96 | 21.96 |
| 2" | L1@0.15 | Ea | 26.00 | 5.94 | 31.94 |
| 2-1/2" | L1@0.20 | Ea | 24.60 | 7.93 | 32.53 |
| 3" | L1@0.25 | Ea | 33.10 | 9.91 | 43.01 |
| 3-1/2" | L1@0.30 | Ea | 59.40 | 11.90 | 71.30 |
| 4" | L1@0.40 | Ea | 63.20 | 15.90 | 79.10 |




PVC coated malleable one hole straps

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.05 | Ea | 9.09 | 1.98 | 11.07 |
| 3/4" | L1@0.06 | Ea | 9.18 | 2.38 | 11.56 |
| 1" | L1@0.10 | Ea | 9.45 | 3.96 | 13.41 |
| 1-1/4" | L1@0.10 | Ea | 13.70 | 3.96 | 17.66 |
| 1-1/2" | L1@0.15 | Ea | 21.20 | 5.94 | 27.14 |
| 2" | L1@0.20 | Ea | 22.20 | 7.93 | 30.13 |
| 2-1/2" | L1@0.20 | Ea | 39.80 | 7.93 | 47.73 |
| 3" | L1@0.25 | Ea | 68.00 | 9.91 | 77.91 |
| 3-1/2" | L1@0.30 | Ea | 96.30 | 11.90 | 108.20 |
| 4" | L1@0.30 | Ea | 102.00 | 11.90 | 113.90 |




PVC coated right angle beam clamps

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.10 | Ea | 17.00 | 3.96 | 20.96 |
| 3/4" | L1@0.15 | Ea | 17.20 | 5.94 | 23.14 |
| 1" | L1@0.20 | Ea | 23.00 | 7.93 | 30.93 |
| 1-1/4" | L1@0.25 | Ea | 23.30 | 9.91 | 33.21 |
| 1-1/2" | L1@0.25 | Ea | 28.80 | 9.91 | 38.71 |
| 2" | L1@0.30 | Ea | 37.30 | 11.90 | 49.20 |
| 2-1/2" | L1@0.40 | Ea | 41.00 | 15.90 | 56.90 |
| 3" | L1@0.50 | Ea | 45.90 | 19.80 | 65.70 |
| 3-1/2" | L1@0.60 | Ea | 47.50 | 23.80 | 71.30 |
| 4" | L1@0.60 | Ea | 51.90 | 23.80 | 75.70 |



PVC coated parallel beam clamps

| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.10 | Ea | 18.70 | 3.96 | 22.66 |
| 3/4" | L1@0.15 | Ea | 19.00 | 5.94 | 24.94 |
| 1" | L1@0.20 | Ea | 23.30 | 7.93 | 31.23 |
| 1-1/4" | L1@0.25 | Ea | 25.70 | 9.91 | 35.61 |
| 1-1/2" | L1@0.25 | Ea | 28.90 | 9.91 | 38.81 |
| 2" | L1@0.30 | Ea | 35.90 | 11.90 | 47.80 |
| 2-1/2" | L1@0.30 | Ea | 43.70 | 11.90 | 55.60 |
| 3" | L1@0.40 | Ea | 49.60 | 15.90 | 65.50 |
| 3-1/2" | L1@0.60 | Ea | 52.10 | 23.80 | 75.90 |
| 4" | L1@0.60 | Ea | 52.40 | 23.80 | 76.20 |



Use these figures to estimate the cost of PVC coated straps and clamps installed on PVC coated conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include screws, anchors, layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: PVC patching material is available in spray cans for repairing any damaged PVC coating.

PVC Coated Clamps, U-bolts and Unions


| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

PVC coated edge-type beam clamps




| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.10 | Ea | 16.00 | 3.96 | 19.96 |
| 3/4" | L1@0.15 | Ea | 17.00 | 5.94 | 22.94 |
| 1" | L1@0.20 | Ea | 28.30 | 7.93 | 36.23 |
| 1-1/4" | L1@0.25 | Ea | 47.80 | 9.91 | 57.71 |
| 1-1/2" | L1@0.25 | Ea | 61.60 | 9.91 | 71.51 |
| 2" | L1@0.30 | Ea | 67.10 | 11.90 | 79.00 |

PVC coated U-bolts




| | | | | | |
|--------|---------|----|-------|-------|-------|
| 1/2" | L1@0.10 | Ea | 7.24 | 3.96 | 11.20 |
| 3/4" | L1@0.15 | Ea | 7.24 | 5.94 | 13.18 |
| 1" | L1@0.20 | Ea | 7.24 | 7.93 | 15.17 |
| 1-1/4" | L1@0.25 | Ea | 7.51 | 9.91 | 17.42 |
| 1-1/2" | L1@0.25 | Ea | 7.65 | 9.91 | 17.56 |
| 2" | L1@0.30 | Ea | 9.36 | 11.90 | 21.26 |
| 2-1/2" | L1@0.35 | Ea | 16.30 | 13.90 | 30.20 |
| 3" | L1@0.35 | Ea | 17.20 | 13.90 | 31.10 |
| 3-1/2" | L1@0.40 | Ea | 18.30 | 15.90 | 34.20 |
| 4" | L1@0.50 | Ea | 24.20 | 19.80 | 44.00 |
| 5" | L1@0.60 | Ea | 33.90 | 23.80 | 57.70 |

PVC coated female conduit unions



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 38.50 | 3.96 | 42.46 |
| 3/4" | L1@0.10 | Ea | 39.20 | 3.96 | 43.16 |
| 1" | L1@0.15 | Ea | 75.00 | 5.94 | 80.94 |
| 1-1/4" | L1@0.20 | Ea | 79.00 | 7.93 | 86.93 |
| 1-1/2" | L1@0.20 | Ea | 145.00 | 7.93 | 152.93 |
| 2" | L1@0.25 | Ea | 194.00 | 9.91 | 203.91 |
| 2-1/2" | L1@0.30 | Ea | 205.00 | 11.90 | 216.90 |
| 3" | L1@0.30 | Ea | 284.00 | 11.90 | 295.90 |
| 3-1/2" | L1@0.35 | Ea | 353.00 | 13.90 | 366.90 |
| 4" | L1@0.40 | Ea | 375.00 | 15.90 | 390.90 |

PVC coated male conduit unions




| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.10 | Ea | 39.90 | 3.96 | 43.86 |
| 3/4" | L1@0.10 | Ea | 44.20 | 3.96 | 48.16 |
| 1" | L1@0.15 | Ea | 55.40 | 5.94 | 61.34 |
| 1-1/4" | L1@0.20 | Ea | 89.60 | 7.93 | 97.53 |
| 1-1/2" | L1@0.20 | Ea | 109.00 | 7.93 | 116.93 |
| 2" | L1@0.25 | Ea | 136.00 | 9.91 | 145.91 |
| 2-1/2" | L1@0.30 | Ea | 240.00 | 11.90 | 251.90 |
| 3" | L1@0.30 | Ea | 318.00 | 11.90 | 329.90 |
| 3-1/2" | L1@0.35 | Ea | 416.00 | 13.90 | 429.90 |
| 4" | L1@0.40 | Ea | 515.00 | 15.90 | 530.90 |

Use these figures to estimate the cost of PVC coated clamps, U-bolts and unions installed on PVC coated conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include screws, bolts, nuts, layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: PVC patching material is available in spray cans for repairing any damaged PVC coating. PVC conduit fittings are rigid conduit fittings that have a PVC bonded coating for corrosion protection.


PVC Coated Couplings and Conduit Bodies

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|--------------------------------------|-----------|------|---------------|------------|----------------|
| PVC coated reducing couplings | | | | | |
| 3/4"- 1/2" | L1@0.05 | Ea | 26.00 | 1.98 | 27.98 |
| 1"- 1/2" | L1@0.06 | Ea | 28.10 | 2.38 | 30.48 |
| 1"- 3/4" | L1@0.06 | Ea | 32.60 | 2.38 | 34.98 |
| 1-1/4"- 3/4" | L1@0.08 | Ea | 41.20 | 3.17 | 44.37 |
| 1-1/4"- 1" | L1@0.08 | Ea | 44.10 | 3.17 | 47.27 |
| 1-1/2"- 3/4" | L1@0.10 | Ea | 35.20 | 3.96 | 39.16 |
| 1-1/2"- 1" | L1@0.10 | Ea | 41.40 | 3.96 | 45.36 |
| 1-1/2"- 1-1/4" | L1@0.10 | Ea | 69.70 | 3.96 | 73.66 |
| 2"- 3/4" | L1@0.15 | Ea | 77.00 | 5.94 | 82.94 |
| 2"- 1" | L1@0.15 | Ea | 74.50 | 5.94 | 80.44 |
| 2"- 1-1/4" | L1@0.15 | Ea | 79.10 | 5.94 | 85.04 |
| 2"- 1-1/2" | L1@0.20 | Ea | 90.90 | 7.93 | 98.83 |
| 3"- 2" | L1@0.20 | Ea | 147.00 | 7.93 | 154.93 |
| 3-1/2"- 2-1/2" | L1@0.25 | Ea | 185.00 | 9.91 | 194.91 |
| 4"- 3" | L1@0.30 | Ea | 365.00 | 11.90 | 376.90 |
| 5"- 4" | L1@0.40 | Ea | 464.00 | 15.90 | 479.90 |




PVC coated Type C conduit bodies

| | | | | | |
|---------------|---------|----|--------|-------|--------|
| C-17 1/2" | L1@0.20 | Ea | 37.50 | 7.93 | 45.43 |
| C-27 3/4" | L1@0.25 | Ea | 39.30 | 9.91 | 49.21 |
| C-37 1" | L1@0.30 | Ea | 54.80 | 11.90 | 66.70 |
| C-47 1-1/4" | L1@0.35 | Ea | 82.30 | 13.90 | 96.20 |
| C-57 1-1/2" | L1@0.40 | Ea | 99.90 | 15.90 | 115.80 |
| C-67 2" | L1@0.40 | Ea | 142.00 | 15.90 | 157.90 |
| C-77 2-1/2" | L1@0.50 | Ea | 273.00 | 19.80 | 292.80 |
| CLF-87 3" | L1@0.60 | Ea | 345.00 | 23.80 | 368.80 |
| CLF-97 3-1/2" | L1@0.70 | Ea | 515.00 | 27.70 | 542.70 |
| CLF-107 4" | L1@1.00 | Ea | 581.00 | 39.60 | 620.60 |



PVC coated Type LB conduit bodies

| | | | | | |
|--------------|---------|----|--------|-------|--------|
| LB-17 1/2" | L1@0.20 | Ea | 37.00 | 7.93 | 44.93 |
| LB-27 3/4" | L1@0.25 | Ea | 37.90 | 9.91 | 47.81 |
| LB-37 1" | L1@0.30 | Ea | 49.70 | 11.90 | 61.60 |
| LB-47 1-1/4" | L1@0.35 | Ea | 81.60 | 13.90 | 95.50 |
| LB-57 1-1/2" | L1@0.35 | Ea | 99.00 | 13.90 | 112.90 |
| LB-67 2" | L1@0.40 | Ea | 140.00 | 15.90 | 155.90 |
| LB-77 2-1/2" | L1@0.50 | Ea | 270.00 | 19.80 | 289.80 |
| LB-87 3" | L1@0.60 | Ea | 339.00 | 23.80 | 362.80 |
| LB-97 3-1/2" | L1@0.70 | Ea | 499.00 | 27.70 | 526.70 |
| LB-107 4" | L1@1.00 | Ea | 559.00 | 39.60 | 598.60 |




Use these figures to estimate the cost of PVC coated couplings and conduit bodies installed on PVC coated conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include covers, layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: PVC patching material is available in spray cans for repairing any damaged PVC coating.

PVC Coated Conduit Bodies

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


PVC coated Type T conduit bodies

| | | | | | |
|-------------|---------|----|--------|-------|--------|
| T-17 1/2" | L1@0.25 | Ea | 49.30 | 9.91 | 59.21 |
| T-27 3/4" | L1@0.30 | Ea | 55.90 | 11.90 | 67.80 |
| T-37 1" | L1@0.35 | Ea | 80.40 | 13.90 | 94.30 |
| T-47 1-1/4" | L1@0.40 | Ea | 135.00 | 15.90 | 150.90 |
| T-57 1-1/2" | L1@0.40 | Ea | 143.00 | 15.90 | 158.90 |
| T-67 2" | L1@0.45 | Ea | 259.00 | 17.80 | 276.80 |
| T-77 2-1/2" | L1@0.60 | Ea | 438.00 | 23.80 | 461.80 |
| T-87 3" | L1@0.70 | Ea | 586.00 | 27.70 | 613.70 |
| T-97 3-1/2" | L1@1.00 | Ea | 842.00 | 39.60 | 881.60 |
| T-107 4" | L1@1.50 | Ea | 918.00 | 59.40 | 977.40 |




PVC coated Type TB conduit bodies

| | | | | | |
|--------------|---------|----|--------|-------|--------|
| TB-17 1/2" | L1@0.25 | Ea | 55.90 | 9.91 | 65.81 |
| TB-27 3/4" | L1@0.30 | Ea | 68.10 | 11.90 | 80.00 |
| TB-37 1" | L1@0.35 | Ea | 73.60 | 13.90 | 87.50 |
| TB-47 1-1/4" | L1@0.40 | Ea | 135.00 | 15.90 | 150.90 |
| TB-57 1-1/2" | L1@0.40 | Ea | 143.00 | 15.90 | 158.90 |
| TB-67 2" | L1@0.45 | Ea | 259.00 | 17.80 | 276.80 |



PVC coated Type X conduit bodies

| | | | | | |
|-------------|---------|----|--------|-------|--------|
| X-17 1/2" | L1@0.30 | Ea | 58.20 | 11.90 | 70.10 |
| X-27 3/4" | L1@0.35 | Ea | 66.10 | 13.90 | 80.00 |
| X-37 1" | L1@0.40 | Ea | 74.80 | 15.90 | 90.70 |
| X-47 1-1/4" | L1@0.45 | Ea | 179.00 | 17.80 | 196.80 |
| X-57 1-1/2" | L1@0.45 | Ea | 233.00 | 17.80 | 250.80 |
| X-67 2" | L1@0.50 | Ea | 336.00 | 19.80 | 355.80 |



PVC coated steel conduit body covers

| | | | | | |
|-------------|---------|----|--------|------|--------|
| 1/2" | L1@0.05 | Ea | 15.40 | 1.98 | 17.38 |
| 3/4" | L1@0.06 | Ea | 16.90 | 2.38 | 19.28 |
| 1" | L1@0.08 | Ea | 22.20 | 3.17 | 25.37 |
| 1-1/4" | L1@0.10 | Ea | 29.20 | 3.96 | 33.16 |
| 1-1/2" | L1@0.10 | Ea | 32.00 | 3.96 | 35.96 |
| 2" | L1@0.10 | Ea | 40.60 | 3.96 | 44.56 |
| 2-1/2" - 3" | L1@0.15 | Ea | 54.90 | 5.94 | 60.84 |
| 2-1/2" - 4" | L1@0.15 | Ea | 108.00 | 5.94 | 113.94 |



Use these figures to estimate the cost of PVC coated conduit bodies installed on PVC coated conduit and PVC coated body covers installed on conduit bodies under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: PVC patching material is available in spray cans for repairing any damaged PVC coating.

PVC Coated Junction Boxes

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


PVC coated Type GUAB junction boxes with covers

| | | | | | |
|----------------------|---------|----|--------|-------|--------|
| 1/2" - 2" dia. | L1@0.35 | Ea | 108.00 | 13.90 | 121.90 |
| 1/2" - 3" dia. | L1@0.40 | Ea | 122.00 | 15.90 | 137.90 |
| 3/4" - 2" dia. | L1@0.40 | Ea | 132.00 | 15.90 | 147.90 |
| 3/4" - 3" dia. | L1@0.45 | Ea | 135.00 | 17.80 | 152.80 |
| 1" - 3" dia. | L1@0.50 | Ea | 154.00 | 19.80 | 173.80 |
| 1-1/4" - 3-5/8" dia. | L1@0.60 | Ea | 248.00 | 23.80 | 271.80 |
| 1-1/2" - 5" dia. | L1@0.75 | Ea | 402.00 | 29.70 | 431.70 |
| 2" - 5" dia. | L1@1.00 | Ea | 452.00 | 39.60 | 491.60 |



PVC coated Type GUAC junction boxes with covers

| | | | | | |
|----------------------|---------|----|--------|-------|--------|
| 1/2" - 2" dia. | L1@0.35 | Ea | 108.00 | 13.90 | 121.90 |
| 1/2" - 3" dia. | L1@0.40 | Ea | 122.00 | 15.90 | 137.90 |
| 3/4" - 2" dia. | L1@0.40 | Ea | 132.00 | 15.90 | 147.90 |
| 3/4" - 3" dia. | L1@0.45 | Ea | 135.00 | 17.80 | 152.80 |
| 1" - 3" dia. | L1@0.50 | Ea | 154.00 | 19.80 | 173.80 |
| 1-1/4" - 3-5/8" dia. | L1@0.60 | Ea | 248.00 | 23.80 | 271.80 |
| 1-1/2" - 5" dia. | L1@0.75 | Ea | 402.00 | 29.70 | 431.70 |
| 2" - 5" dia. | L1@1.00 | Ea | 452.00 | 39.60 | 491.60 |



PVC coated Type GUAL junction boxes with covers

| | | | | | |
|----------------------|---------|----|--------|-------|--------|
| 1/2" - 2" dia. | L1@0.35 | Ea | 108.00 | 13.90 | 121.90 |
| 1/2" - 3" dia. | L1@0.40 | Ea | 122.00 | 15.90 | 137.90 |
| 3/4" - 2" dia. | L1@0.40 | Ea | 132.00 | 15.90 | 147.90 |
| 3/4" - 3" dia. | L1@0.45 | Ea | 135.00 | 17.80 | 152.80 |
| 1" - 3" dia. | L1@0.50 | Ea | 154.00 | 19.80 | 173.80 |
| 1-1/4" - 3-5/8" dia. | L1@0.60 | Ea | 248.00 | 23.80 | 271.80 |
| 1-1/2" - 5" dia. | L1@0.75 | Ea | 402.00 | 29.70 | 431.70 |
| 2" - 5" dia. | L1@1.00 | Ea | 452.00 | 39.60 | 491.60 |




PVC coated Type GUAN junction boxes with covers

| | | | | | |
|----------------------|---------|----|--------|-------|--------|
| 1/2" - 2" dia. | L1@0.35 | Ea | 108.00 | 13.90 | 121.90 |
| 1/2" - 3" dia. | L1@0.40 | Ea | 122.00 | 15.90 | 137.90 |
| 3/4" - 2" dia. | L1@0.40 | Ea | 132.00 | 15.90 | 147.90 |
| 3/4" - 3" dia. | L1@0.45 | Ea | 135.00 | 17.80 | 152.80 |
| 1" - 3" dia. | L1@0.50 | Ea | 154.00 | 19.80 | 173.80 |
| 1-1/4" - 3-5/8" dia. | L1@0.60 | Ea | 248.00 | 23.80 | 271.80 |
| 1-1/2" - 5" dia. | L1@0.75 | Ea | 402.00 | 29.70 | 431.70 |
| 2" - 5" dia. | L1@1.00 | Ea | 452.00 | 39.60 | 491.60 |



PVC coated Type GUAW junction boxes with covers

| | | | | | |
|----------------|---------|----|--------|-------|--------|
| 1/2" - 2" dia. | L1@0.40 | Ea | 144.00 | 15.90 | 159.90 |
| 1/2" - 3" dia. | L1@0.45 | Ea | 171.00 | 17.80 | 188.80 |
| 3/4" - 2" dia. | L1@0.45 | Ea | 151.00 | 17.80 | 168.80 |
| 3/4" - 3" dia. | L1@0.50 | Ea | 175.00 | 19.80 | 194.80 |



Use these figures to estimate the cost of PVC coated junction boxes installed on PVC coated conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the box cover, layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: PVC patching material is available in spray cans for repairing damaged PVC coating.

PVC Coated Junction Boxes and Sealing Fittings


| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|

PVC coated Type GUAT junction boxes with covers




| | | | | | |
|----------------------|---------|----|--------|-------|--------|
| 1/2" - 2" dia. | L1@0.40 | Ea | 151.00 | 15.90 | 166.90 |
| 1/2" - 3" dia. | L1@0.45 | Ea | 170.00 | 17.80 | 187.80 |
| 3/4" - 2" dia. | L1@0.50 | Ea | 163.00 | 19.80 | 182.80 |
| 3/4" - 3" dia. | L1@0.55 | Ea | 183.00 | 21.80 | 204.80 |
| 1" - 3" dia. | L1@0.60 | Ea | 286.00 | 23.80 | 309.80 |
| 1-1/4" - 3-5/8" dia. | L1@0.65 | Ea | 556.00 | 25.80 | 581.80 |
| 1-1/2" - 5" dia. | L1@0.80 | Ea | 620.00 | 31.70 | 651.70 |
| 2" - 5" dia. | L1@1.10 | Ea | 652.00 | 43.60 | 695.60 |

PVC coated Type GUAX junction boxes with covers




| | | | | | |
|----------------------|---------|----|--------|-------|--------|
| 1/2" - 2" dia. | L1@0.45 | Ea | 149.00 | 17.80 | 166.80 |
| 1/2" - 3" dia. | L1@0.50 | Ea | 168.00 | 19.80 | 187.80 |
| 3/4" - 2" dia. | L1@0.55 | Ea | 157.00 | 21.80 | 178.80 |
| 3/4" - 3" dia. | L1@0.60 | Ea | 175.00 | 23.80 | 198.80 |
| 1" - 3" dia. | L1@0.65 | Ea | 182.00 | 25.80 | 207.80 |
| 1-1/4" - 3-5/8" dia. | L1@0.70 | Ea | 196.00 | 27.70 | 223.70 |
| 1-1/2" - 5" dia. | L1@0.90 | Ea | 564.00 | 35.70 | 599.70 |
| 2" - 5" dia. | L1@1.25 | Ea | 621.00 | 49.50 | 670.50 |

PVC coated Type EYD female sealing fittings



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.35 | Ea | 108.00 | 13.90 | 121.90 |
| 3/4" | L1@0.40 | Ea | 109.00 | 15.90 | 124.90 |
| 1" | L1@0.45 | Ea | 125.00 | 17.80 | 142.80 |
| 1-1/4" | L1@0.50 | Ea | 137.00 | 19.80 | 156.80 |
| 1-1/2" | L1@0.60 | Ea | 173.00 | 23.80 | 196.80 |
| 2" | L1@0.75 | Ea | 189.00 | 29.70 | 218.70 |

PVC coated Type EYD male-female sealing fittings



| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.35 | Ea | 108.00 | 13.90 | 121.90 |
| 3/4" | L1@0.40 | Ea | 109.00 | 15.90 | 124.90 |
| 1" | L1@0.45 | Ea | 125.00 | 17.80 | 142.80 |
| 1-1/4" | L1@0.50 | Ea | 142.00 | 19.80 | 161.80 |
| 1-1/2" | L1@0.60 | Ea | 180.00 | 23.80 | 203.80 |
| 2" | L1@0.75 | Ea | 197.00 | 29.70 | 226.70 |
| 2-1/2" | L1@0.90 | Ea | 289.00 | 35.70 | 324.70 |
| 3" | L1@1.00 | Ea | 393.00 | 39.60 | 432.60 |
| 3-1/2" | L1@1.25 | Ea | 393.00 | 49.50 | 442.50 |
| 4" | L1@1.40 | Ea | 927.00 | 55.50 | 982.50 |


Use these figures to estimate the cost of PVC coated junction boxes and sealing fittings installed on PVC coated conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include the cover, layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: PVC patching material is available in spray cans for repairing damaged PVC coating.

PVC Coated Sealing Fittings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------|-----------|------|---------------|------------|----------------|
|----------|-----------|------|---------------|------------|----------------|


PVC coated Type EYS female sealing fittings

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.30 | Ea | 60.20 | 11.90 | 72.10 |
| 3/4" | L1@0.35 | Ea | 55.70 | 13.90 | 69.60 |
| 1" | L1@0.40 | Ea | 66.80 | 15.90 | 82.70 |
| 1-1/4" | L1@0.50 | Ea | 95.40 | 19.80 | 115.20 |
| 1-1/2" | L1@0.50 | Ea | 123.00 | 19.80 | 142.80 |
| 2" | L1@0.60 | Ea | 136.00 | 23.80 | 159.80 |




PVC coated Type EYS male-female sealing fittings

| | | | | | |
|--------|---------|----|----------|-------|----------|
| 1/2" | L1@0.30 | Ea | 60.80 | 11.90 | 72.70 |
| 3/4" | L1@0.35 | Ea | 56.30 | 13.90 | 70.20 |
| 1" | L1@0.40 | Ea | 67.30 | 15.90 | 83.20 |
| 1-1/4" | L1@0.50 | Ea | 96.30 | 19.80 | 116.10 |
| 1-1/2" | L1@0.50 | Ea | 126.00 | 19.80 | 145.80 |
| 2" | L1@0.60 | Ea | 141.00 | 23.80 | 164.80 |
| 2-1/2" | L1@0.75 | Ea | 218.00 | 29.70 | 247.70 |
| 3" | L1@0.90 | Ea | 293.00 | 35.70 | 328.70 |
| 3-1/2" | L1@1.00 | Ea | 872.00 | 39.60 | 911.60 |
| 4" | L1@1.25 | Ea | 1,130.00 | 49.50 | 1,179.50 |




PVC coated Type EZS female sealing fittings

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.30 | Ea | 70.70 | 11.90 | 82.60 |
| 3/4" | L1@0.35 | Ea | 91.80 | 13.90 | 105.70 |
| 1" | L1@0.40 | Ea | 110.00 | 15.90 | 125.90 |
| 1-1/4" | L1@0.50 | Ea | 125.00 | 19.80 | 144.80 |
| 1-1/2" | L1@0.50 | Ea | 241.00 | 19.80 | 260.80 |
| 2" | L1@0.60 | Ea | 503.00 | 23.80 | 526.80 |




PVC coated Type EZS male-female sealing fittings

| | | | | | |
|--------|---------|----|--------|-------|--------|
| 1/2" | L1@0.30 | Ea | 71.20 | 11.90 | 83.10 |
| 3/4" | L1@0.35 | Ea | 92.70 | 13.90 | 106.60 |
| 1" | L1@0.40 | Ea | 110.00 | 15.90 | 125.90 |
| 1-1/4" | L1@0.50 | Ea | 131.00 | 19.80 | 150.80 |
| 1-1/2" | L1@0.50 | Ea | 189.00 | 19.80 | 208.80 |
| 2" | L1@0.60 | Ea | 169.00 | 23.80 | 192.80 |
| 2-1/2" | L1@0.70 | Ea | 318.00 | 27.70 | 345.70 |
| 3" | L1@0.90 | Ea | 527.00 | 35.70 | 562.70 |



Use these figures to estimate the cost of PVC coated sealing fittings installed on PVC coated conduit under the conditions described on pages 5 and 6. Costs listed are for each fitting installed. The crew is one electrician working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit. Note: PVC patching material is available in spray cans for repairing damaged PVC coating.


Hanger Fittings



| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|----------------------------|-----------|------|---------------|------------|----------------|
| Plated threaded rod | | | | | |
| 1/4-20 x 6' | L1@1.25 | CLF | 175.00 | 49.50 | 224.50 |
| 1/4-20 x 10' | L1@1.25 | CLF | 280.00 | 49.50 | 329.50 |
| 1/4-20 x 12' | L1@1.15 | CLF | 338.00 | 45.60 | 383.60 |
| 3/8-16 x 6' | L1@1.30 | CLF | 192.00 | 51.50 | 243.50 |
| 3/8-16 x 10' | L1@1.30 | CLF | 471.00 | 51.50 | 522.50 |
| 3/8-16 x 12' | L1@1.30 | CLF | 590.00 | 51.50 | 641.50 |
| 1/2-13 x 6' | L1@1.50 | CLF | 326.00 | 59.40 | 385.40 |
| 1/2-13 x 10' | L1@1.50 | CLF | 847.00 | 59.40 | 906.40 |
| 1/2-13 x 12' | L1@1.50 | CLF | 1,020.00 | 59.40 | 1,079.40 |
| 5/8-11 x 6' | L1@1.75 | CLF | 887.00 | 69.40 | 956.40 |
| 5/8-11 x 10' | L1@1.75 | CLF | 1,250.00 | 69.40 | 1,319.40 |
| 5/8-11 x 12' | L1@1.75 | CLF | 1,550.00 | 69.40 | 1,619.40 |



| | | | | | |
|----------------------|---------|----|------|------|-------|
| Rod couplings | | | | | |
| 1/4-20 | L1@0.05 | Ea | 1.54 | 1.98 | 3.52 |
| 3/8-16 | L1@0.05 | Ea | 3.11 | 1.98 | 5.09 |
| 1/2-13 | L1@0.08 | Ea | 3.19 | 3.17 | 6.36 |
| 5/8-11 | L1@0.10 | Ea | 7.44 | 3.96 | 11.40 |




| | | | | | |
|--------------------------------|---------|----|-----|------|------|
| Toggle bolts, wing nuts | | | | | |
| 1/8 x 3" | L1@0.10 | Ea | .14 | 3.96 | 4.10 |
| 3/16 x 3" | L1@0.10 | Ea | .22 | 3.96 | 4.18 |
| 1/4 x 4" | L1@0.15 | Ea | .33 | 5.94 | 6.27 |
| 3/8 x 4" | L1@0.20 | Ea | .40 | 7.93 | 8.33 |



| | | | | | |
|--------------------------------------|---------|----|------|-------|-------|
| Expansion anchors, flush type | | | | | |
| 1/4-20 | L1@0.15 | Ea | .34 | 5.94 | 6.28 |
| 3/8-16 | L1@0.15 | Ea | .55 | 5.94 | 6.49 |
| 1/2-13 | L1@0.25 | Ea | 1.49 | 9.91 | 11.40 |
| 5/8-11 | L1@0.30 | Ea | 2.13 | 11.90 | 14.03 |



| | | | | | |
|-----------------------|---------|----|-----|------|------|
| Steel hex nuts | | | | | |
| 1/4-20 | L1@0.02 | Ea | .22 | .79 | 1.01 |
| 3/8-16 | L1@0.03 | Ea | .23 | 1.19 | 1.42 |
| 1/2-13 | L1@0.05 | Ea | .29 | 1.98 | 2.27 |
| 5/8-11 | L1@0.10 | Ea | .33 | 3.96 | 4.29 |




| | | | | | |
|--|---------|----|-----|------|------|
| Fender washers, 1-1/2" diameter | | | | | |
| 1/4" | L1@0.02 | Ea | .03 | .79 | .82 |
| 3/8" | L1@0.03 | Ea | .05 | 1.19 | 1.24 |
| 1/2" | L1@0.04 | Ea | .08 | 1.59 | 1.67 |

Use these figures to estimate the cost of installing steel hanger fittings for hanging or mounting conduit or electrical equipment under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet of steel channel strut, or each fitting installed. The crew is one electrical working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit.

Steel Channel (Strut) and Fittings

| Material | Craft@Hrs | Unit | Material Cost | Labor Cost | Installed Cost |
|-------------------------------|-----------|------|---------------|------------|----------------|
| 14 gauge steel channel | | | | | |
| 13/16" x 1-5/8" plated | L1@4.00 | CLF | 220.00 | 159.00 | 379.00 |
| 13/16" x 1-5/8" galvanized | L1@4.00 | CLF | 273.00 | 159.00 | 432.00 |
| 1-5/8" x 1-5/8" plated | L1@6.00 | CLF | 314.00 | 238.00 | 552.00 |
| 1-5/8" x 1-5/8" galvanized | L1@6.00 | CLF | 336.00 | 238.00 | 574.00 |



14 gauge steel channel with 9/16" holes, 1-7/8" oc


| | | | | | |
|----------------------------|---------|-----|--------|--------|--------|
| 13/16" x 1-5/8" plated | L1@4.00 | CLF | 221.00 | 159.00 | 380.00 |
| 13/16" x 1-5/8" galvanized | L1@4.00 | CLF | 291.00 | 159.00 | 450.00 |
| 1-5/8" x 1-5/8" plated | L1@6.00 | CLF | 297.00 | 238.00 | 535.00 |
| 1-5/8" x 1-5/8" galvanized | L1@6.00 | CLF | 381.00 | 238.00 | 619.00 |

12 gauge steel channel

| | | | | | |
|----------------------------|---------|-----|--------|--------|--------|
| 13/16" x 1-5/8" plated | L1@4.00 | CLF | 220.00 | 159.00 | 379.00 |
| 13/16" x 1-5/8" galvanized | L1@4.00 | CLF | 263.00 | 159.00 | 422.00 |
| 1-5/8" x 1-5/8" plated | L1@6.00 | CLF | 314.00 | 238.00 | 552.00 |
| 1-5/8" x 1-5/8" galvanized | L1@6.00 | CLF | 379.00 | 238.00 | 617.00 |


12 gauge steel channel with 9/16" holes, 1-7/8" oc

| | | | | | |
|----------------------------|---------|-----|--------|--------|--------|
| 13/16" x 1-5/8" plated | L1@4.00 | CLF | 261.00 | 159.00 | 420.00 |
| 13/16" x 1-5/8" galvanized | L1@4.00 | CLF | 271.00 | 159.00 | 430.00 |
| 1-5/8" x 1-5/8" plated | L1@6.00 | CLF | 286.00 | 238.00 | 524.00 |
| 1-5/8" x 1-5/8" galvanized | L1@6.00 | CLF | 286.00 | 238.00 | 524.00 |




Channel nuts

| | | | | | |
|---------------------|---------|----|------|------|------|
| 1/4-20 13/16" strut | L1@0.05 | Ea | 1.04 | 1.98 | 3.02 |
| 3/8-16 13/16" strut | L1@0.05 | Ea | 1.06 | 1.98 | 3.04 |
| 1/2-13 13/16" strut | L1@0.05 | Ea | 1.07 | 1.98 | 3.05 |
| 1/4-20 1-5/8" strut | L1@0.05 | Ea | 1.19 | 1.98 | 3.17 |
| 3/8-16 1-5/8" strut | L1@0.05 | Ea | 1.38 | 1.98 | 3.36 |
| 1/2-13 1-5/8" strut | L1@0.05 | Ea | 1.51 | 1.98 | 3.49 |



Channel spring nuts

| | | | | | |
|---------------------|---------|----|------|------|------|
| 1/4-20 13/16" strut | L1@0.06 | Ea | 1.27 | 2.38 | 3.65 |
| 3/8-16 13/16" strut | L1@0.06 | Ea | 1.27 | 2.38 | 3.65 |
| 1/2-13 13/16" strut | L1@0.06 | Ea | 1.37 | 2.38 | 3.75 |
| 1/4-20 1-5/8" strut | L1@0.06 | Ea | 1.75 | 2.38 | 4.13 |
| 3/8-16 1-5/8" strut | L1@0.06 | Ea | 1.85 | 2.38 | 4.23 |
| 1/2-13 1-5/8" strut | L1@0.06 | Ea | 2.01 | 2.38 | 4.39 |



Use these figures to estimate the cost of installing steel channel strut and fittings for hanging or mounting conduit or electrical equipment under the conditions described on pages 5 and 6. Costs listed are for each 100 linear feet of steel channel strut, or each fitting installed. The crew is one electrical working at a labor cost of \$39.63 per manhour. These costs include layout, material handling, and normal waste. Add for sales tax, delivery, supervision, mobilization, demobilization, cleanup, overhead and profit.

Index

- 10,000 AIC bolt-on breakers..... 307
10,000 AIC DC breakers 314
10,000 amp interrupt capacity 306
120 volt fixtures 184, 188
120 volt smoke detectors..... 371
120/277 volt switches 219
14,000 AIC breakers..... 312
2" range expansion
PVC couplings 39
208 volt fixtures 184, 188
22,000 AIC DC breakers 314
240 volt fixtures 184, 188
240 volt safety switches..... 275-277
277 volt fixtures 184, 188
277 volt switches 224-228
3-0 boxes..... 120
3-position switches, maintain contact 219
3-wire receptacles 245
30 degree PVC sweeping elbows 43-44
30 degree Schedule 40 PVC elbows 37
30,000 AIC breakers..... 314-315
4 square surface covers 131
4 square switch rings..... 129
4-0 boxes..... 120
4-S boxes 120
4-way power intrafacer 541
4-wire locking single receptacles 254
45 degree elbows
GRS 49
IMC 52
PVC sweeping 44
Schedule 40 PVC 38
Type EB or DB 45
45 degree flex connectors
die cast 31
insulated throat 35-36
liquid-tight 35-36
malleable 31
480 volt fixtures 188, 192
5 degree bend couplings, P&C... 46
5-way power intrafacer 541
5-wire locking single receptacles 254
6 range expansion PVC couplings 40
60 Hz incandescent dimmers ... 221
600 volt safety switches..... 278-281
90 degree elbows
aluminum rigid 58
die cast, EMT..... 27
GRS 49
IMC 53
PVC coated steel 78
PVC sweeping 44-45
Schedule 40 PVC 38
Schedule 80 PVC 38
Type EB or DB..... 46
90 degree malleable flex connectors 32
- A**
- Abandon plugs, duct..... 336
underfloor raceway 342
AC (armored cable) 88, 103
AC bolt-on breakers..... 312-313
AC breakers..... 306
AC grounded switches..... 223-224
AC horns..... 368
- AC magnetic contactors 390
starters..... 382
starters, three pole..... 400-403
starters, two pole 398-399
AC plug-on breakers..... 310-313
AC quiet switches..... 223-226
AC type cable 88
Access..... 8, 11, 16
Access boxes, precast concrete..... 373
Access, service entrance equipment..... 274
Accessories, floor box 156
Accuracy, estimating 7
Acrylic lens 176
ACSR (aluminum conductor steel reinforced)..... 108
neutral..... 111-112
wire 108-110
Adapters, duct 336
PVC 39
Adapters, cable
coaxial cable 537
subminiature D to modular jack 532
Additional costs 6
Adelphi..... 113
Adjustable bar hangers..... 129
Adjustable cast iron floor boxes 153
Adjustable flood light 164
Adjustable floor boxes and covers 153
Adjusting costs 6, 92, 222, 337
AF type wire..... 89
AFCI duplex receptacles 247
AIC (amp interrupt capacity)..... 307
Air alternator, hookup 379
Air compressor, hookup..... 379
Air handlers, hookup..... 379
Air-handling fixtures..... 178-179
Allowance for experience 6
waste 5, 16
Allowances
vertical runs 16
wire pulling..... 91
Almond 108
Almond-XLP 109
Alternator, air, hookup 379
Aluminum
abandon plugs, underfloor raceway 342
blank body covers..... 64
bus duct 346-349
bushings 61-62
cable 107, 113
circuit breaker enclosures..... 316
conductor, bare..... 114
conductor, grounding..... 441
conduit 15
conduit assemblies 451-454
conduit bodies 65
elbows 58
feeder wire..... 14
flex conduit assemblies .. 451-454
flex conduit bodies 65
frame fluorescent fixtures 177
housing exit fixtures..... 172
insulated ground bushings 62, 442
ladder cable tray 363
ladder tray..... 363
- light poles 196-198
locknuts 61
neutral..... 109, 111-112
nipples 58-61
one hole straps 76
reducing bushings 69-70
rigid conduit (ARC) 58
service drop wire 110-112
terminations 62
tray fittings 364
union 72
wire 90, 105-112
Aluminum/copper conversion 92
Aluminum rigid conduit (ARC) 58
bushings 61
locknuts 61
nipples 58-61
termination 62
American Wire Gauge system... 88
Ammeter 269
Ampacity 89, 90, 218
Anchors, expansion 86
Anti-oxidation material 91
Anti-short bushing 103
Apartment entry control 372
Appaloosa 111, 112
Appeal, inspector's decision 7
Apple 107
Apple-XLP 108
Appliance wire 96
Apricot 108
Apricot-XLP 109
Aquastats, hookup..... 379
ARC (aluminum rigid conduit)..... 58
ARC fault circuit interrupter 247
Architectural rectangular housing..... 189
Architectural square floods 189
Armored cable 88, 103
Arms, pole 197
Asbestos insulation..... 89
Assemblies
aluminum flex conduit..... 451-454
EMT conduit 447-450
galvanized rigid conduit .. 463-466
handy box switches 467-470
PVC conduit..... 459-462
receptacle and handy boxes 508-509
receptacle and sectional boxes 510-513
receptacles, duplex..... 515, 517
receptacles, single..... 514, 516
sectional box switches... 471-486
steel flex conduit..... 455-458
switches, 1 and 2 gang.... 487-507
Troffer fluorescent 518
Assumptions, conduit tables..... 16
Asymmetric lens 188
AWG 88
AWM type wire 96
- B**
- Backcharges for cleanup..... 8
Backfill 420
Backhoes..... 420
Backup power..... 378
Ball aligners..... 157
Ballasts
exterior weatherproof potted.. 194
fluorescent 213-216
high intensity discharge 206-207, 209
- indoor enclosed 194
metal halide 207
remote 159
weatherproof potted..... 194
Baluns..... 533-534
Bar hangers 120, 129
Bare aluminum conductor..... 114
Bare copper ring..... 439
Bare copper wire 88, 102, 442
Base, steel raceway..... 426
Base type duct spacers 47
Base wage, electrician..... 5
Basis, material costs..... 5
Bat wings 158
Bathroom fixtures 164
Batteries
engine-generators 378
exit fixtures 172
Battery powered smoke detectors..... 371
Beacons..... 365, 369
Beam clamps..... 11
EMT conduit hanger 26
PVC coated 79-80
Beech 108
Beech-XLP 109
Bells 365, 367
Bending
conduit, number permitted..... 10
GRS 12
P&C duct 12
raceway 423
Bergen 113
Bid shopping..... 9
Bidding government work 9
Blade-type fuses..... 285-299
Blank duct..... 336-337
Blank plates 261-263
jumbo 267
Bliss 113
Bloomfield 113
BNC plug and jack..... 533
BNC plug connectors..... 535-536
Boiler control panels, hookup ... 379
Boilers, hookup..... 379
Bollards..... 190
Bolt hangers, tomic..... 132
Bolt-on circuit breakers..... 272, 307
Bolt-on fuses..... 293
Bonding
connection 441
definitions 439-440
problems 441
Bonding conductor..... 11
Bonding jumpers..... 68
Boring 421
data logs 420
Box assemblies .. 467-486, 508-513
Box covers
concrete 126
floor..... 154
galvanized cast..... 67
octagon..... 126
round 133-136
square 136
weatherproof..... 67
Box grounding clips 442
Box plugs, underfloor raceway 341
Box, steel channel system..... 432
Boxes..... 119
cast aluminum 143-145
fiberglass 133-139
floor..... 153-155

| | | | | | | | |
|-------------------------------|------------------------|--------------------------------------|----------|---------------------------------|--------------|---------------------------------|------------------|
| galvanized cast..... | 66 | solid direct burial..... | 100-101 | Cerapus..... | 110, 112 | grounded switches..... | 224, 226 |
| ganged..... | 132 | splicer..... | 88 | Chain pull receptacles..... | 161 | incandescent dimmers..... | 229 |
| handy..... | 123 | stranded direct burial..... | 100 | Chain trenchers..... | 420 | switches..... | 224-227, 230-233 |
| hinge cover pull..... | 147-148 | stranded service entrance..... | 100 | Chairs (duct supports)..... | 336 | Commercial lighting..... | 157 |
| JIC wiring..... | 150-151 | telephone..... | 525 | Channel flat wire..... | 432 | Commercial specification grade | |
| junction..... | 339 | underground distribution..... | 113 | Channel strut, steel..... | 87 | switches..... | 233 |
| masonry..... | 132 | URD..... | 113 | Channel tray..... | 358 | Communications cable..... | 521-527 |
| NEMA..... | 146-151 | Cable adapter assemblies..... | 434 | Channel wire systems..... | 424 | coaxial..... | 526-527 |
| octagon..... | 125-126 | Cable connector savers..... | 532 | Checklist, service entrance | | LAN..... | 527 |
| old work switch..... | 142 | Cable connectors..... | 529-532 | equipment..... | 273 | multi-conductor..... | 523-525 |
| outlet..... | 119, 133-139 | centerline clamp..... | 532 | Cherry..... | 107 | plugs..... | 533 |
| plastic..... | 140-142 | data cable connectors..... | 532 | Cherry-XLP..... | 108 | solid..... | 521, 525 |
| plug-in tap..... | 345 | field programmable..... | 532 | Chiller control panels, | | stranded..... | 521-525 |
| pull..... | 146-152 | gender changer..... | 532 | hookup..... | 379 | telephone..... | 525 |
| raintight..... | 148-150 | subminiature D plug | | Chiller, water, hookup..... | 379 | transceiver/drop..... | 527 |
| round..... | 133-135, 140, 143, 153 | kits..... | 529-531 | Chimes..... | 365, 369 | twinaxial..... | 526 |
| square..... | 127, 136, 140-141 | subminiature | | Chola..... | 111, 112 | Communications | |
| steel, overfloor raceway..... | 427 | D receptacles..... | 529-531 | Choosing a specialty..... | 8 | equipment..... | 519-537 |
| switch..... | 123-124, 141-142 | subminiature D straight | | Chow..... | 111 | Communications duct..... | 339 |
| weatherproof..... | 144-145 | exit backshells..... | 531 | Circular fluorescent lamps..... | 212 | Compact fluorescent lamps..... | 201 |
| Boxes and rings, ganged..... | 132 | Cable contacts..... | 528 | Circuit breaker | | Compliance with code..... | 7 |
| Brass | | Cable cover, strain relief..... | 533 | disconnect, starters | | Compression EMT connectors..... | 20 |
| abandon plugs..... | 342 | Cable distribution systems..... | 519 | with..... | 413-417 | Compressor, hookup..... | 379 |
| carpet flanges..... | 156 | Cable fittings, | | enclosures..... | 315-316 | Concealed conduit..... | 16 |
| plugs..... | 156 | communications..... | 528-537 | loadcenters..... | 322-323 | Conch..... | 110, 112 |
| Breakers, circuit..... | 272, 306-307 | Cable tray..... | 358-364 | panelboards..... | 325-326 | Concordia..... | 113 |
| meter centers..... | 318-321 | aluminum ladder..... | 363 | plug-in switches, bus | | Concrete | |
| rating..... | 271 | layout..... | 359 | duct..... | 356-357 | access boxes..... | 373 |
| Brenau..... | 113 | louver opening..... | 361 | Circuit breakers..... | 272, 306-307 | octagon box covers..... | 126 |
| Bridge cranes, hookup..... | 379 | system for communications..... | 519 | meter centers..... | 318-321 | products, precast..... | 375 |
| Buckeye..... | 108 | Calculating material quantities..... | 13 | rating..... | 243 | removal..... | 421 |
| Buckeye-XLP..... | 109 | Callbacks..... | 8 | Circuit control switches..... | 218, 271 | rings..... | 126 |
| Budget hoists, hookup..... | 379 | Canopy..... | 157 | Circuit tests..... | 8 | Conditions, working..... | 6 |
| Building frame as ground..... | 439 | light fixture..... | 163 | Clam..... | 109, 111 | Conductors..... | 88 |
| Building management | | Capped elbows | | Clamps | | high voltage..... | 88 |
| systems..... | 365 | aluminum..... | 65 | conduit..... | 77 | Conduit | |
| Building wire, copper..... | 92-96 | galvanized..... | 65 | PVC coated..... | 79-80 | aluminum rigid (ARC)..... | 58 |
| Built-in grounding..... | 218 | Caps | | water pipe..... | 438 | bender..... | 10 |
| Burrs, removing..... | 11 | entrance..... | 77 | Class R fuses, | | bends, number permitted..... | 10 |
| Bus bars..... | 269 | PVC..... | 40 | starters with..... | 409-410 | body covers..... | 64 |
| Bus duct..... | 343-357 | Carpet flanges..... | 156 | Clay conduit..... | 15 | clamps, rigid steel..... | 77 |
| aluminum..... | 346-349 | Carpet pan..... | 335 | Cleanup..... | 8 | EMT..... | 17 |
| circuit breakers..... | 356 | Cartridge fuses..... | 271 | Clear lens luminaires..... | 190 | EMT assemblies..... | 447-450 |
| copper..... | 350-351 | fast acting..... | 304-305 | Clear polycarbonate carpet | | ENT..... | 48 |
| elbows..... | 354 | links..... | 288-290 | flanges..... | 156 | flex aluminum..... | 451-454 |
| feeder..... | 346-347, 350-351 | non-renewable..... | 285-286 | Clio..... | 110, 112 | flex steel..... | 455-458 |
| fittings..... | 354 | non-time delay 291, 293-294, 297 | | Clips | | flexible..... | 28 |
| plug-in..... | 352-353, 356 | renewable..... | 287, 289 | earthquake..... | 159 | galvanized rigid (GRS)..... | 49 |
| reducers..... | 343 | time delay..... | | EMT..... | 27 | galvanized rigid | |
| switches..... | 356 |292, 295-296, 298-303 | | safety..... | 159 | assemblies..... | 463-466 |
| Bushed nipples..... | 71 | Cast aluminum boxes..... | 143-145 | Clock hanger | | gaskets..... | 65 |
| Bushings | | covers..... | 143-144 | receptacles..... | 218, 237 | hubs..... | 443 |
| aluminum..... | 61-62 | gang extension rings..... | 144-145 | Clocks..... | 366 | liquid-tight..... | 33-34 |
| insulated ground..... | 54, 442 | gang weatherproof | | commercial grade..... | 370 | MC..... | 52 |
| plastic..... | 54 | boxes..... | 144-145 | Closed asymmetric lens..... | 188 | PVC..... | 37 |
| reducing..... | 69 | round weatherproof boxes..... | 143 | Coated conduit..... | 13 | PVC assemblies..... | 459-462 |
| Busway..... | 343 | Cast boxes, galvanized..... | 66 | Coaxial cable adapters..... | 537 | PVC coated..... | 78 |
| Butternut..... | 108 | covers..... | 67 | Coaxial communications | | take-off..... | 13 |
| Butternut-XLP..... | 109 | Cast iron floor boxes..... | 153-155 | cable..... | 526-527 | weight per 100'..... | 18 |
| Buzzers..... | 365, 367 | rectangle..... | 154-155 | Coaxial plug..... | 533 | Conduit assemblies | |
| C | | Cast metal | | Cockle..... | 110, 112 | aluminum flex..... | 451-454 |
| Cabinet connectors | | conduit bodies..... | 63 | Code, compliance with..... | 7 | EMT..... | 447-450 |
| duct..... | 336 | entrance elbows..... | 63 | Codes, wire..... | 88 | ENT..... | 48 |
| underfloor raceway..... | 341 | CD-ROM, installing..... | 5 | Collie..... | 109, 111 | GRS..... | 463-466 |
| Cabinets, signal..... | 327 | Ceiling fans..... | 217 | Color coded cable | | PVC..... | 459-462 |
| Cable..... | 88-118 | Ceiling fixtures | | for undercarpet..... | 540 | steel flex..... | 455-458 |
| aluminum..... | 107, 113 | supporting..... | 158 | Colors | | Conduit bodies | |
| armored..... | 103 | wraparound..... | 176 | lighting fixtures..... | 159 | aluminum..... | 65 |
| communications..... | 521-527 | Ceiling mounted fixtures | | wire..... | 92 | cast metal..... | 63 |
| copper..... | 100-104 | incandescent light..... | 161-163 | Combination | | galvanized..... | 63 |
| high voltage..... | 88 | light with canopy..... | 162-163 | AC magnetic starters..... | 404-418 | PVC..... | 41 |
| Local Area Network (LAN)..... | 527 | utility fixture..... | 163 | clips, EMT to strut..... | 26 | PVC coated..... | 81 |
| non-metallic..... | 100 | Ceiling spacers..... | 157 | couplings..... | 36 | Conduit connectors | |
| power..... | 104 | Cellular flooring..... | 520 | plates..... | 261, 263-268 | flex..... | 29-31 |
| safety..... | 159 | Cement asbestos duct..... | 15 | plates, jumbo..... | 267 | squeeze flexible..... | 30 |
| service entrance..... | 101 | Cement, PVC..... | 11 | socket & main breaker..... | 317 | Conduit cutter..... | 10 |
| single conductor..... | 104 | Cenia..... | 110, 112 | starters..... | 404-417 | Conduit, EMT, | |
| | | Centerline clamp cable | | starters, bus duct..... | 357 | assemblies..... | 447-450 |
| | | connectors..... | 532 | Commercial grade | | Conduit flex assemblies..... | 455-458 |
| | | Centrifugal switch..... | 377 | clocks..... | 370 | Conduit hangers, EMT..... | 26 |

| | | | | | | | |
|---|----------------|--|------------|---|--------------|--|--------------|
| Conduit, PVC, assemblies..... | 459-462 | P&C..... | 45, 46 | set screw flex couplings..... | 32 | galvanized rigid (GRS)..... | 49 |
| Conduit, rigid, assemblies..... | | pricing..... | 10 | squeeze flex connectors..... | 29, 30 | intermediate metal (IMC)..... | 52 |
| Conduit spacers..... | 463-466 | PVC coated..... | 81 | Diffusers..... | 159 | ladder tray..... | 363 |
| Conduit system, communications..... | 519 | PVC coated steel..... | 78 | polycarbonate for utility light .. | 164 | louvered cable tray..... | 361 |
| Conduit tables, using..... | 15 | Type EB or DB..... | 45 | Dimmer..... | | 90 degree PVC coated..... | 78 |
| Condulets..... | 12, 121 | underfloor raceway..... | 341 | fluorescent fixtures..... | 159 | PVC..... | 37, 43-45 |
| Connector lugs..... | 118 | Cover markings, handholes..... | 373 | incandescent fixtures..... | 229 | Electrical metallic tubing..... | 10, 17 |
| Connectors..... | 73, 115 | Cover mounted keyless..... | | Dimming switches..... | 229 | Electrician base wage..... | 5 |
| communications cable..... | 532 | fixtures..... | 161 | Disconnect switches..... | 271 | Electrician defined..... | 6 |
| conduit..... | 29 | Cover types, handy box..... | 119 | Distribution section..... | 269 | Electrode, driven..... | 438 |
| data..... | 534 | Covers..... | | Distribution systems, overhead..... | 433 | Elevators, hookup..... | 379 |
| EMT..... | 19-21 | cast aluminum..... | 143 | Doberman..... | 109, 111 | Eleven circuit overhead distribution systems..... | 434 |
| EMT conduit, set screw..... | 447 | conduit bodies..... | 64 | Dolly, reel..... | 92 | Employer's labor burden..... | 5 |
| ENT..... | 48 | floor boxes..... | 154-155 | Dome lights, corridor..... | 370 | EMT clips..... | 26-27 |
| flex..... | 29 | galvanized cast boxes..... | 67 | Door openers..... | 371 | conduit..... | 17 |
| flexible metal conduit..... | 11 | GFI..... | 121 | Door switch..... | 371 | conduit assemblies..... | 447-450 |
| insulated..... | 115 | handy box..... | 123 | Door trip, intrusion detector..... | 371 | conduit fittings..... | 18 |
| RG/U cable..... | 535-536 | octagon box..... | 126 | Double conductor lugs..... | 118 | conduit hangers..... | 26 |
| screw-on..... | 115 | outlet box..... | 120, 128 | Double face exit fixtures..... | 173 | couplings..... | 22 |
| self-stripping..... | 115 | precast concrete boxes..... | 373 | Double throw safety switches..... | 282 | described..... | 10 |
| split bolt..... | 116 | round..... | 136, 144 | Drilling, light standard foundation..... | 421 | elbows..... | 19, 27 |
| steel set screw..... | 74 | square..... | 136 | Drive-on EMT couplings..... | 22 | fittings..... | 10, 18 |
| telephone cable..... | 534 | steel raceway..... | 426 | Drop cord power..... | 343 | gasketed pulling elbows..... | 27 |
| twinaxial cable..... | 537 | surface, raised..... | 130-131 | Dropouts..... | | hand benders..... | 27 |
| two bolt..... | 117 | Crew size..... | 6 | ladder tray..... | 364 | hangers..... | 26 |
| two-way..... | 116 | Crimp snap, hardware for..... | 528-529 | louvered cable tray..... | 362 | installation guidelines..... | 11 |
| wire..... | 115-117 | Criollo..... | 110, 112 | Drum fixtures..... | 165 | malleable entrance caps..... | 27 |
| with spacers..... | 117 | Cross, bus duct..... | 354 | Dry type transformers..... | 332-334 | nail straps..... | 24 |
| Conservation of energy..... | 157 | Crown plugs, brass..... | 156 | Dual element plug fuses..... | 283-284 | 90 degree die cast elbows..... | 27 |
| Consistency on take-offs..... | 15 | Current limiting fuses..... | 291-305 | Duct..... | | pulling elbows..... | 27 |
| Construction grade flex conduit..... | 33 | Cutter, conduit..... | 10 | blank..... | 336, 337 | split adapters..... | 27 |
| Contactors, magnetic..... | 389-397 | Cutting..... | | bus..... | 346-353 | steel tube..... | 10 |
| Contacts, communications cable..... | 528 | concrete or masonry..... | 16 | coupling..... | 336 | straps..... | 24 |
| Continental lampholder..... | 168-169 | GRS..... | 12 | elbows..... | 336 | supporting..... | 11 |
| Control devices..... | 383 | oil..... | 12 | end bells, P&C..... | 47 | thin wall..... | 10 |
| Control panel, mechanical..... | 380 | PVC..... | 11 | feeder..... | 336 | to couplings..... | 24 |
| Control stations..... | 418-419 | Cylinder lampholder..... | 170 | heaters, hookup..... | 379 | to strut combination clips..... | 26 |
| Convenience outlets..... | 218 | D | | lines..... | 335 | Enamel spray paint..... | 429 |
| Converse..... | 113 | Damp locations, fluorescent fixtures for..... | 176 | materials, underfloor..... | 335 | Enclosed fixtures..... | 183 |
| Conversion table, copper/aluminum..... | 537 | Data cable connectors..... | 532 | P&C..... | 45 | Enclosed-gasketed fixtures..... | 176 |
| Convex glass lens..... | 192 | Data connectors..... | 534 | plugs, P&C..... | 46 | Enclosed indoor ballasts..... | 194 |
| Conveyor control panels, hookup..... | 379 | DB P&C duct..... | 12 | plugs, underfloor raceway..... | 341 | Enclosures, circuit breaker..... | 315-316 |
| Conveyors, hookup..... | 379 | DC breakers..... | 309-310 | sections..... | 337 | End bells installing..... | 373 |
| Cooling towers, hookup..... | 379 | DC horns..... | 368 | staking..... | 338 | PVC..... | 40 |
| Copper..... | | Decorative ceiling fans..... | 217 | supports..... | 336, 340 | End caps ladder tray..... | 363 |
| building wire..... | 89, 93-96, 442 | Decorator plates..... | 263-264 | Duplex decorator receptacles..... | 245 | louvered cable tray..... | 361 |
| bus duct..... | 350-351 | jumbo..... | 267 | Duplex receptacles..... | 239-243 | End closures, bus duct..... | 355 |
| conductor lugs..... | 118 | Decorator switches..... | 229-233 | commercial..... | 239-241 | End-of-row cap..... | 158 |
| connections, exothermic..... | 445 | Decorator track fixture..... | 170 | assemblies..... | 515, 517 | Energy conservation..... | 157 |
| flexible cords..... | 96-99 | Deep switch plates..... | 267 | grounded..... | 240-243 | Energy consumption monitoring..... | 365 |
| ring as ground..... | 439 | Deep-cut trim plates..... | 221 | hospital..... | 240-243 | Energy saving lamps | 208, 211-212 |
| service entrance cable..... | 100 | Defects..... | 8 | receptacle plates..... | 261- 262 | ENT conduit and fittings..... | 48 |
| wire connector lugs..... | 118 | Delivery costs, material..... | 5 | residential..... | 239 | Entrance cable..... | 107 |
| Copper-clad ground rods..... | 444 | Demobilization..... | 7 | specification..... | 239, 241-243 | caps..... | 77 |
| Cords, flexible..... | 89, 96-99 | Detectors..... | 371 | underfloor raceway..... | 342 | elbows, cast metal..... | 63 |
| Corridor dome lights..... | 370 | Device plates..... | 221 | Duplex service drop..... | 109 | hubs, duct..... | 336 |
| Corridor fixtures, wraparound... | 176 | Devices, EXO..... | 271 | Duplex switches..... | 233-234 | lights..... | 165 |
| Corrosive locations, conduit for..... | 15 | Dewatering..... | 420 | single pole..... | 233-234 | Entry control systems..... | 366, 372 |
| Cost multiplier..... | 6 | Die cast..... | | switch with grounding receptacle..... | 239-246 | Entry release switch..... | 372 |
| Cost tables, adjusting..... | 92 | bushed nipples..... | 71 | three-way switches..... | 233-234 | EPR cable..... | 104 |
| Costena..... | 111, 112 | compression EMT couplings..... | 23 | E | | Equipment grounding conductors..... | 440 |
| Costs, additional..... | 6 | duplex flex connectors..... | 29 | Earthquake clips..... | 159 | Equipment hookup..... | 377, 379-381 |
| Couplings..... | 73 | EMT connectors..... | 19-22 | Earthquake considerations..... | 157 | Escutcheon..... | 157 |
| calculating quantity..... | 13 | flex connectors..... | 31 | Earthwork..... | 420 | Estimating access boxes..... | 374 |
| duct..... | 336 | gasketed pulling elbows, EMT..... | 27 | EB P&C duct..... | 12 | accuracy..... | 7 |
| ENT..... | 48 | insulated bushed nipples..... | 71 | Edge-type beam clamps..... | 80 | bus duct..... | 345 |
| flex to EMT..... | 32 | insulated connectors..... | 29, 30, 35 | Elbows..... | | cable tray..... | 360 |
| flex to rigid..... | 32 | liquid-tight flex connectors..... | 35 | aluminum..... | 58 | lighting fixtures..... | 159 |
| flexible conduit..... | 32 | offset nipples..... | 73 | bus duct..... | 354 | pitfalls..... | 16 |
| GRS..... | 51 | screw-in flex connectors..... | 29 | duct..... | 336 | service equipment..... | 273 |
| malleable threadless..... | 73-74 | screw-in flex couplings..... | 32 | EMT..... | 18 | Estimating Electrical Construction..... | 9 |
| malleable three piece..... | 72 | set screw EMT couplings..... | 22 | entrance..... | 63 | | |
| | | | | 45 degree IMC..... | 52 | | |
| | | | | galvanized capped..... | 65 | | |

| | |
|---|----------|
| Estimating software, installing | 5 |
| Evaporative coolers, hookup | 379 |
| Excavation | 15, 420 |
| access box | 373 |
| takeoff | 420 |
| Exhaust fans, hookup | 379 |
| Exit fixtures | 171-173 |
| EXO devices | 271 |
| Exothermic copper connections | 445 |
| Exothermic weld | 441 |
| Expandable bar hangers | 126 |
| Expanded metal tray | 519 |
| Expansion | |
| anchors | 86 |
| couplings | 39-40 |
| fittings | 68 |
| joint, bus duct | 355 |
| Experience, allowance for | 6 |
| Explosion proof horn sirens | 368 |
| Exposed conduit | 16 |
| Exterior fixtures | |
| entrance fixture | 165 |
| floodlights | 185, 187 |
| walkway luminaires | 191 |
| Exterior weatherproof | |
| potted ballast | 194 |
| Externally operated devices (EXO) | 271 |

F

| | |
|---|------------------|
| F type connectors for | |
| RG/U cable | 536 |
| Fan coil units, hookup | 379 |
| Fans, ceiling | 217 |
| Fast acting fuses | 304-305 |
| Fast installation, fixtures for | 184 |
| Feeder breaker | 271 |
| Feeder bus duct | 346-347, 350-351 |
| Feeder circuits, aluminum wire | 91 |
| Feeder duct, blank | 336 |
| Female adapters (FA) | 46 |
| Female conduit unions, | |
| PVC coated | 80 |
| Fender washers | 86 |
| Ferrule type fuses | 285-303 |
| Fiber duct | 15 |
| Fiberglass | |
| box covers | 136 |
| outlet boxes | 121, 133-139 |
| switch boxes | 143-145 |
| Field programmable cable connectors | 532 |
| Fig | 108 |
| Fig-XLP | 109 |
| Filbert | 108 |
| Filbert-XLP | 109 |
| Finish color, lighting fixtures | 159 |
| Fire alarm breaker | 272 |
| Fire resistance | 335 |
| Fire stop fitting, bus duct | 345 |
| Fish tape | 91 |
| leader | 423 |
| Fishing vacuum | 91 |
| Fittings | |
| aluminum tray | 364 |
| ARC | 58 |
| bus duct | 354 |
| cable tray | 361 |
| communications cable | 528-537 |
| EMT conduit | 18 |
| ENT conduit | 48 |
| expansion | 68 |
| hanger | 86 |
| louvered tray | 361 |
| P&C | 45-47 |
| PVC | 38 |
| PVC coated | 78 |

| | |
|--|---------------|
| service | 342 |
| steel channel system | 432 |
| steel overfloor raceway | 429 |
| steel raceway | 431, 435 |
| steel surface raceway | 426-428 |
| two piece raceway | |
| assembly | 430 |
| underfloor duct | 336 |
| underfloor raceway | 341 |
| wireway | 330 |
| Five pole contactors | 396-397 |
| Fixed-temperature detectors | 366 |
| Fixture tests | 8 |
| Fixture whips | 434 |
| Fixture wire | 88 |
| Fixtures | |
| estimating | 159 |
| exit | 171-173 |
| floodlights | 185-189 |
| fluorescent | 174-180 |
| HID | 181-194 |
| incandescent | 161-165 |
| lighting | 157-218 |
| track light | 168-171 |
| FLA (full load ampere) | |
| rating | 378 |
| Flanged end, bus duct | 354 |
| Flanges, carpet | 156 |
| Flashing beacons | 369 |
| Flat elbows, bus duct | 354 |
| Flat glass lens, | |
| HID fixtures | 188, 191, 192 |
| Flex conduit assemblies | |
| aluminum | 451-454 |
| steel | 455-458 |
| Flexible conduit | 28 |
| cutting | 11 |
| liquid-tight | 33-34 |
| Flexible conduit connectors | 29-32 |
| liquid-tight | 34-35 |
| Flexible conduit couplings | 32 |
| Flexible cords | 89, 91, 96-99 |
| restrictions on use | 90 |
| Flexible metallic tubing | 15 |
| Floodlights | |
| adjustable | 164 |
| exterior | 187 |
| heavy duty | 185 |
| without poles | 186 |
| Floor box | |
| accessories | 156 |
| covers | 155 |
| Floor boxes | 153-155 |
| cast iron | 154-155 |
| outlet boxes, round | 153 |
| semi-adjustable | 153-155 |
| Floor mat | 371 |
| Flow switches, hookup | 379 |
| Fluorescent dimming | |
| switches | 229 |
| Fluorescent fixtures | 174 |
| aluminum frame | 177 |
| assemblies | 518 |
| ballasts | 213-216 |
| damp or wet locations | 176 |
| ganging | 158 |
| Fluorescent lamps | 201, 210-212 |
| Flush mounted | |
| push buttons | 370 |
| screw cover boxes | 146-147 |
| starters | 384-385 |
| Flush plugs, brass | 156 |
| Flush starters | 386 |
| Foundations, light standards | 421 |
| Four circuit overhead | |
| distribution systems | 433-434 |
| Four lamp fluorescent | |
| fixtures | 176 |
| Four pole AC magnetic contactors | 394-395 |

| | |
|------------------------------|-----------------------|
| Framed Troffer lay-in T-bar | |
| fixtures | 177 |
| Frequency generator | 366 |
| Fringe benefits | 5 |
| Full load ampere (FLA) | 378 |
| Furnaces, hookup | 379 |
| Furring channels | 158 |
| Fuse ampereage, fusible | |
| switches | 271 |
| Fuses, cartridge | |
| current limiting | 296-305 |
| fast acting | 304-305 |
| links | 288-290 |
| non-renewable | 285-286 |
| non-time delay | 291, 293-294, 297 |
| renewable | 287, 289 |
| time delay | 292, 295-296, 298-303 |
| Fuses, plug | 283-284 |
| Fusible disconnect, | |
| starters with | 406-418 |
| Fusible plug-in switches, | |
| bus duct | 356 |
| Fusible switches | 271 |

| | |
|---------------------------|---------|
| Fuses, plug | 283-284 |
| Fusible disconnect, | |
| starters with | 406-418 |
| Fusible plug-in switches, | |
| bus duct | 356 |
| Fusible switches | 271 |

G

| | |
|------------------------------------|--------------|
| Galvanized | |
| box covers | 67 |
| cable tray | 361 |
| capped elbows | 65 |
| cast boxes | 66 |
| conduit assemblies | 463-466 |
| conduit bodies | 63 |
| expansion fittings | 68 |
| messenger strand | 114 |
| trim plates | 221 |
| Galvanized rigid steel (GRS) | 12 |
| conduit | 49 |
| conduit assemblies | 463-466 |
| couplings | 51 |
| elbows | 49-51 |
| hand benders | 52 |
| locknuts | 54 |
| nipples | 55-57 |
| terminations | 52 |
| Galvanized steel | |
| messenger strand | 114 |
| Ganged boxes and rings | 132 |
| Ganging fluorescent fixtures | 158 |
| Gasketed pulling elbows, EMT | 27 |
| Gaskets, conduit body | 65 |
| Gauge, wire | 88 |
| Gender changer, cable | |
| connector | 532 |
| General duty safety switches | 275 |
| General purpose control | |
| stations | 418-419 |
| Generators, standby | 365 |
| GFCI duplex receptacles | 246 |
| Government work, bidding | 9 |
| Ground | |
| bushing | 62, 441, 442 |
| clamp hub | 438 |
| megger | 440 |
| pipe | 438 |
| rod | 438, 444 |
| rod clamp | 444 |
| rod couplings | 444 |
| rod stud bolts | 444 |
| testing | 440-441 |
| Ground fault circuit | |
| interrupter (GFI) | |
| covers | 121 |
| definition | 440 |
| duplex receptacles | 246 |
| Grounded | |
| conductor | 439 |
| duplex receptacles | 240-243 |

| | |
|------------------------------|----------|
| spec grade receptacles | 240 |
| side-wired receptacles | 237 |
| switches | 223-236 |
| switches, key operated | 235 |
| Grounding | |
| built-in | 218 |
| conductors | 439 |
| connection | 441 |
| definitions | 439-440 |
| electrode conductors | 439 |
| jumper | 442 |
| locknuts | 445 |
| problems | 441 |
| receptacles | 237-248 |
| requirements | 438-441 |
| Grullo | 111, 112 |
| Guard | |
| heat | 167 |
| lighting fixture | 159 |

H

| | |
|----------------------------------|-------------------|
| Hackney | 111, 112 |
| Hand benders | |
| EMT | 27 |
| GRS | 52 |
| Handholes | 373, 375 |
| Handy boxes | 123 |
| covers | 123 |
| description | 119 |
| receptacle assemblies | 508-509 |
| switch assemblies | 467-470 |
| Hanger spacing, cable tray | 358 |
| Hangers | |
| bar, adjustable | 129 |
| bolt, tomic | 132 |
| bus duct | 345 |
| EMT | 26 |
| fittings | 86 |
| ladder tray | 364 |
| louvered cable tray | 362 |
| Hard service cord | 88 |
| Harness, wire, overhead | |
| distribution systems | 433 |
| Hazardous conditions | 119, 121 |
| HDE contacts | 528 |
| Heat guard | 167 |
| Heat-recovery fixtures | 178-179 |
| Heavy duty | |
| control stations | 418-419 |
| EMT straps | 25 |
| floodlights | 185 |
| receptacles, spec grade | 246 |
| safety switches | 276-281 |
| spec grade switches | 230 |
| Hickory | 108 |
| Hickory-XLP | 109 |
| High ampereage current, | |
| distributing | 343 |
| High bay lighting | 425 |
| High bay open reflector | |
| fixtures | 182 |
| High intensity discharge (HID) | |
| fixtures | |
| area lighting | 188 |
| floodlights | 185-187, 189, 191 |
| luminaires | 184, 190-192 |
| recessed | 181-183 |
| street lighting | 194 |
| walkway fixtures | 190 |
| wall fixtures | 190 |
| High intensity discharge | |
| (HID) lamps | 204-207 |
| ballasts | 205-207, 209 |
| core and coil | 209 |
| High output (HO) lamps | 211 |
| High-potential test | 90 |
| High pressure sodium | |
| ballasts | 209 |
| lamps | 208 |
| lights | 186 |

| | | | | | | | |
|---|-------------------|---------------------------------|---------------|------------------------------------|--------------|-----------------------|--------------|
| High-tech building management systems | 365 | Insulation | | HID | 204-207 | Low-pressure sodium | |
| High time clause | 16 | asbestos | 89 | incandescent | 200-203 | lamps | 208 |
| High voltage wire and cable | 88 | heavy | 96 | LED | 199-200, 203 | lights | 186, 190 |
| splicing | 90 | kit | 540 | mercury vapor | 204 | Lugs | |
| Hinged cover wireway | 329 | thermoplastic | 88 | quartz | 203 | copper wire | 118 |
| Hinged pull boxes | 147-151 | Types A and B | 88 | sodium | 208 | solder type | 118, 443 |
| Hinged square poles | 196 | Insurance | 5 | special voltage | 201-203 | solderless type | 118, 443 |
| Holes in concrete or masonry | 16 | Intermediate metal | | standard voltage | 200-203 | Luminaires | 184, 190-192 |
| Hollins | 113 | conduit (IMC) | 52 | tubular quartz | 203 | | |
| Hook stick | 343 | couplings | 53 | LAN (Local Area Network) | | | |
| Hookup | | elbows | 52-53 | cable | 527 | | |
| kitchen equipment | 378, 380 | running thread | 53 | Large radius elbows (GRS) | 50-51 | | |
| mechanical equipment | 378, 380 | Intermediate type spacers | 47 | Layout, cable tray | 359 | | |
| motor | 379 | Interrupt capacity | 306 | LED | 199-200, 203 | | |
| standby generator | 381 | Intrusion detectors | 366, 371 | Lens | | | |
| Horizontal elbows, underfloor | | Ionization detectors | 366 | clear | 190 | | |
| raceway | 341 | Isolated ground | | closed asymmetric | 188 | | |
| Horizontal pole-mounted | | receptacles | 237, 240, 242 | convex glass | 192 | | |
| floodlights | 186 | | | flat | 188, 192 | | |
| Horn sirens | 368 | | | prismatic | 190 | | |
| Horns | 365, 368 | | | vandal-resistant | 180 | | |
| Horsepower rated | | | | Leveling | | | |
| starters | 386 | | | cable tray | 358 | | |
| switches | 228-229 | | | duct | 340 | | |
| Hospital grade | | | | underfloor raceway | 342 | | |
| receptacles | 237, 240-243, 246 | | | Light fixtures | 157-218 | | |
| Hot box | 11 | | | bathroom | 164 | | |
| HP rated manual motor | | | | ceiling mounted | | | |
| starters | 388-389 | | | incandescent | 162 | | |
| Humidistat, hookup | 379 | | | ceiling mounted | | | |
| Hunter | 113 | | | with canopy | 162-163 | | |
| | | | | commercial | 157 | | |
| | | | | estimating | 157, 159-160 | | |
| | | | | exit lighting | 171-173 | | |
| | | | | finish color | 159 | | |
| | | | | floodlights | 185-191 | | |
| | | | | fluorescent | 174-180 | | |
| | | | | guards | 159 | | |
| | | | | HID | 181-194 | | |
| | | | | high bay | 425 | | |
| | | | | incandescent | 161-167 | | |
| | | | | mounting height | 158 | | |
| | | | | pricing services | 159 | | |
| | | | | retrofit | 183 | | |
| | | | | surface mounted | | | |
| | | | | incandescent | 161 | | |
| | | | | suspension system | 158 | | |
| | | | | track lights | 168-171 | | |
| | | | | Light poles | 195-198 | | |
| | | | | Light track, surface mounted | 168 | | |
| | | | | Lighted handle switches | 229 | | |
| | | | | Lighted knob incandescent | | | |
| | | | | dimmers | 229 | | |
| | | | | Lightning | 438 | | |
| | | | | Links, cartridge fuse | 288-290 | | |
| | | | | Linnet | 114 | | |
| | | | | Liquid-tight | | | |
| | | | | flex conduit | 15, 33-34 | | |
| | | | | flex connectors | 34-36 | | |
| | | | | flex to rigid combination | | | |
| | | | | couplings | 36 | | |
| | | | | Listings, subcontractor | 9 | | |
| | | | | Loadcenters | 272, 322-324 | | |
| | | | | Local Area Network (LAN) | | | |
| | | | | cable | 527 | | |
| | | | | Locating duct inserts | 337 | | |
| | | | | Locking receptacle, steel | | | |
| | | | | channel system | 432 | | |
| | | | | Locking receptacles | 219, 253-254 | | |
| | | | | Locknuts | | | |
| | | | | aluminum | 61 | | |
| | | | | grounding | 445 | | |
| | | | | GRS | 54 | | |
| | | | | Lockup boxes | 7 | | |
| | | | | Louvered cable tray | 361 | | |
| | | | | fittings | 361-362 | | |
| | | | | Low bay open reflector | | | |
| | | | | fixtures | 183 | | |
| | | | | Low voltage protection, | | | |
| | | | | starters | 388-389 | | |

| | |
|-----------------------------------|----------|
| Megger, ground | 440 |
| Mercury switches | 219 |
| Mercury vapor | |
| ballasts | 206 |
| floodlights | 185-191 |
| HID fixtures | 181-184 |
| lamps | 204, 206 |
| luminaires | 184, 192 |
| street lights | 193-194 |
| Merlin | 114 |
| Messenger strand | 114 |
| Metal conduit, flexible | 11 |
| Metal halide | |
| ballasts | 207 |
| lamps | 205, 207 |
| floodlights | 185-191 |
| HID fixtures | 181-184 |
| lamps | 206 |
| luminaires | 184, 192 |
| street lights | 193-194 |
| Metal wireway, | |
| communications | 519 |
| Metallic outlet boxes | 441 |
| Metallic raceway, grounding | 439 |
| Meter centers | 318-321 |
| Meter sockets | 272, 317 |
| Mobilization | 7 |
| Modular couplers | 534 |
| Modular keystone jacks | 534 |
| Modulating valves, hookup | 380 |
| Mogul aluminum conduit | |
| bodies | 65 |
| Moisture-resistant | |
| thermoplastic | 88 |
| Momentary contact | |
| switches | 235 |
| Momentary control switch | 382 |
| Monmouth | 113 |
| Monorail trolley, hookup | 380 |
| Montclair | 113 |
| Motion detectors | 366 |
| Motivating employees | 7 |
| Motor control center (MCC) | 383 |
| Motor control equipment | 382-419 |
| Motor control stations | 418-419 |
| Motor rotation, reversing | 377 |
| Motor starters, manual | 384 |
| Motorized valves, hookup | 380 |
| Motors | 377 |
| hookup | 379 |
| types | 378 |
| Mounting height, lighting | |
| fixtures | 158 |
| Mouse | 91 |
| MTW type wire | 88, 95 |
| Multi-conductor | |
| communications cable | 523-525 |
| Multi-gang masonry boxes | 132 |
| Multi-gang switch boxes | 121 |
| Multi-outlet strips, colors | |
| available | 424 |
| Multi-outlet systems | 424 |
| Murex | 109, 111 |
| Mustang | 110, 112 |

N

| | |
|--------------------------------------|----------------|
| N type connectors for | |
| RG/U cable | 536 |
| Nassa | 109, 111 |
| National Electrical | |
| Code (NEC) | 10, 88-89, 438 |
| National Estimator, installing | 5 |
| Necking, manhole | 376 |
| NEMA | |
| cable tray | 358 |
| Class 1 pull boxes | 146-148 |
| Class 3R pull boxes | 148-150 |

| | |
|---------------------------------|-------------------|
| magnetic starters | 382 |
| safety switches | 271 |
| Neritina | 110, 112 |
| Neutral | |
| ACSR | 111, 112 |
| aluminum | 109, 111-112 |
| reduced | 112 |
| Nipples | |
| aluminum | 58-61 |
| bushed | 71 |
| GRS | 55 |
| offset | 72 |
| NM type cable | 89, 98-100 |
| Non-adjustable cast iron | |
| floor boxes | 153 |
| Non-fused disconnect, | |
| starters | 404-405, 411 |
| Non-fused safety switches | 275 |
| Non-fusible switches | 271 |
| Non-metallic | |
| cable | 100 |
| conduit, ENT | 48 |
| conduit spacers | 76 |
| conduit, Type CN-P | 34 |
| outlet boxes | 121 |
| sheathed cable | 89, 98-102 |
| Non-renewable fuses | 285-286 |
| Non-time delay | |
| fuses | 291, 293-294, 297 |

O

| | |
|--------------------------------|---------------|
| Octagon boxes | 120, 125-126 |
| covers | 126 |
| Off-street area lighting | 188 |
| Offset bar hangers | 126 |
| Offset elbows, underfloor | |
| raceway | 341 |
| Offset nipples | |
| die cast | 73 |
| malleable | 72 |
| Offsets, described | 10 |
| Oldenberg | 110, 112 |
| Olive | 108 |
| Olive-XLP | 109 |
| On-site storage | 7 |
| One circuit overhead | |
| distribution systems | 433 |
| One gang floor boxes | 154 |
| One gang masonry boxes | 132 |
| One gang switch | |
| assemblies | 487-489 |
| One hole EMT straps | 24 |
| One level junction boxes | 339-340 |
| One piece raceways | |
| sizes | 423 |
| steel | 426 |
| Opal globe utility fixture | |
| ceiling mounted | 163 |
| wall mounted | 164 |
| Open luminaires | 188 |
| Open reflector fixtures | 182 |
| Open type contactors | |
| five pole | 397 |
| four pole | 396 |
| three pole | 393 |
| two pole | 389-391 |
| Open type starters | 385, 399, 403 |
| HP rated | 386 |
| Orange, code name | 108 |
| XLP | 109 |
| Orange face receptacles | 253-254 |
| Ought scale | 88 |
| Outlet box covers | 120, 128, 136 |
| Outlet boxes | 133-139, 153 |
| concrete | 126 |
| fiberglass | 133 |
| handy | 123 |

| | |
|-------------------------------|------------------|
| installation labor | 122 |
| number of wires allowed | 121 |
| sectional switch | 123 |
| size to use | 122 |
| special | 121 |
| square | 127 |
| takeoff | 121 |
| Outlet receptacles | 237-242, 336 |
| Overcurrent devices | 438 |
| Overfloor raceway, steel | |
| boxes | 427 |
| fittings | 426 |
| raceway | 424, 426 |
| Overhead costs | 5 |
| Overhead distribution | |
| systems | 433 |
| Overhead door, hookup | 380 |
| Overhead service, | |
| sockets for | 317 |
| Overload protection | 271 |
| motors | 377 |
| Overload relays | |
| motor starters | 385 |
| starters with | 388-389, 404-418 |
| Oversize plates | 221 |
| Oxidation | 91 |
| Oyster | 109, 111 |

P

| | |
|-----------------------------------|--------------|
| P&C | |
| couplings | 46 |
| duct | 12, 45 |
| elbows | 45, 46 |
| end bells | 47 |
| female adapters (FA) | 46 |
| fittings | 46 |
| plugs | 46 |
| Pace | 113 |
| Pad mount transformer | |
| slabs | 374, 376 |
| Paging systems | 365 |
| Paint, spray enamel | 429 |
| Palomino | 111, 112 |
| Paludina | 110, 112 |
| Pancake box | 120 |
| Panel or box adapter | |
| ladder tray | 363 |
| louvered cable tray | 361 |
| Panelboards | 272, 324-327 |
| circuit breaker | 325-326 |
| rating | 272 |
| Par38 lamp, lampholder for | 168 |
| Parachute | 91 |
| Parallel beam clamps | 79 |
| Partridge | 114 |
| Peach | 108 |
| Peach-XLP | 109 |
| Pear | 107 |
| Pear-XLP | 108 |
| Pecan | 108 |
| Pecan-XLP | 109 |
| Pedestals | 541 |
| Pedestals for power | 541 |
| Pekingese | 109, 111 |
| Percheron | 110, 112 |
| Periwinkle | 110, 112 |
| Permits, temporary power | 7 |
| Photo controls | 259 |
| Photocell controlled lights | 188 |
| Photoelectric switches | 221 |
| tungsten | 223 |
| Pigeon | 114 |
| Pignut | 108 |
| Pignut-XLP | 109 |
| Pigtail plug | 533 |
| Pilot switches | 232 |
| Pins, cable contacts | 528 |
| Pinto | 110, 112 |

| | |
|----------------------------------|------------------|
| Pipe adapters, underfloor | |
| raceway | 341 |
| Pipe inserts, underfloor | |
| raceway | 341 |
| Pit excavation | 422 |
| Pitfalls, estimating | 16 |
| Plaster | |
| frames | 158 |
| ring | 119, 121 |
| Plastic | |
| blank covers | 142 |
| boxes | 140-142 |
| bushings | 54 |
| locking connectors | 255-256 |
| locking plugs | 257-258 |
| pull lines for conduit | |
| assemblies | 447-450 |
| spacers | 47 |
| switch rings | 142 |
| Plate electrodes | 439 |
| Plates | 260 |
| amp size | 267-268 |
| blank | 261-263 |
| combination | 261, 263-268 |
| decorator | 263-264 |
| deep | 267 |
| jumbo | 267 |
| receptacle | 261-262, 265-268 |
| semi-jumbo | 266 |
| switch | 260-267 |
| telephone | 263 |
| weatherproof | 268 |
| Plug-in bus duct | |
| aluminum | 348-349 |
| copper | 350-353 |
| units | 356-357 |
| Plug-in devices | |
| breakers, loadcenter | 324 |
| fittings | 354-355 |
| switches | 356-357 |
| Plug fuses | 283-284 |
| Plugs | |
| communications cable | 533 |
| duct | 336 |
| PVC | 40 |
| Plum | 108 |
| Plum-XLP | 109 |
| Plumber's perforated | |
| metal tape | 11 |
| Pneumatic switches, hookup | 380 |
| Pole mounted | |
| floodlights | 186-187, 189 |
| Poles | 186 |
| aluminum | 196-198 |
| steel | 195-196 |
| street light | 195 |
| telephone-power | 424, 436-437 |
| Polycarbonate diffuser | 164 |
| Polyvinyl chloride conduit | 11 |
| Porcelain receptacles | 161 |
| Portunas | 109, 111 |
| Potted ballasts | 194 |
| Power cable | 104 |
| Power cord connectors | 249 |
| Power cord plugs | 250-252 |
| Power cord receptacles | 248-249 |
| Power duct | 339 |
| Power groove lamps | 212 |
| Power intrafacer | 541 |
| Power systems equipment, | |
| illustration | 270 |
| Power taps, | |
| steel channel system | 432 |
| Power, temporary | 6 |
| Pratt | 113 |
| Precast concrete access | |
| boxes | 373-376 |
| Preheat lamps | 210 |
| Pressure switches | 366 |
| hookup | 380 |

| | |
|--|--------------|
| Prewired duplex receptacles | 239-248 |
| Prewired fixture housings .. | 166-167 |
| Prewired switches..... | 223-232 |
| Prices, adjusting | 222 |
| Pricing | |
| access boxes | 374 |
| wiring devices | 221 |
| Pricing service, lighting fixtures..... | 159 |
| Printing National Estimator instructions | 5 |
| Prismatic lens | |
| fixtures | 181 |
| luminaires | 190 |
| Productivity factors | 7-8 |
| Profit | 5, 7 |
| Public address systems..... | 365 |
| Pull boxes | |
| hinged..... | 147-152 |
| NEMA Class 1 | 146-148 |
| NEMA Class 3R..... | 148-150 |
| raintight | 148-150 |
| Pull line for conduit assemblies..... | 447-466 |
| Pull rate | 91 |
| Pulley, wire | 423 |
| Pulling | |
| elbows, EMT | 27 |
| wire | 91 |
| Pump control panels, hookup .. | 380 |
| Push button stations..... | 418-419 |
| Push buttons, signal .. | 366, 370-371 |
| Push on-off dimmers | 229 |
| PVC | |
| bending..... | 11 |
| boxes | 43 |
| caps | 40 |
| conduit | 37 |
| conduit assemblies | 459-462 |
| conduit bodies | 41-42 |
| couplings, expansion | 39-40 |
| covers | 43 |
| described | 11 |
| elbows | 37-38, 43 |
| end bells | 40 |
| fittings | 38 |
| junction boxes..... | 43 |
| outlet boxes | 121 |
| plugs | 40 |
| reducing bushings | 41 |
| service entrance caps..... | 42 |
| PVC coated | |
| beam clamps | 79-80 |
| clamps | 79-80 |
| conduit | 78 |
| conduit bodies | 81-82 |
| conduit unions | 80 |
| couplings | 81 |
| couplings, steel..... | 78 |
| covers | 82 |
| fittings | 78 |
| junction boxes..... | 83-84 |
| sealing fittings..... | 84-85 |
| straps | 79 |
| U-bolts | 80 |
| PVC jacketed communications cable | 521-525 |

Q

| | |
|----------------------|--------------|
| Quadruplex..... | 111-112 |
| service drop | 110 |
| Quail | 114 |
| Quality control..... | 8 |
| Quartz lamps | 203 |
| Quiet switches | 223-227, 230 |
| Quince | 108 |
| Quince-XLP | 109 |

R

| | |
|---|------------------|
| R14 lamp, lampholder for | 169 |
| R20 lamp | |
| continental lampholder for | 168-169 |
| decorator track fixture for..... | 170 |
| petite cylinder lampholder for | 169 |
| R30 lamp | |
| continental lampholder for | 169 |
| shielded universal lampholder for..... | 168 |
| stepped base lampholder for .. | 171 |
| R40 lamp | |
| continental lampholder for | 169 |
| shielded universal lampholder for..... | 168 |
| stepped base lampholder for .. | 171 |
| Raceway | |
| defined..... | 10 |
| fittings, underfloor | 341 |
| steel | 431 |
| surface..... | 423-437 |
| surface, steel | 426 |
| underfloor | 335-342 |
| Radio suppressors..... | 159 |
| Raintight meter centers | 321 |
| Raintight pull boxes | 148-150 |
| Raised box covers | 131 |
| Ramapo | 113 |
| Rapid-start lamps | 210 |
| Rate-of-rise detectors..... | 366, 371 |
| Raven | 114 |
| Receptacle and handy box assemblies..... | 508-509 |
| Receptacle and sectional box assemblies..... | 510-513 |
| Receptacle assemblies..... | 508-517 |
| duplex | 515, 517 |
| single | 514, 516 |
| Receptacle | |
| plates | 261-262, 265-268 |
| weatherproof | 268 |
| Receptacles 119, 237-249, 253-254 | |
| duplex | 239-243 |
| single | 237-238 |
| Recessed fixtures | |
| door | 181 |
| fluorescent | 177 |
| HID | 181-183 |
| incandescent | 166-167 |
| Rechargeable batteries, exit fixtures | 172 |
| Rectangular floor box covers.... | 155 |
| Rectangular floor boxes | |
| cast iron | 155 |
| sheet metal | 154 |
| Red neon pilot switches..... | 233 |
| Reduced neutral | 112 |
| Reduced wall conduit, flex, aluminum or steel | 28 |
| Reducers, bus duct..... | 343, 355 |
| Reducing | |
| bushings | 69-70 |
| bushings, PVC | 41 |
| couplings, PVC coated | 81 |
| underfloor raceway | 341 |
| voltage drop | 14 |
| washers | 70 |
| Refrigeration, hookup | 380 |
| Regis | 113 |
| Reinforcing, overfloor raceway | 424 |
| Remote ballasts..... | 159 |
| Renewable cartridge fuses | 287, 289 |
| Rental equipment, earthwork.... | 420 |
| Residential switches | 223 |
| Restrictions | |
| conduit | 11 |
| use of armored cable | 88 |

| | |
|---------------------------------------|----------|
| Retrofit fixtures, recessed HID | 182-183 |
| Retrofitting for communications..... | 520 |
| Reversing motor rotation | 377 |
| Reversing starters | 388-389 |
| RG/U cable, plug connectors for..... | 535-536 |
| Right angle beam clamps | 79 |
| Rigid conduit..... | 49 |
| aluminum | 58 |
| assemblies..... | 463-466 |
| elbows | 49-50 |
| terminations | 52 |
| Rigid steel | |
| conduit clamps..... | 77 |
| conduit, galvanized..... | 49 |
| couplings (IMC) | 53 |
| nipples | 55-57 |
| Rings | |
| gang extension | 144-145 |
| plastic switch | 142 |
| switch | 129 |
| RJ11 jack | 533 |
| RJ45 plug and jack | 533 |
| Roadway luminaires | 193 |
| Rock outcrop | 420 |
| Rockland | 113 |
| Rocky soil, excavation | 420 |
| Rod couplings..... | 86 |
| Rod, threaded..... | 86 |
| Roller/plunger detector | 371 |
| Romex | 98-100 |
| clamps | 119 |
| Rotary incandescent dimmers | 229 |
| Rotating beacons..... | 369 |
| Round | |
| box covers | 136 |
| cylinder lampholder | 169 |
| fiberglass boxes..... | 133-136 |
| fixtures, glass ceiling | 162 |
| fixtures, opal glass utility..... | 165 |
| fixtures, walkway | 190 |
| fixtures, white trim..... | 166 |
| flanges, carpet | 156 |
| floor box covers | 154 |
| floor outlet boxes | 153 |
| luminaires | 191-192 |
| poles | 197-198 |
| RSC (rigid steel conduit)..... | 12 |
| Runcina | 110, 112 |
| Running thread, steel | 53 |

S

| | |
|-----------------------------|------------------|
| S type flexible cord | 89, 96 |
| Safety clips | 159 |
| Safety switches..... | 271, 275-282 |
| 240 volt general duty | 275 |
| 240 volt heavy duty..... | 276-277 |
| 600 volt heavy duty..... | 278-281 |
| rating | 271 |
| Safety wire and cable | 159 |
| Sail switches, hookup | 380 |
| Sales tax | 5 |
| Sand encasement..... | 15 |
| Sand, excavation | 420 |
| Scaffold work | 6 |
| Scalloped | 110, 112 |
| Schedule 40 PVC | |
| conduit | 37 |
| couplings | 38, 39 |
| elbows | 38 |
| Schedule 80 PVC | |
| conduit | 37 |
| elbows | 38 |
| Scheduling..... | 6, 8 |
| Screw cover boxes | |
| | 146-147, 148-149 |

| | |
|---|--------------|
| Screw cover wireway..... | 328 |
| Screw-in fuses | 271 |
| Screw terminals | 533 |
| SE-SER plastic jacket cable | 107 |
| Sealing fittings, PVC coated..... | 84-85 |
| Sectional box receptacle assemblies..... | 510-513 |
| Sectional box switch assemblies | |
| 15 amp..... | 471-478 |
| 20 amp..... | 479-486 |
| Sectional switch boxes | 119, 124 |
| Sections, duct | 337 |
| Self illuminating exit fixtures | 173 |
| Self-stripping connectors | 115 |
| Semi-adjustable floor boxes | |
| cast iron | 153-155 |
| sheet metal | 153-154 |
| Semi-flush mounted socket | 317 |
| Semi-jumbo switch plates..... | 266 |
| Service drop wire..... | 110-111 |
| Service entrance cable | 88, 101 |
| Service entrance caps, PVC..... | 42 |
| Service entrance equipment..... | 269-334 |
| checklist..... | 273 |
| Service fittings | 342 |
| Service section | 269 |
| Set screw connectors, steel..... | 74 |
| Set screw couplings | |
| malleable | 74 |
| steel EMT | 23 |
| Setter..... | 111 |
| SEU cable..... | 89, 101 |
| SEU type wire..... | 107 |
| Seven circuit overhead distribution systems | 434 |
| Sheet metal | |
| floor boxes | 153-154 |
| hinged cover pull boxes .. | 147-148 |
| JIC wiring | 150-151 |
| panels for JIC enclosures | 152 |
| raintight screw cover pull boxes | 148-149 |
| raintight hinge cover pull boxes | 149-150 |
| screw cover pull boxes .. | 146-149 |
| tray, communications..... | 519 |
| Shepherd | 111 |
| Shielded cable | 104 |
| Shielded universal lampholder..... | 168 |
| Shopping subcontractor bids | 9 |
| Shoring | 420 |
| Short-circuit interrupting capacity | 271 |
| Show Me video, viewing..... | 5 |
| Side or back wiring, switches..... | 223-232 |
| Side-mounted single-lamp fixtures..... | 174 |
| Side-wired receptacles | 237-245 |
| Side-wired switches..... | 223-232 |
| Side/back wired receptacles | 237-245 |
| Side/back wired switches..... | 225, 227-230 |
| Signal | |
| cabinets | 327 |
| systems | 365-372 |
| terminal cabinets | 327 |
| transformers | 366, 370 |
| Silent switches..... | 219 |
| Silicon-bronze conduit | 15 |
| Single conductor cable | 104 |
| Single decorator receptacles..... | 244 |
| Single face exit fixtures..... | 171, 173 |
| Single gang | |
| switch boxes | 137-138, 141 |
| switch rings..... | 129-130 |

| | | | |
|-----------------------------|----------------------------------|-----------------------------|-------------------------------|
| Single pole | Squeeze flexible conduit | Subcontractor listings | rapid-start |
| space, breakers in | connectors | Subgrade conditions | slimline |
| switches | Stainless steel raceway | Sub-panels | T17 preheat lamps |
| Single receptacles | Staking duct | Suffolk | T9 circular fluorescent lamps |
| | Standard colors, wiring | Sump pumps, hookup | Taft |
| assemblies | devices | Super metalarc lights | Takeoff |
| plates | Standard switches | Supervision | cable tray |
| underfloor raceway | Standard voltage lamps | Support material, special | conduit |
| Single stroke | Standard wall | Supporting straps | consistency |
| bells | GRS conduit | Supports | excavation |
| chimes | steel conduit, flex | cable tray | lighting fixtures |
| Single-lamp strip fixtures | Standby electrical generators | duct | motor control equipment |
| Sirens | Standby engine-generators | GRS | outlet boxes |
| horns | hookup | Surface cabling | underfloor duct |
| Sizes | Standpipes, underfloor | Surface covers | wire |
| outlet box | raceway | Surface metal raceway | wiring devices |
| wire | Starter/circuit breaker, | assemblies | work sheet |
| SJ type flexible cord | bus duct | Surface mounted | Tamper-resistant (TR), cost |
| SJO type flexible cord | starter/fusible switch, | breaker enclosures | adjustment for |
| Slab, transformer | bus duct | buzzers | Tandem breakers |
| Sleeves | Starters | fluorescent fixtures | Tap & splice adapter |
| Slide control dimmers | combination | incandescent fixtures | Tap boxes, bus duct |
| Slimline lamps | magnetic | push buttons | Tapered poles |
| Smart buildings | motor | screw cover boxes | Taxes |
| Smoke detectors | motor, manual | single circuit light track | T-bar fixtures |
| SO type flexible cord | with stainless steel covers | Surface raceway | Tee |
| Soapstone duct | Station wire connectors | communications | bus duct |
| Sockets | Stations, control | fittings | ladder tray |
| cable contacts | Stats, outside air, hookup | Suspension system, lighting | louvered cable tray |
| meter | Steel | Swan | Telephone |
| Sodium lamps | boxes, overfloor raceway | Swanate | plates |
| Solder cup contacts | conduit blank body covers | Sweetbriar | terminal cabinets |
| Solder type lugs | conduit, rigid | Switch assemblies | Telephone cable |
| Solderless type lugs | flex conduit assemblies | handy box | connectors |
| Solenoid valves, hookup | hex nuts | one and two gang | fittings |
| Solid armored cable | messenger strand | sectional box | Telephone-communications |
| Solid communications | poles | Switch boxes | pole |
| cable | raceway base | fiberglass | Telephone-power |
| Solid direct burial cable | raceway cover | four gang | poles |
| Solid wire | raceway fittings | single gang | Temperature |
| Spacers | reducing bushings | three gang | detectors |
| ceiling | reducing washers | two gang | operating for wire |
| conduit | running thread | Switch control schemes | Temporary electrical service |
| connectors | set screw connectors | Switch handles, | Temporary power |
| plastic | straps | illuminated | Terminal blocks |
| Spaniel | surface raceway | Switch legs | Terminal cabinets |
| Sparate | Steel channel, overhead | Switch plates | Terminations |
| Spare key switches | distribution, fittings | deep | aluminum |
| Sparrow | Steel channel (strut) & fittings | jumbo | GRS |
| Special outlet boxes | Steel compression EMT | semi-jumbo | rigid conduit |
| Special support material | connectors | Switch ring | Terrier |
| Special voltage lamps | couplings | bus duct | Test blocks |
| Specialty switches | Steel fittings | Switches | Testing, service entrance |
| Specialty, choosing | overfloor raceway | bus duct | equipment |
| Specification grade | surface raceway | commercial | TF type wire |
| receptacles | Steel frame fluorescent | disconnect | TFF type wire |
| switches | fixtures | entry release | TFFN type wire |
| Spherical lampholder | Steel tube EMT | grounded | THC connector for RG/U |
| Splice connectors, | Stem | handy box assemblies | cable |
| telephone cable | Stephens | industrial | Thermal circuit breakers |
| Split adapters, EMT | Stepped base lampholders | key operated | Thermal magnetic |
| Split bolt connectors | STO type flexible cord | momentary control | breakers |
| Spray paint, enamel | Straight couplings, P&C | one gang assemblies | Thermoplastic insulation |
| Square | Strain relief cable cover | quiet | THHN type wire |
| boxes | Stranded cable | residential | Thin wall EMT |
| exterior walkway luminaires | armored | safety | Threaded hubs, boxes |
| fiberglass boxes | communications | sectional box assemblies | Threaded rod, steel |
| glass fixtures | direct burial | side or back wiring | Threading |
| luminaires | service entrance | specialty | wire |
| opal glass utility drum | Stranded wire | time release | GRS |
| fixture | Straps | two gang assemblies | Threadless connectors |
| outlet boxes | malleable | Switching whips | Three conductor lugs |
| poles, hinged | PVC coated | System engineering, | Three gang boxes |
| switch rings | steel, one hole | channel wiring | floor |
| tapered steel poles | supporting | T12 lamps | switch |
| walkway fixtures | Street light poles | high output | Three lamp fluorescent |
| white glass light fixture | Street luminaires | preheat | fixtures |
| Square base aluminum light | Stress cone | T12 lamps | Three phase circuit |
| poles | Strip fixtures | high output | Three pole |
| poles | Strombus | preheat | contactors |
| | | | starters |

Buy similar Craftsman Book Co. titles here: <https://www.Craftsman-Book.com>

Practical References for Builders

Electrical Blueprint Reading Revised eBook

Shows how to read and interpret electrical drawings, wiring diagrams, and specifications for constructing electrical systems. Shows how a typical lighting and power layout would appear on a plan, and explains what to do to execute the plan. Describes how to use a panelboard or heating schedule, and includes typical electrical specifications.

208 pages, 8½ x 11

eBook (PDF) also available; \$14.88 at www.craftsman-book.com

Code Check Electrical 7th Edition

This 7th edition of Code Check Electrical has been completely updated to the 2014 & 2011 *National Electrical Code* and the 2012 *International Residential Code*. Spiral bound, a flip chart with durable, laminated pages, this reliable resource clearly details how to avoid the most common electrical violations, while stressing the central safety principles behind the 2014 & 2011 *National Electrical Code*. This edition covers every type of residential electrical system, offering the most up-to-date information on grounding, bonding, service panels, branch circuits, GFCIs and AFCIs, switches, receptacles, and so much more. Over a hundred tables and figures make this the on-the-job choice for electricians, contractors, and inspectors.

31 pages, 8½ x 11, \$19.95

Also available: **Code Check Electrical 6th Edition, which is based on the 2011 NEC and the 2009 IRC, \$19.95**

Building Code Compliance for Contractors & Inspectors

An answer book for both contractors and building inspectors, this manual explains what it takes to pass inspections under the 2009 *International Residential Code*. It includes a code checklist for every trade, covering some of the most common reasons why inspectors reject residential work — footings, foundations, slabs, framing, sheathing, plumbing, electrical, HVAC, energy conservation and final inspection. The requirement for each item on the checklist is explained, and the code section cited so you can look it up or show it to the inspector. Knowing in advance what the inspector wants to see gives you an (almost unfair) advantage. To pass inspection, do your own pre-inspection before the inspector arrives. If your work requires getting permits and passing inspections, put this manual to work on your next job. If you're considering a career in code enforcement, this can be your guidebook. **8½ x 11, 232 pages, \$32.50**

eBook (PDF) also available; \$16.25 at www.craftsman-book.com

Construction Contract Writer



Relying on a "one-size-fits-all" boilerplate construction contract to fit your jobs can be dangerous — almost as dangerous as a handshake agreement. *Construction Contract Writer* lets you draft a contract in minutes that precisely fits your needs and the particular job, and meets both state and federal requirements. You just answer a series of questions — like an interview — to construct a legal contract for each project you take on. Anticipate where disputes could arise and settle them in the contract before they happen. Include the warranty protection you intend, the payment schedule, and create subcontracts from the prime contract by just clicking a box. Includes a feedback button to an attorney on the Craftsman staff to help should you get stumped — **No extra charge. \$149.95.** Download the *Construction Contract Writer* at: <http://www.constructioncontractwriter.com>

Journeyman Electrician's Preparation & Study Guide eBook

This is not only a great study guide filled with sample electrician's exam questions — it teaches you how to quickly turn to the code section that answers the questions. Most electrician's exams give you about 2 minutes per question — not enough time to browse through 800 pages of fine print looking for each answer. This manual, based on the 2008 and 2011 NEC editions, explains how the Code is organized, so you understand where the information you need is located. Then it shows how to rearrange and tab your copy of the Code to streamline your search efforts. Next, you learn a step-by-step search procedure, in which you're shown how to analyze the question to determine its subject, know where to look in the index, find the exact article, then turn right to the Code section that answers your question. **96 pages**

eBook (PDF); \$17.00 at www.craftsman-book.com

Electrician's Exam Preparation Guide to the 2014 NEC

Need help in passing the apprentice, journeyman, or master electrician's exam? This is a book of questions and answers based on actual electrician's exams over the last few years. Almost a thousand multiple-choice questions — exactly the type you'll find on the exam — cover every area of electrical installation: electrical drawings, services and systems, transformers, capacitors, distribution equipment, branch circuits, feeders, calculations, measuring and testing, and more. It gives you the correct answer, an explanation, and where to find it in the latest NEC. Also tells how to apply for the test, how best to study, and what to expect on examination day. Includes a certificate for a FREE download of an Interactive Study Center, with all the questions in the book in test-yourself software that makes studying for the exam almost fun! Based on the 2014 NEC.

352 pages, 8½ x 11, \$59.50

eBook (PDF) also available; \$29.75 at www.craftsman-book.com

Also available: **Electrician's Exam Preparation Guide 2011, \$54.50**

eBook (PDF) also available; \$27.25 at www.craftsman-book.com

ElectriCalc Pro Calculator

This unique calculator, based on the 2005 *National Electrical Code* and updateable to future NEC codes, solves electrical problems in seconds: Calculates wire sizes, gives you integrated voltage drop solutions, conduit sizing for 12 types of conduit, and finds motor full-load amps per the current NEC. Also offers one-button parallel and de-rated wire sizing, computes fuse and breaker sizes, sizes overload protection, calculates service and equipment grounding conductor sizes, finds NEMA starter sizes, works in volts, volt-amps, watts, kVA, kW, PF%, and DC resistance, and even operates as a math calculator. **3½ x 7, \$99.95**

Insurance Restoration Contracting: Startup to Success

Insurance restoration — the repair of buildings damaged by water, fire, smoke, storms, vandalism and other disasters — is an exciting field of construction that provides lucrative work that's immune to economic downturns. And, with insurance companies funding the repairs, your payment is virtually guaranteed. But this type of work requires special knowledge and equipment, and that's what you'll learn about in this book. It covers fire repairs and smoke damage, water losses and specialized drying methods, mold remediation, content restoration, even damage to mobile and manufactured homes. You'll also find information on equipment needs, training classes, estimating books and software, and how restoration leads to lucrative remodeling jobs. It covers all you need to know to start and succeed as the restoration contractor that both homeowners and insurance companies call on first for the best jobs. **640 pages, 8½ x 11, \$69.00**

eBook (PDF) also available; \$34.50 at www.craftsman-book.com

Residential Wiring to the 2011 NEC® eBook

This completely revised book explains how to install rough and finish wiring in new construction, alterations, and additions. It takes you from basic electrical theory to advanced wiring methods, updated to comply with the 2011 *National Electrical Code*. You'll find complete instructions on troubleshooting and repair of existing wiring, with hundreds of drawings and photos showing you how to plan and install wiring to code. Includes demand factors, circuit loads, and the formulas you need. Every subject is referenced to the 2011 NEC®, with many of the most-needed NEC® tables reproduced to help you install wiring that passes inspection the first time. **304 pages.**

Available only as an eBook (PDF) \$24.00 at www.craftsman-book.com

Residential Wiring to the 2008 NEC

This completely revised manual explains in simple terms how to install rough and finish wiring in new construction, alterations, and additions. It takes you from basic electrical theory to current wiring methods that comply with the 2008 *National Electrical Code*. You'll find complete instructions on troubleshooting and repairs of existing wiring, and how to extend service into additions and remodels. Hundreds of drawings and photos show you the tools and gauges you need, and how to plan and install the wiring. Includes demand factors, circuit loads, the formulas you need, and over 20 pages of the most-needed 2008 NEC tables to help your wiring pass inspection the first time. Includes a CD-ROM with an Interactive Study Center that helps you retain what you've learned, and study for the electrician's exam. Also on the CD is the entire book in PDF format, with easy search features so you can quickly find answers to your residential wiring questions. **304 pages, 8½ x 11, \$42.00**

eBook (PDF) also available; \$21.00 at www.craftsman-book.com

Electrical Inspection Notes

In this pocket-sized flip chart, you'll find code compliance information to help you make sure that every part of your electrical work is up to code. Here you'll find checklists, calculations, diagrams, plain-English code explanations, tables and charts, and who is responsible for what task during each step of the project. It lists everything to check for in the design stage, what to check for in interior electrical work, conductors, grounding, wiring methods, conduits, outlets, circuit panels, lighting, testing methods, exterior lighting, electrical service, heating, low voltage and more.

236 pages, 3 x 6, \$24.95

Estimating Electrical Construction Revised

Estimating the cost of electrical work can be a very detailed and exacting discipline. It takes specialized skills and knowledge to create reliable estimates for electrical work. See how an expert estimates materials and labor for residential and commercial electrical construction. Learn how to use labor units, the plan take-off, and the bid summary to make an accurate estimate, how to deal with suppliers, use pricing sheets, and modify labor units. This book provides extensive labor unit tables and blank forms on a CD for estimating your next electrical job. **272 pages, 8½ x 11, \$59.00**

eBook (PDF) also available; \$29.50 at www.craftsman-book.com

2011 National Electrical Code

This new electrical code incorporates sweeping improvements to make the code more functional and user-friendly. Here you'll find the essential foundation for electrical code requirements for the 21st century. With hundreds of significant and widespread changes, this 2011 NEC contains all the latest electrical technologies, recently-developed techniques, and enhanced safety standards for electrical work. This is the standard all electricians are required to know, even if it hasn't yet been adopted by their local or state jurisdictions. **880 pages, 8½ x 11, \$85.00**

Also available: **2008 National Electrical Code, \$75.00**

National Electrical Code Quick-Card 2014 NEC

In this unique, 6-page laminated quick-reference guide, you get all the *National Electrical Code* (NEC) essentials you need to know based on the current 2014 NEC. **6 pages, 8½ x 11, \$7.95**



Craftsman Book Company
6058 Corte del Cedro
Carlsbad, CA 92011

Call me.

1-800-829-8123

Fax (760) 438-0398

Name _____

e-mail address (for order tracking and special offers) _____

Company _____

Address _____

City/State/Zip _____

☐ This is a residence

Total enclosed _____ (In California add 7.5% tax)

*Free Media Mail shipping, within the US,
when your check covers your order in full.*

In A Hurry?

We accept phone orders charged to your

☐ Visa, ☐ MasterCard, ☐ Discover or ☐ American Express

Card# _____

Exp. date _____ Initials _____

Tax Deductible: Treasury regulations make these references tax deductible when used in your work. Save the canceled check or charge card statement as your receipt.

Order online www.craftsman-book.com
Free on the Internet! Download any of Craftsman's estimating databases for a 30-day free trial! www.craftsman-book.com/downloads

National Electrical Code Quick-Card 2011 NEC

In this unique, 6-page laminated quick-reference guide, you get all the *National Electrical Code* (NEC) essentials you need to know based on the 2011 NEC. **6 pages, 8½ x 11, \$7.95**

Electrical Blueprint Symbols Quick-Card

This NEW updated 4-page, laminated guide provides the essential electrical symbols used in architectural plans and engineering drawings. A must have for every electrical contractor. **4 pages, 8½ x 11, \$7.95**

Wiring a House 5th Edition

A master electrician gives you the tips and shortcuts he's learned in over 30 years of wiring houses to meet code and to provide years of reliable service. Here you'll learn what materials work best in what application, which tools get the job done in the fastest time, and how to figure out and design the right wiring layout for any residential job, whether the entire house, or just a room. You also see how to install main service panels, ensure that the house is properly grounded, and install receptacles, GFCIs, switches, fixtures and appliances per NEC requirements. Dozens of diagrams and full-color illustrations show you exactly how the work goes together.

364 pages, 8½ x 11, \$24.95

DeWalt Electrical Code Reference

Based on the 2005 and 2008 National Electrical Codes, this spiral-bound reference illustrates hundreds of the most common electrical Code requirements and installations. Color illustrations and photos show exactly what the Code requires, so there's no guesswork. Find what you need, illustrated on thick glossy industrial-strength pages made to survive — even in your tool kit. Covers branch circuits, receptacle placement, 3- and 4-way switch wiring, panelboard wiring, GFCI and AFCI requirements, conductor ampacity tables, and workspace requirements. You'll find information on terminals, common wiring methods, overcurrent protection, wiring services calculations, smoke detector wiring; and wiring layout for bedrooms, bathrooms, kitchens, dining and living rooms, laundry rooms and garages. Gives requirements for HVAC, conductor sizing, subpanels, underground raceways, service grounding, and ground rods.

80 pages, 5 x 8, \$19.95. By: American Contractors Exam Service

10-Day Money Back Guarantee

- ☐ 32.50 Building Code Compliance for Contractors & Inspectors
- ☐ 19.95 Code Check Electrical 7th Edition
- ☐ 19.95 Code Check Electrical 6th Edition
- ☐ 19.95 DeWalt Electrical Code Reference
- ☐ 99.95 ElectriCalc Pro Calculator
- ☐ 7.95 Electrical Blueprint Symbols Quick-Card
- ☐ 24.95 Electrical Inspection Notes
- ☐ 59.50 Electrician's Exam Prep Guide to the 2014 NEC
- ☐ 54.50 Electrician's Exam Prep Guide to the 2011 NEC
- ☐ 59.00 Estimating Electrical Construction Revised
- ☐ 69.00 Insurance Restoration Contracting: Startup to Success
- ☐ 85.00 2011 National Electrical Code
- ☐ 75.00 2008 National Electrical Code
- ☐ 7.95 National Electrical Code Quick-Card 2014 NEC
- ☐ 7.95 National Electrical Code Quick-Card 2011 NEC
- ☐ 42.00 Residential Wiring to the 2008 NEC
- ☐ 24.95 Wiring a House 5th Edition
- ☐ 87.75 National Electrical Estimator with FREE National Estimator Download
- ☐ FREE Full Color Catalog

Prices subject to change without notice

Download all of Craftsman's most popular costbooks for one low price with the Craftsman Site License: www.craftsmansitelicense.com